

Chipsmall Limited consists of a professional team with an average of over 10 year of expertise in the distribution of electronic components. Based in Hongkong, we have already established firm and mutual-benefit business relationships with customers from, Europe, America and south Asia, supplying obsolete and hard-to-find components to meet their specific needs.

With the principle of "Quality Parts, Customers Priority, Honest Operation, and Considerate Service", our business mainly focus on the distribution of electronic components. Line cards we deal with include Microchip, ALPS, ROHM, Xilinx, Pulse, ON, Everlight and Freescale. Main products comprise IC, Modules, Potentiometer, IC Socket, Relay, Connector. Our parts cover such applications as commercial, industrial, and automotives areas.

We are looking forward to setting up business relationship with you and hope to provide you with the best service and solution. Let us make a better world for our industry!



## Contact us

Tel: +86-755-8981 8866 Fax: +86-755-8427 6832

Email & Skype: info@chipsmall.com Web: www.chipsmall.com

Address: A1208, Overseas Decoration Building, #122 Zhenhua RD., Futian, Shenzhen, China









# **DATA SHEET**

**WIRELESS COMPONENTS** 

Ceramic Patch Antenna ANT1212B00FT1575S

GPS PIN 12 × 12 × 4 mm



YAGEO Phicomp



Wireless Components Ceramic Patch Antenna

#### <u>FEATURES</u>

- Compact size
- High radiation efficiency
- Pin-solder process
- RoHS compliant

#### **APPLICATIONS**

- Navigation device
- Telematics box
- Fleet management

#### ORDERING INFORMATION

All part numbers are identified by the series, packing type, material, size, antenna type, working frequency and packing quantity.

#### **PART NUMBER**

ANT 1212 B 00F T 1575S (1) (2) (3) (4) (5)

(I) PRODUCT

ANT = Antenna

(2) SIZE

12 = 12x12 mm

(3) ANTENNA TYPE

B = Bulk Antenna

(4) SERIAL NO.

00F

(5) PACKING TYPE

T = Tray

(6) WORKING FREQUENCY

1575 =1.575 GHz

PHYCOMP CTC

CAN43934220F1581B

12NC

43934220F158




#### **SPECIFICATION**

Table I

DESCRIPTION	VALUE
Centre Frequency	I 580 ± 3 MHz
Bandwidth	5 MHz (Typ.)
Gain	-1.5 dBic (Typ.)
VSWR	2.0 Max
Polarization	Right Hand Circular Polarization
Axis Ratio	≦ 3dB
Beam Width	> I20 degrees
Impedance	50 Ω
Operating Temperature	-40~105 °C


#### NOTE

- I. Based on  $30\times30\text{mm}^2$  square ground plane.
- 2. Centre frequency will be offset to working frequency while changes of customer's housing and ground plane.
- 3. Please contact local sales if you need customized design to gain optimum antenna performance.




6

#### **ELECTRICAL PERFORMANCES**








2D x-z plane pattern

2D y-z plane pattern



3D radiation pattern

Fig. 4 Radiation Pattern (Frequency = 1580MHz)



Wireless Components Ceramic Patch Antenna

6

### REVISION HISTORY

REVISION DATE CHANGE NOTIFICATION DESCRIPTION

Version 0 Mar 09, 2015

- New data sheet for Patch antenna, PIN Feed size 12×12×4 mm

