



Chipsmall Limited consists of a professional team with an average of over 10 year of expertise in the distribution of electronic components. Based in Hongkong, we have already established firm and mutual-benefit business relationships with customers from,Europe,America and south Asia,supplying obsolete and hard-to-find components to meet their specific needs.

With the principle of “Quality Parts,Customers Priority,Honest Operation,and Considerate Service”,our business mainly focus on the distribution of electronic components. Line cards we deal with include Microchip,ALPS,ROHM,Xilinx,Pulse,ON,Everlight and Freescale. Main products comprise IC,Modules,Potentiometer,IC Socket,Relay,Connector.Our parts cover such applications as commercial,industrial, and automotives areas.

We are looking forward to setting up business relationship with you and hope to provide you with the best service and solution. Let us make a better world for our industry!



Contact us

Tel: +86-755-8981 8866 Fax: +86-755-8427 6832

Email & Skype: info@chipsmall.com Web: www.chipsmall.com

Address: A1208, Overseas Decoration Building, #122 Zhenhua RD., Futian, Shenzhen, China






EPCOS Sample Kit 2014

Chip Inductors

SIMID 1812-C, B82432X002



www.epcos.com

SMT Inductors – SIMID 1812-C

L_R	μH	1.0	1.5	1.8	2.2	3.3	3.9	4.7	6.8
Q _{min}		40	40	40	40	40	40	40	40
f _L	MHz	1	1	1	1	1	1	1	1
f _Q	MHz	7.96	7.96	7.96	7.96	7.96	7.96	7.96	7.96
I _R	mA	600	535	490	480	425	410	390	360
R _{max}	Ω	0.28	0.35	0.41	0.43	0.55	0.59	0.65	0.78
f _{res, min}	MHz	200	120	100	90	60	50	40	35
Ord. code	B82432	C1102K000	C1152K000	C1182K000	C1222K000	C1332K000	C1392K000	C1472K000	C1682K000
L_R	μH	8.2	10	15	18	22	33	39	47
Q _{min}		40	40	30	30	30	30	30	30
f _L	MHz	1	1	0.1	0.1	0.1	0.1	0.1	0.1
f _Q	MHz	7.96	7.96	2.52	2.52	2.52	2.52	2.52	2.52
I _R	mA	330	320	280	270	260	230	220	210
R _{max}	Ω	0.92	0.98	1.25	1.35	1.45	1.85	2.05	2.30
f _{res, min}	MHz	30	28	21	18	16	13	12	12
Ord. code	B82432	C1822K000	C1103K000	C1153K000	C1183K000	C1223K000	C1333K000	C1393K000	C1473K000
L_R	μH	68	100	150	220	330	470	680	1000
Q _{min}		30	30	30	30	30	30	30	30
f _L	MHz	0.1	0.1	0.1	0.1	0.1	0.1	0.1	0.1
f _Q	MHz	2.52	0.796	0.796	0.796	0.796	0.796	0.796	0.796
I _R	mA	190	145	130	115	85	75	65	55
R _{max}	Ω	2.80	4.70	6.10	7.50	14.1	17.5	25.0	32.0
f _{res, min}	MHz	10	8	7	6	4.5	4	3.3	2.8
Ord. code	B82432	C1683K000	C1104K000	C1154K000	C1224K000	C1334K000	C1474K000	C1684K000	C1105K000

SIMID® is a registered trademark. Tolerance: K_A ± 10%. Additional values upon request.



1.0 μH



1.5 μH



1.8 μH



2.2 μH



3.3 μH



3.9 μH



4.7 μH



6.8 μH



8.2 μH



10 μH



15 μH



18 μH



22 μH



33 μH



39 μH



47 μH



68 μH



100 μH



150 μH



220 μH



330 μH



470 μH



680 μH



1000 μH

Important information: It is incumbent on the customer to check and decide whether a product is suitable for use in a particular application. Our products are described in detail in our data sheets. Our *Important notes* and the product-specific *Cautions and warnings* must be observed. All relevant information is available through our sales offices.