

Chipsmall Limited consists of a professional team with an average of over 10 year of expertise in the distribution of electronic components. Based in Hongkong, we have already established firm and mutual-benefit business relationships with customers from, Europe, America and south Asia, supplying obsolete and hard-to-find components to meet their specific needs.

With the principle of "Quality Parts, Customers Priority, Honest Operation, and Considerate Service", our business mainly focus on the distribution of electronic components. Line cards we deal with include Microchip, ALPS, ROHM, Xilinx, Pulse, ON, Everlight and Freescale. Main products comprise IC, Modules, Potentiometer, IC Socket, Relay, Connector. Our parts cover such applications as commercial, industrial, and automotives areas.

We are looking forward to setting up business relationship with you and hope to provide you with the best service and solution. Let us make a better world for our industry!



# Contact us

Tel: +86-755-8981 8866 Fax: +86-755-8427 6832

Email & Skype: info@chipsmall.com Web: www.chipsmall.com

Address: A1208, Overseas Decoration Building, #122 Zhenhua RD., Futian, Shenzhen, China









## Is Now Part of



# ON Semiconductor®

To learn more about ON Semiconductor, please visit our website at <a href="https://www.onsemi.com">www.onsemi.com</a>

ON Semiconductor and the ON Semiconductor logo are trademarks of Semiconductor Components Industries, LLC dba ON Semiconductor or its subsidiaries in the United States and/or other countries. ON Semiconductor owns the rights to a number of patents, trademarks, copyrights, trade secrets, and other intellectual property. A listing of ON Semiconductor's product/patent coverage may be accessed at www.onsemi.com/site/pdf/Patent-Marking.pdf. ON Semiconductor reserves the right to make changes without further notice to any products herein. ON Semiconductor makes no warranty, representation or guarantee regarding the suitability of its products for any particular purpose, nor does ON Semiconductor assume any liability arising out of the application or use of any product or circuit, and specifically disclaims any and all liability, including without limitation special, consequential or incidental damages. Buyer is responsible for its products and applications using ON Semiconductor products, including compliance with all laws, regulations and safety requirements or standards, regardless of any support or applications information provided by ON Semiconductor. "Typical" parameters which may be provided in ON Semiconductor data sheets and/or specifications can and do vary in different applications and actual performance may vary over time. All operating parameters, including "Typicals" must be validated for each customer application by customer's technical experts. ON Semiconductor does not convey any license under its patent rights nor the rights of others. ON Semiconductor products are not designed, intended, or authorized for use as a critical component in life support systems or any EDA Class 3 medical devices with a same or similar classification in a foreign jurisdiction or any devices intended for implantation in the human body. Should Buyer purchase or use ON Semiconductor products for any such unintended or unauthorized application, Buyer shall indemnify and hold ON Semiconductor and its officers, employees, emplo




August 2015


# **BAT54T / BAT54ST Schottky Barrier Diode**

## **Features**

- · Low Forward Voltage Drop
- · Surface Mount Device at 0.95 mm Maximum Height
- MSL 1 per J-STD-020
- · Pb Free and RoHS Compliant
- · Matte Sn Lead Finish
- · Green Mold Compound







## **Ordering Information**

| Part Number | Top Mark | Package    | Packing Method |
|-------------|----------|------------|----------------|
| BAT54T      | L1       | SOT-523 3L | Tape and Reel  |
| BAT54ST     | L4       | SOT-523 3L | Tape and Reel  |

## **Absolute Maximum Ratings**

Stresses exceeding the absolute maximum ratings may damage the device. The device may not function or be operable above the recommended operating conditions and stressing the parts to these levels is not recommended. In addition, extended exposure to stresses above the recommended operating conditions may affect device reliability. The absolute maximum ratings are stress ratings only. Values are at  $T_A = 25^{\circ}\text{C}$  unless otherwise noted.

| Symbol             | Parameter                          | Value       | Unit |
|--------------------|------------------------------------|-------------|------|
| V <sub>RRM</sub>   | Maximum Repetitive Reverse Voltage | 30          | V    |
| I <sub>F(AV)</sub> | Average Rectified Forward Current  | 200         | mA   |
| T <sub>J</sub>     | Operating Junction Temperature     | 125         | °C   |
| T <sub>STG</sub>   | Storage Temperature Range          | -55 to +125 | °C   |

## Thermal Characteristics(1)

Values are at  $T_A = 25$ °C unless otherwise noted.

| Symbol          | Parameter   | Value | Unit |
|-----------------|---|-------|------|
| $P_{D}$         | Power Dissipation   | 150   | mW   |
| $R_{\theta JA}$ | Thermal Resistance, Junction-to-Ambient                                       | 500   | °C/W |
| ΨJL             | Junction-to-Lead Thermal Characteristics,<br>Thermocouple Soldered to Cathode | 165   | °C/W |

### Note:

1. Device mounted on FR-4 PCB minimum land pad

## **Electrical Characteristics**

Values are at  $T_A = 25$ °C unless otherwise noted. Parameters are tested per individual diode.

| Symbol          | Parameter                 | Conditions   | Min. | Max. | Unit |
|-----------------|---------------------------|--|------|------|------|
| BV <sub>R</sub> | Reverse Breakdown Voltage | I <sub>R</sub> = 100 μA  | 30   |      | V    |
| I <sub>R</sub>  | Reverse Leakage Current   | V <sub>R</sub> = 25 V  |      | 2    | μΑ   |
| V <sub>F</sub>  | Forward Voltage           | I <sub>F</sub> = 0.1 mA  |      | 0.24 |      |
|                 |                           | I <sub>F</sub> = 1 mA  |      | 0.32 |      |
|                 |                           | I <sub>F</sub> = 10 mA   |      | 0.40 | V    |
|                 |                           | I <sub>F</sub> = 30 mA   |      | 0.50 |      |
|                 |                           | I <sub>F</sub> = 100 mA  |      | 1.00 |      |
| C <sub>T</sub>  | Total Capacitance         | V <sub>R</sub> = 1 V, f = 1 MHz  |      | 10   | pF   |
| t <sub>rr</sub> | Reverse Recovery Time     | $I_F = I_R = 10 \text{ mA}, I_{RR} = 0.1 \text{ x } I_R$<br>$R_L = 100 \Omega$ |      | 5    | ns   |

## **Typical Performance Characteristics**




Figure 1. Forward Current vs. Forward Voltage




Figure 2. Reverse Current vs. Reverse Voltage





Figure 3. Total Capacitance vs. Reverse Voltage



**Figure 4. Power Derating Curve** 

## **Physical Dimensions** 1.80 1.40 0.35 -0.40 (3x) 0,15 0.65 (3X) 3 0.90 1.80 0.70 1.40 1.15 2 (0.20) 0.30 0.15 (2X) 0.50 0.50 0.5 0.5 LAND PATTERN RECOMMENDATION 0.30 MAX 10° MAX 10° MAX 0.85 0.95 0.60 0.60 0.25 8° 0.10 MAX 0° 0.10 0.40 (2X) NOTES: FAIRCHILD A. REFERENCE TO EIAJ SC75 STANDARD. B. ALL DIMENSIONS ARE IN MILLIMETERS. C DOES NOT COMPLY EIAJ SC75 STANDARD. D. DIMENSIONS ARE EXCLUSIVE OF BURRS, MOLD FLASH AND TIE BAR PROTRUSIONS. E. LAND PATTERN RECOMMENDATION BASE FROM EIAJ STD. F. DRAWING FILE NAME: MKT-MAD03B REV1 Figure 5. 3-Lead, SOT523



#### TRADEMARKS

The following includes registered and unregistered trademarks and service marks, owned by Fairchild Semiconductor and/or its global subsidiaries, and is not intended to be an exhaustive list of all such trademarks.

BitSiC™ Green FPS™

Build it Now™ Green FPS™ e-Series™

CorePLUSTM GmaxTM GTOTM GTOTM GTOTM CROSSVOLTTM IntelliMAXTM ISOPI ANARTM

Current Transfer Logic™ Making Small Speakers Sound Louder DEUXPEED® and Better™

Dual Cool™

EcoSPARK®

EfficientMax™

ESBC™

MicroPak™

MicroPak™

MicroPak™

MicroPak™

Fairchild® MillerDrive™
Fairchild Semiconductor®
FACT Quiet Series™ MTi®
FACT® MTx®
FastvCore™ MVN®
FETBench™ mWSaver®

OptoHiT<sup>TM</sup>
OPTOLOGIC<sup>®</sup>

OPTOPLANAR®

Power Supply WebDesigner™

PowerTrench® PowerXS™

Programmable Active Droop™

QFĔT<sup>®</sup>
QS™
Quiet Series™
RapidConfigure™

Saving our world, 1mW/W/kW at a time™

SignalWise™ SmartMax™ SMART START™

Solutions for Your Success™

SPM®
STEALTH™
SuperFET®
SuperSOT™-3
SuperSOT™-6
SuperSOT™-8
SupreMOS®
SyncFET™
Sync-Lock™

SYSTEM SYSTEM

TinyBoost®
TinyBuck®
TinyCalc™
TinyLogic®
TINYOPTO™
TinyPower™
TinyPWM™
TinyWire™
TranSiC™
TriFault Detect

TriFault Detect™ TRUECURRENT®\* µSerDes™

SerDes\*
UHC®\*
Ultra FRFET™
UniFET™
VCX™
VisualMax™
VoltagePlus™
XS™
Xsens™

仙童™

\* Trademarks of System General Corporation, used under license by Fairchild Semiconductor.

#### ISCLAIMER

FAIRCHILD SEMICONDUCTOR RESERVES THE RIGHT TO MAKE CHANGES WITHOUT FURTHER NOTICE TO ANY PRODUCTS HEREIN TO IMPROVE RELIABILITY, FUNCTION, OR DESIGN. TO OBTAIN THE LATEST, MOST UP-TO-DATE DATASHEET AND PRODUCT INFORMATION, VISIT OUR WEBSITE AT <a href="http://www.fairchildsemi.com">http://www.fairchildsemi.com</a>. FAIRCHILD DOES NOT ASSUME ANY LIABILITY ARISING OUT OF THE APPLICATION OR USE OF ANY PRODUCT OR CIRCUIT DESCRIBED HEREIN; NEITHER DOES IT CONVEY ANY LICENSE UNDER ITS PATENT RIGHTS, NOR THE RIGHTS OF OTHERS. THESE SPECIFICATIONS DO NOT EXPAND THE TERMS OF FAIRCHILD'S WORLDWIDE TERMS AND CONDITIONS, SPECIFICALLY THE WARRANTY THEREIN, WHICH COVERS THESE PRODUCTS.

#### **AUTHORIZED USE**

Unless otherwise specified in this data sheet, this product is a standard commercial product and is not intended for use in applications that require extraordinary levels of quality and reliability. This product may not be used in the following applications, unless specifically approved in writing by a Fairchild officer: (1) automotive or other transportation, (2) military/aerospace, (3) any safety critical application – including life critical medical equipment – where the failure of the Fairchild product reasonably would be expected to result in personal injury, death or property damage. Customer's use of this product is subject to agreement of this Authorized Use policy. In the event of an unauthorized use of Fairchild's product, Fairchild accepts no liability in the event of product failure. In other respects, this product shall be subject to Fairchild's Worldwide Terms and Conditions of Sale, unless a separate agreement has been signed by both Parties.

#### ANTI-COUNTERFEITING POLICY

Fairchild Semiconductor Corporation's Anti-Counterfeiting Policy. Fairchild's Anti-Counterfeiting Policy is also stated on our external website, www.fairchildsemi.com, under Terms of Use

Counterfeiting of semiconductor parts is a growing problem in the industry. All manufacturers of semiconductor products are experiencing counterfeiting of their parts. Customers who inadvertently purchase counterfeit parts experience many problems such as loss of brand reputation, substandard performance, failed applications, and increased cost of production and manufacturing delays. Fairchild is taking strong measures to protect ourselves and our customers from the proliferation of counterfeit parts. Fairchild strongly encourages customers to purchase Fairchild parts either directly from Fairchild or from Authorized Fairchild Distributors who are listed by country on our web page cited above. Products customers buy either from Fairchild directly or from Authorized Fairchild Distributors are genuine parts, have full traceability, meet Fairchild's quality standards for handling and storage and provide access to Fairchild's full range of up-to-date technical and product information. Fairchild and our Authorized Distributors will stand behind all warranties and will appropriately address any warranty issues that may arise. Fairchild will not provide any warranty coverage or other assistance for parts bought from Unauthorized Sources. Fairchild is committed to combat this global problem and encourage our customers to do their part in stopping this practice by buying direct or from authorized distributors.

#### PRODUCT STATUS DEFINITIONS

## **Definition of Terms**

| Definition of Terms             |                       |   |  |
|---------------------------------|-----------------------|---|--|
| <b>Datasheet Identification</b> | Product Status        | Definition  |  |
| Advance Information             | Formative / In Design | Datasheet contains the design specifications for product development. Specifications may change in any manner without notice.   |  |
| Preliminary                     | First Production      | Datasheet contains preliminary data; supplementary data will be published at a later date. Fairchild Semiconductor reserves the right to make changes at any time without notice to improve design. |  |
| No Identification Needed        | Full Production       | Datasheet contains final specifications. Fairchild Semiconductor reserves the right to make changes at any time without notice to improve the design.   |  |
| Obsolete                        | Not In Production     | Datasheet contains specifications on a product that is discontinued by Fairchild Semiconductor. The datasheet is for reference information only.  |  |

Rev. 176

ON Semiconductor and in are trademarks of Semiconductor Components Industries, LLC dba ON Semiconductor or its subsidiaries in the United States and/or other countries. ON Semiconductor owns the rights to a number of patents, trademarks, copyrights, trade secrets, and other intellectual property. A listing of ON Semiconductor's product/patent coverage may be accessed at <a href="www.onsemi.com/site/pdf/Patent-Marking.pdf">www.onsemi.com/site/pdf/Patent-Marking.pdf</a>. ON Semiconductor reserves the right to make changes without further notice to any products herein. ON Semiconductor assume any liability arising out of the application or use of any product or circuit, and specifically disclaims any and all liability, including without limitation special, consequential or incidental damages. Buyer is responsible for its products and applications using ON Semiconductor products, including compliance with all laws, regulations and safety requirements or standards, regardless of any support or applications information provided by ON Semiconductor. "Typical" parameters which may be provided in ON Semiconductor data sheets and/or specifications can and do vary in different applications and actual performance may vary over time. All operating parameters, including "Typicals" must be validated for each customer application by customer's technical experts. ON Semiconductor does not convey any license under its patent rights nor the rights of others. ON Semiconductor products are not designed, intended, or authorized for use as a critical component in life support systems or any FDA Class 3 medical devices or medical devices with a same or similar classification in a foreign jurisdiction or any devices intended for implantation in the human body. Should Buyer purchase or use ON Semiconductor products for any such unintended or unauthorized application, Buyer shall indemnify and hold ON Semiconductor and its officers, employees, subsidiaries, affiliates, and distributors harmless against all claims, costs, damages, and exp

## **PUBLICATION ORDERING INFORMATION**

#### LITERATURE FULFILLMENT:

Literature Distribution Center for ON Semiconductor 19521 E. 32nd Pkwy, Aurora, Colorado 80011 USA Phone: 303-675-2175 or 800-344-3860 Toll Free USA/Canada Fax: 303-675-2176 or 800-344-3867 Toll Free USA/Canada Email: orderlit@onsemi.com N. American Technical Support: 800–282–9855 Toll Free USA/Canada
Europe, Middle East and Africa Technical Support:
Phone: 421 33 790 2910

Phone: 421 33 790 2910

Japan Customer Focus Center

Phone: 81–3–5817–1050

ON Semiconductor Website: www.onsemi.com

Order Literature: http://www.onsemi.com/orderlit

For additional information, please contact your local Sales Representative