

Chipsmall Limited consists of a professional team with an average of over 10 year of expertise in the distribution of electronic components. Based in Hongkong, we have already established firm and mutual-benefit business relationships with customers from, Europe, America and south Asia, supplying obsolete and hard-to-find components to meet their specific needs.

With the principle of "Quality Parts, Customers Priority, Honest Operation, and Considerate Service", our business mainly focus on the distribution of electronic components. Line cards we deal with include Microchip, ALPS, ROHM, Xilinx, Pulse, ON, Everlight and Freescale. Main products comprise IC, Modules, Potentiometer, IC Socket, Relay, Connector. Our parts cover such applications as commercial, industrial, and automotives areas.

We are looking forward to setting up business relationship with you and hope to provide you with the best service and solution. Let us make a better world for our industry!



Contact us

Tel: +86-755-8981 8866 Fax: +86-755-8427 6832

Email & Skype: info@chipsmall.com Web: www.chipsmall.com

Address: A1208, Overseas Decoration Building, #122 Zhenhua RD., Futian, Shenzhen, China









USB Ranger® 2244

Singlemode Fiber Optic USB 2.0 Extender



Ranger 2244 extends USB 2.0 beyond the desktop up to 10km over singlemode fiber optic cabling using ExtremeUSB® technology.

Ranger 2244 Features

- Powered by ExtremeUSB®. Long reach USB 2.0 enabled by Icron's LionsGate™ USB 2.0 Extension ASIC.
- Extends USB 2.0 high-speed and USB 1.1 (low-speed, full speed) devices up to 10km over fiber optics.
- Supports all USB device types: Control, Interrupt, Bulk and Isochronous at up to 480Mbps.
- Operates with USB 2.0 high-speed host controllers and USB 1.1 classic hosts.
- True plug and play, ready to operate right out of the box. No new driver installation required.
- Supports all major operating systems including Windows®, Mac OS®, and Linux®
- Integrated hub provides four remote USB 2.0 ports. Number of devices can be increased using additional USB hubs.
- Ideal for a wide variety of USB devices, from printers, scanners, hard drives, and audio devices, to touch screens, web cams, and game controllers.
- AC power adapter at remote unit provides standard 500mA to each USB port.
- Power adapter at local unit is not required for normal operation.



USB Ranger® 2244

Applications

- Industrial Control
- Digital Signage
- Home Network Integration
- Medical Device Connectivity

- KVM Extension
- Remote Desktop USB Connections
- Security: web camera, access control.
- · USB Device Sharing: print, scan, storage.

Ordering Information

The Ranger 2244 system includes a Local Extender (LEX) module, a Remote Extender (REX) module, a 2 meter USB cable, and an International power adapter with country specific cord.

Name	Part Number	Description
USB Ranger® 2244	00-00264	4-Port Singlemode Fiber Optic USB 2.0 Extender, International (100-240V) Power Adapter: North American plug
USB Ranger® 2244	00-00265	4-Port Singlemode Fiber Optic USB 2.0 Extender, International (100-240V) Power Adapter: European plug
USB Ranger® 2244	00-00266	4-Port Singlemode Fiber Optic USB 2.0 Extender, International (100-240V) Power Adapter: UK plug
USB Ranger® 2244	00-00267	4-Port Singlemode Fiber Optic USB 2.0 Extender, International (100-240V) Power Adapter: Australian plug

Product Specifications

Range	6 miles (10km) over SMF
LEX unit USB connector	1 x USB Type B
LEX unit Link connector	1 x SFP Duplex LC
REX unit Link connector	1 x SFP Duplex LC
REX unit USB connector	4 x USB Type A
Maximum USB devices supported	14 (including USB hubs)
Power adapter Maximum Rating	5V DC @ 3A
Current available to USB at REX	4 x 500mA
LEX and REX unit dimensions	3.94" x 2.99" x 1.02" (100 mm x 76 mm x 26 mm)
Operating temperature range	0°C to 50°C
Total system shipping weight	2.0 lbs. (0.9 kilograms)
Regulatory testing	FCC (Class B), IC (Class B), CE (Class B)
ESD Rating	EMC EN-61000-4-2:2001 8kV Contact, 16kV Air

Specifications subject to change without notification.

Contact sales@icron.com for more information or OEM options.

