imall

Chipsmall Limited consists of a professional team with an average of over 10 year of expertise in the distribution of electronic components. Based in Hongkong, we have already established firm and mutual-benefit business relationships with customers from, Europe, America and south Asia, supplying obsolete and hard-to-find components to meet their specific needs.

With the principle of "Quality Parts, Customers Priority, Honest Operation, and Considerate Service", our business mainly focus on the distribution of electronic components. Line cards we deal with include Microchip, ALPS, ROHM, Xilinx, Pulse, ON, Everlight and Freescale. Main products comprise IC, Modules, Potentiometer, IC Socket, Relay, Connector. Our parts cover such applications as commercial, industrial, and automotives areas.

We are looking forward to setting up business relationship with you and hope to provide you with the best service and solution. Let us make a better world for our industry!



Contact us

Tel: +86-755-8981 8866 Fax: +86-755-8427 6832 Email & Skype: info@chipsmall.com Web: www.chipsmall.com Address: A1208, Overseas Decoration Building, #122 Zhenhua RD., Futian, Shenzhen, China





Multi Layer Ceramic Capacitor (MLCC)




1. Model : CL21B105KPFNNNG

2. Description


Part no.	Size (inch(mm))	Thickness (mm)	Temperature charateristics	Capacitance value	Capacitance tolerance(%)	Voltage (V)
CL21B105KPFNNNG	0805/2012	1.25mm	X7R	1uF	\pm 10 %	10

3. Characteristics data


1) Frequency characteristics Agilent E4294A, 0.5Vrms, 1kHz to 100MHz




3) DC Bias characteristics (Agilent 4284A, 1kHz, 1Vrms)








2) Temperature characteristics of capacitance(TCC) Agilent 4284A, 1kHz, 1Vrms



4) Bias TCC characteristics (Agilent 4284A, 1kHz, 1Vrms, 5Vdc)



Any data in this sheet are subject to change, modify or discontinue without notice The data sheets include the typical data for design reference only. If there is any question regarding the data sheets, please contact our sales personnel or application engineers