imall

Chipsmall Limited consists of a professional team with an average of over 10 year of expertise in the distribution of electronic components. Based in Hongkong, we have already established firm and mutual-benefit business relationships with customers from, Europe, America and south Asia, supplying obsolete and hard-to-find components to meet their specific needs.

With the principle of "Quality Parts, Customers Priority, Honest Operation, and Considerate Service", our business mainly focus on the distribution of electronic components. Line cards we deal with include Microchip, ALPS, ROHM, Xilinx, Pulse, ON, Everlight and Freescale. Main products comprise IC, Modules, Potentiometer, IC Socket, Relay, Connector. Our parts cover such applications as commercial, industrial, and automotives areas.

We are looking forward to setting up business relationship with you and hope to provide you with the best service and solution. Let us make a better world for our industry!



Contact us

Tel: +86-755-8981 8866 Fax: +86-755-8427 6832 Email & Skype: info@chipsmall.com Web: www.chipsmall.com Address: A1208, Overseas Decoration Building, #122 Zhenhua RD., Futian, Shenzhen, China





40GHz Low Loss Coaxial Cables

| Features: | |
|-------------------------|---|
| Strain Relief: | |
| Center Conductor | : |
| Inner Braid: | |
| Outer Braid: | |
| Dielectric: | |
| | |

Jacket: **Cable Outer Dia.: Connectors:**

Center Pin:

Jacket Color:

Heavy duty adhesive strain relief Silver-plated solid copper Flat Silver plated copper strip PC (Round Silver-plated copper braid) Low density microporous PTFE (Polytetrafluoroethylene) FEP (Fluorinated Ethylene Propylene) 0.160 (4.06mm) SST, corrosion-resistant 303 stainless steel per ASTM-A582 (Passivated finish per SAE-AMS-2700) GPBC (Gold-plated beryllium copper) Grey **Operating Temperature:** -55°C to +85°C (2.92mm (K) (Available in -55°C to +125°C, HF SMA Only)

40GHZ LOW LOSS RF COAX CABLE ASSEMBLIES WITH 2.92mm (K) STAINLESS STEEL **CONNECTORS**



Electrical Specifications: Impedance: 50 Ohms **Frequency:** Up to 40GHz <0.9 dB/ft at 40GHz **Insertion Loss: VSWR:** <1.35 to 40GHz Max Oper. Volt: **500V RMS Nominal Capacitance:** 27.0 pF/ft Velocity of Propagation: 76% **RF Shielding:** < -90 dB 0.08 Max. at 500MHz Attenuation (dB/ft): *connector loss not included 0.17 Max at 2GHz 0.45 Max at 12GHz


CRYSTEK CORPORATION

Minimum Bend Radius: 1.0"

Custom Lengths Available

Mechanical Specifications: Connector Corrosion (salt spray):

MIL-STD-202, method 101, test cond. B 5% salt solution. **Connector Durability:** 500 connections Min.



Electrical Test Data Supplied With Each Cable Assembly


2.9mm(K) / 2.9mm(K) [Straight/Straight]


| Part Number | Description | Length |
|-------------------|------------------------------------------------------------------|--------|
| CCK40-MM-160-30 | 40GHz Low Loss Coax Cable, 2.9mm(K) Male/Male, Straight/Straight | 30" |
| CCK40-MM-160-36 | 40GHz Low Loss Coax Cable, 2.9mm(K) Male/Male, Straight/Straight | 36" |
| CCK40-MM-160-39.4 | 40GHz Low Loss Coax Cable, 2.9mm(K) Male/Male, Straight/Straight | 39.4" |
| CCK40-MM-160-48 | 40GHz Low Loss Coax Cable, 2.9mm(K) Male/Male, Straight/Straight | 48" |

^{0.57} Max at 18GHz 0.70 Max at 26GHz 0.90 Max at 40GHz



40GHZ LOW LOSS RF **RYSTEK** COAX CABLE ASSEMBLIES WITH 2.92mm (K) STAINLESS STEEL **CONNECTORS** Roh





12730 COMMONWEALTH DRIVE • FORT MYERS, FL 33913 PHONE: 239-561-3311 • 800-237-3061 Rev.: A FAX: 239-561-1025 . WWW.CRYSTEK.COM Date: 12-14-09