

Chipsmall Limited consists of a professional team with an average of over 10 year of expertise in the distribution of electronic components. Based in Hongkong, we have already established firm and mutual-benefit business relationships with customers from, Europe, America and south Asia, supplying obsolete and hard-to-find components to meet their specific needs.

With the principle of "Quality Parts, Customers Priority, Honest Operation, and Considerate Service", our business mainly focus on the distribution of electronic components. Line cards we deal with include Microchip, ALPS, ROHM, Xilinx, Pulse, ON, Everlight and Freescale. Main products comprise IC, Modules, Potentiometer, IC Socket, Relay, Connector. Our parts cover such applications as commercial, industrial, and automotives areas.

We are looking forward to setting up business relationship with you and hope to provide you with the best service and solution. Let us make a better world for our industry!



# Contact us

Tel: +86-755-8981 8866 Fax: +86-755-8427 6832

Email & Skype: info@chipsmall.com Web: www.chipsmall.com

Address: A1208, Overseas Decoration Building, #122 Zhenhua RD., Futian, Shenzhen, China









October 1987 Revised January 1999

## **CD4007C**

# **Dual Complementary Pair Plus Inverter**

#### **General Description**

The CD4007C consists of three complementary pairs of N-and P-channel enhancement mode MOS transistors suitable for series/shunt applications. All inputs are protected from static discharge by diode clamps to  $V_{\mbox{\scriptsize DD}}$  and  $V_{\mbox{\scriptsize SS}}.$ 

For proper operation the voltages at all pins must be constrained to be between  $\rm V_{SS}-0.3V$  and  $\rm V_{DD}+0.3V$  at all times

#### **Features**

■ Wide supply voltage range: 3.0V to 15V
■ High noise immunity: 0.45 V<sub>CC</sub> (typ.)


## **Ordering Code:**

Order Number	Package Number	Package Description
CD4007CM	M14A	14-Lead Small Outline Integrated Circuit (SOIC), JEDEC MS-120, 0.150" Narrow
CD4007CN	N14A	14-Lead Plastic Dual-In-Line Package (PDIP), JEDEC MS-001, 0.300" Wide

Devices also available in Tape and Reel. Specify by appending the suffix letter "X" to the ordering code.

### **Connection Diagram**

#### Pin Assignments for DIP and SOIC



 $\textbf{Note:} \ \textbf{All P-channel substrates are connected to V}_{DD} \ \textbf{and all N-channel substrates are connected to V}_{SS}.$ 

**Top View** 

## **Absolute Maximum Ratings**(Note 1)

Voltage at Any Pin  $V_{SS}$  -0.3V to  $V_{DD}$  +0.3V Operating Temperature Range -40°C to +85°C

-65°C to +150°C Storage Temperature Range

Power Dissipation (P<sub>D</sub>)

Dual-In-Line 700 mW Small Outline 500 mW

Operating  $V_{\rm DD}$  Range Lead Temperature (Soldering, 10 seconds)  $V_{SS}$  +3.0V to  $V_{SS}$  +15V

260°C

**Note 1:** This device should not be connected to circuits with the power on because high transient voltages may cause permanent damage.

#### **DC Electrical Characteristics**

	Parameter	Conditions	Limits									
Symbol			-40°C		+25°C			+85°C			Units	
			Min	Тур	Max	Min	Тур	Max	Min	Тур	Max	
IL	Quiescent Device	V <sub>DD</sub> = 5.0V			0.5		0.005	0.05			15	μΑ
	Current	$V_{DD} = 10V$			1.0		0.005	1.0			30	μΑ
P <sub>D</sub>	Quiescent Device	V <sub>DD</sub> = 5.0V			2.5		0.025	2.5			75	μW
	Dissipation Package	V <sub>DD</sub> = 10V			10		0.05	10			300	μW
V <sub>OL</sub>	Output Voltage	V <sub>DD</sub> = 5.0V			0.05		0	0.01			0.05	V
	LOW Level	$V_{DD} = 10V$			0.05		0	0.01			0.05	V
V <sub>OH</sub>	Output Voltage	V <sub>DD</sub> = 5.0V	4.95			4.95	5.0		4.95			V
	HIGH Level	$V_{DD} = 10V$	9.95			9.95	10		9.95			V
V <sub>NL</sub>	Noise Immunity	$V_{DD} = 5.0V, V_{O} = 3.6V$			1.5		2.25	1.5			1.4	V
	(All inputs)	$V_{DD} = 10V, V_{O} = 7.2V$			3.0		4.5	3.0			2.9	V
V <sub>NH</sub>	Noise Immunity	$V_{DD} = 5.0V, V_{O} = 0.95V$	3.6			3.5	2.25		3.5			V
	(All Inputs)	$V_{DD} = 10V, V_{O} = 2.9V$	7.1			7.0	4.5		7.0			V
I <sub>D</sub> N	Output Drive Current	$V_{DD} = 5.0V, V_{O} = 0.4V, V_{I} = V_{DD}$	0.35			0.3	1.0		0.24			mA
	N-Channel	$V_{DD} = 10V, V_{O} = 0.5V, V_{I} = V_{DD}$	1.2			1.0	2.5		8.0			mA
I <sub>D</sub> P	Output Drive Current	$V_{DD} = 5.0V, V_{O} = 2.5V, V_{I} = V_{SS}$	-1.3			-1.1	-4.0		-0.9			mA
	P-Channel	$V_{DD} = 10V, V_{O} = 9.5V, V_{I} = V_{SS}$	-0.65			-0.55	-2.5		-0.45			mA
I	Input Current						10					pА


#### **AC Electrical Characteristics** (Note 2)

 $T_A = 25^{\circ}C$  and  $C_L = 15$  pF and rise and fall times = 20 ns. Typical temperature coefficient for all values of  $V_{DD} = 0.3\%/^{\circ}C$ 

7, 2			55				
Symbol	Parameter	Conditions	Min	Тур	Max	Units	
$t_{PLH} = t_{PHL}$	Propagation Delay Time	V <sub>DD</sub> = 5.0V		35	75	ns	
		$V_{DD} = 10V$		20	50	ns	
$t_{TLH} = t_{THL}$	Transition Time	V <sub>DD</sub> = 5.0V		50	100	ns	
		$V_{DD} = 10V$		30	50	ns	
CI	Input Capacitance	Any Input		5		pF	


Note 2: AC Parameters are guaranteed by DC correlated testing.

# **AC Test Circuits**





# INPUT 6 P 8, 13 OUTPU


# **Switching Time Waveforms**




## Physical Dimensions inches (millimeters) unless otherwise noted







14-Lead Small Outline Integrated Circuit (SOIC), JEDEC MS-120, 0.150" Narrow Package Number M14A



14-Lead Plastic Dual-In-Line Package (PDIP), JEDEC MS-001, 0.300" Wide Package Number N14A

#### LIFE SUPPORT POLICY

FAIRCHILD'S PRODUCTS ARE NOT AUTHORIZED FOR USE AS CRITICAL COMPONENTS IN LIFE SUPPORT DEVICES OR SYSTEMS WITHOUT THE EXPRESS WRITTEN APPROVAL OF THE PRESIDENT OF FAIRCHILD SEMICONDUCTOR CORPORATION. As used herein:

- Life support devices or systems are devices or systems which, (a) are intended for surgical implant into the body, or (b) support or sustain life, and (c) whose failure to perform when properly used in accordance with instructions for use provided in the labeling, can be reasonably expected to result in a significant injury to the user.
- A critical component in any component of a life support device or system whose failure to perform can be reasonably expected to cause the failure of the life support device or system, or to affect its safety or effectiveness.

www.fairchildsemi.com