

Chipsmall Limited consists of a professional team with an average of over 10 year of expertise in the distribution of electronic components. Based in Hongkong, we have already established firm and mutual-benefit business relationships with customers from, Europe, America and south Asia, supplying obsolete and hard-to-find components to meet their specific needs.

With the principle of "Quality Parts, Customers Priority, Honest Operation, and Considerate Service", our business mainly focus on the distribution of electronic components. Line cards we deal with include Microchip, ALPS, ROHM, Xilinx, Pulse, ON, Everlight and Freescale. Main products comprise IC, Modules, Potentiometer, IC Socket, Relay, Connector. Our parts cover such applications as commercial, industrial, and automotives areas.

We are looking forward to setting up business relationship with you and hope to provide you with the best service and solution. Let us make a better world for our industry!



Contact us

Tel: +86-755-8981 8866 Fax: +86-755-8427 6832

Email & Skype: info@chipsmall.com Web: www.chipsmall.com

Address: A1208, Overseas Decoration Building, #122 Zhenhua RD., Futian, Shenzhen, China







SMD Schottky Barrier Diode

COACHIP SMD Diodes Specialis

CDBUR0320/0330/0340 (RoHs Device)

io = 350 mA

 $V_R = 20 \text{ to } 40 \text{ Volts}$

Features

Low forward voltage.

Designed for mounting on small surface.

Extremely thin / leadless package.

Majority carrier conduction.

Mechanical data

Case: 0603(1608) standard package,

molded plastic.


Terminals: Gold plated, solderable per

MIL-STD-750, method 2026.

Polarity: Indicated by cathode band.

Mounting position: Any

Weight: 0.003 gram(approx.).



Maximum Rating (at TA=25°C unless otherwise noted)

| | | | , | | | | |
|---|------------|-------------|-----------|-----------|------|--|--|
| Parameter | Symbol | CDBUR0320 | CDBUR0330 | CDBUR0340 | Unit | | |
| Repetitive Peak reverse voltage Reverse voltage | Vrrm Vr | 20 | 30 | 40 | V | | |
| RMS reverse voltage | VR(RMS) | 14 | 21 | 28 | V | | |
| Average forward rectified current | lo | 350 | | | | | |
| Forward current, surge peak 8.3 ms single half sine-wave | IFSM | 1.5 | | | | | |
| Power dissipation | Pp | 150 | | | | | |
| Thermal resistance junction to ambient air | R øja | 667 | | | | | |
| Storage temperature | Тѕтс | -65 TO +125 | | | | | |
| Junction temperature | Tj | +125 | | | | | |

Electrical Characteristics (at TA=25°C unless otherwise noted)

| Parameter | | Conditions | Symbol | Min | Тур | Max | Unit |
|-----------------------|----------------------------------|--------------------------------------|--------|-----|-----|--------------|------|
| CD | OBUR0320 OBUR0330 OBUR0340 | VR = 10V VR = 20V VR = 30V | lr | | | 5 5 5 | uA |
| Forward voltage | | IF = 20mA IF = 200mA | VF | | | 0.37 0.60 | ٧ |
| Capacitance between | terminals | f = 1 MHz, and 0 VDC reverse voltage | Ст | | 50 | | pF |
| Reverse recovery time | е | IF=IR=10mA,Irr=0.1xIR,RL=100 ohm | Trr | · | 6.4 | | nS |



RATING AND CHARACTERISTIC CURVES (CDBUR0320/0330/0340)

Fig. 1 - Forward characteristics




Fig.3 - Capacitance between terminals characteristics




Fig. 2 - Reverse characteristics




Fig.4 - Current derating curve

