



Chipsmall Limited consists of a professional team with an average of over 10 year of expertise in the distribution of electronic components. Based in Hongkong, we have already established firm and mutual-benefit business relationships with customers from,Europe,America and south Asia,supplying obsolete and hard-to-find components to meet their specific needs.

With the principle of "Quality Parts,Customers Priority,Honest Operation,and Considerate Service",our business mainly focus on the distribution of electronic components. Line cards we deal with include Microchip,ALPS,ROHM,Xilinx,Pulse,ON,Everlight and Freescale. Main products comprise IC,Modules,Potentiometer,IC Socket,Relay,Connector.Our parts cover such applications as commercial,industrial, and automotives areas.

We are looking forward to setting up business relationship with you and hope to provide you with the best service and solution. Let us make a better world for our industry!



Contact us

Tel: +86-755-8981 8866 Fax: +86-755-8427 6832

Email & Skype: info@chipsmall.com Web: www.chipsmall.com


Address: A1208, Overseas Decoration Building, #122 Zhenhua RD., Futian, Shenzhen, China




Sample Kit Contents

KEMET Part Number	Case Size	Capacitance	Cap Tolerance	Rated Voltage	Dielectric	Quantity
	EIA/Metric	pF	%	VDC		
CBR02C108B5GAC	0201/0603	0.1	±0.1	50	COG	100
CBR02C208B5GAC	0201/0603	0.2	±0.1	50	COG	100
CBR02C308B5GAC	0201/0603	0.3	±0.1	50	COG	100
CBR02C408B5GAC	0201/0603	0.4	±0.1	50	COG	100
CBR02C508B5GAC	0201/0603	0.5	±0.1	50	COG	100
CBR02C608B5GAC	0201/0603	0.6	±0.1	50	COG	100
CBR02C708B5GAC	0201/0603	0.7	±0.1	50	COG	100
CBR02C808B5GAC	0201/0603	0.8	±0.1	50	COG	100
CBR02C908B5GAC	0201/0603	0.9	±0.1	50	COG	100
CBR02C109B5GAC	0201/0603	1.0	±0.1	50	COG	100
CBR02C129B5GAC	0201/0603	1.2	±0.1	50	COG	100
CBR02C159B5GAC	0201/0603	1.5	±0.1	50	COG	100
CBR02C189B5GAC	0201/0603	1.8	±0.1	50	COG	100
CBR02C209B5GAC	0201/0603	2.0	±0.1	50	COG	100
CBR02C229B5GAC	0201/0603	2.2	±0.1	50	COG	100
CBR02C279B5GAC	0201/0603	2.7	±0.1	50	COG	100
CBR02C309B5GAC	0201/0603	3.0	±0.1	50	COG	100
CBR02C339B5GAC	0201/0603	3.3	±0.1	50	COG	100
CBR02C399B5GAC	0201/0603	3.9	±0.1	50	COG	100
CBR02C409B5GAC	0201/0603	4.0	±0.1	50	COG	100
CBR02C479B5GAC	0201/0603	4.7	±0.1	50	COG	100
CBR02C509C5GAC	0201/0603	5.0	±0.25	50	COG	100
CBR02C569C5GAC	0201/0603	5.6	±0.25	50	COG	100
CBR02C609C5GAC	0201/0603	6.0	±0.25	50	COG	100
CBR02C689C5GAC	0201/0603	6.8	±0.25	50	COG	100
CBR02C709C5GAC	0201/0603	7.0	±0.25	50	COG	100
CBR02C809C5GAC	0201/0603	8.0	±0.25	50	COG	100
CBR02C829C5GAC	0201/0603	8.2	±0.25	50	COG	100
CBR02C909C5GAC	0201/0603	9.0	±0.25	50	COG	100
CBR02C100J5GAC	0201/0603	10	±5	50	COG	100
CBR02C120J5GAC	0201/0603	12	±5	50	COG	100
CBR02C150J5GAC	0201/0603	15	±5	50	COG	100
CBR02C180J5GAC	0201/0603	18	±5	50	COG	100
CBR02C200J5GAC	0201/0603	20	±5	50	COG	100
CBR02C220J3GAC	0201/0603	22	±5	25	COG	100
CBR02C240J3GAC	0201/0603	24	±5	25	COG	100
CBR02C270J3GAC	0201/0603	27	±5	25	COG	100
CBR02C300J3GAC	0201/0603	30	±5	25	COG	100
CBR02C330J3GAC	0201/0603	33	±5	25	COG	100

Dimensions – Millimeters (Inches)



Case Size (in.)	Case Size (mm)	L Length	W Width	T Thickness	B Bandwidth	Mounting Technique
0201	0603	0.60±0.03 (0.024±0.001)	0.30±0.03 (0.012±0.001)	0.30±0.03 (0.012±0.001)	0.15±0.05 (0.006±0.002)	Solder Reflow Only



www.kemet.com/CBR