



Chipsmall Limited consists of a professional team with an average of over 10 year of expertise in the distribution of electronic components. Based in Hongkong, we have already established firm and mutual-benefit business relationships with customers from,Europe,America and south Asia,supplying obsolete and hard-to-find components to meet their specific needs.

With the principle of “Quality Parts,Customers Priority,Honest Operation,and Considerate Service”,our business mainly focus on the distribution of electronic components. Line cards we deal with include Microchip,ALPS,ROHM,Xilinx,Pulse,ON,Everlight and Freescale. Main products comprise IC,Modules,Potentiometer,IC Socket,Relay,Connector.Our parts cover such applications as commercial,industrial, and automotives areas.

We are looking forward to setting up business relationship with you and hope to provide you with the best service and solution. Let us make a better world for our industry!



Contact us

Tel: +86-755-8981 8866 Fax: +86-755-8427 6832

Email & Skype: info@chipsmall.com Web: www.chipsmall.com


Address: A1208, Overseas Decoration Building, #122 Zhenhua RD., Futian, Shenzhen, China




Sample Kit Contents

KEMET Part Number	Case Size	Capacitance	Cap Tolerance	Rated Voltage	Dielectric	Quantity
	EIA/Metric	pF	%	VDC		
CBR04C108B1GAC	0402/1005	0.1	±0.1	100	COG	100
CBR04C208B1GAC	0402/1005	0.2	±0.1	100	COG	100
CBR04C308B1GAC	0402/1005	0.3	±0.1	100	COG	100
CBR04C408B1GAC	0402/1005	0.4	±0.1	100	COG	100
CBR04C508B1GAC	0402/1005	0.5	±0.1	100	COG	100
CBR04C608B1GAC	0402/1005	0.6	±0.1	100	COG	100
CBR04C708B1GAC	0402/1005	0.7	±0.1	100	COG	100
CBR04C808B1GAC	0402/1005	0.8	±0.1	100	COG	100
CBR04C908B1GAC	0402/1005	0.9	±0.1	100	COG	100
CBR04C109B1GAC	0402/1005	1.0	±0.1	100	COG	100
CBR04C129B1GAC	0402/1005	1.2	±0.1	100	COG	100
CBR04C159B1GAC	0402/1005	1.5	±0.1	100	COG	100
CBR04C189B1GAC	0402/1005	1.8	±0.1	100	COG	100
CBR04C209B1GAC	0402/1005	2.0	±0.1	100	COG	100
CBR04C229B1GAC	0402/1005	2.2	±0.1	100	COG	100
CBR04C279B1GAC	0402/1005	2.7	±0.1	100	COG	100
CBR04C309B1GAC	0402/1005	3.0	±0.1	100	COG	100
CBR04C339B1GAC	0402/1005	3.3	±0.1	100	COG	100
CBR04C399B1GAC	0402/1005	3.9	±0.1	100	COG	100
CBR04C409B1GAC	0402/1005	4.0	±0.1	100	COG	100
CBR04C479B1GAC	0402/1005	4.7	±0.1	100	COG	100
CBR04C509C1GAC	0402/1005	5.0	±0.25	100	COG	100
CBR04C569C1GAC	0402/1005	5.6	±0.25	100	COG	100
CBR04C609C1GAC	0402/1005	6.0	±0.25	100	COG	100
CBR04C689C1GAC	0402/1005	6.8	±0.25	100	COG	100
CBR04C709C1GAC	0402/1005	7.0	±0.25	100	COG	100
CBR04C809C1GAC	0402/1005	8.0	±0.25	100	COG	100
CBR04C829C1GAC	0402/1005	8.2	±0.25	100	COG	100
CBR04C909C1GAC	0402/1005	9.0	±0.25	100	COG	100
CBR04C100J1GAC	0402/1005	10	±5	100	COG	100
CBR04C120J1GAC	0402/1005	12	±5	100	COG	100
CBR04C150J1GAC	0402/1005	15	±5	100	COG	100
CBR04C180J1GAC	0402/1005	18	±5	100	COG	100
CBR04C220J1GAC	0402/1005	22	±5	100	COG	100
CBR04C270J1GAC	0402/1005	27	±5	100	COG	100
CBR04C390J1GAC	0402/1005	39	±5	100	COG	100
CBR04C470J1GAC	0402/1005	47	±5	100	COG	100
CBR04C560J1GAC	0402/1005	56	±5	100	COG	100
CBR04C680J3GAC	0402/1005	68	±5	25	COG	100
CBR04C820J3GAC	0402/1005	82	±5	25	COG	100
CBR04C101J3GAC	0402/1005	100	±5	25	COG	100

Dimensions – Millimeters (Inches)



Case Size (in.)	Case Size (mm)	L Length	W Width	T Thickness	B Bandwidth	Mounting Technique
0402	1005	1.00 ±0.05 (0.040 ±0.002)	0.50 ±0.05 (0.020 ±0.002)	0.50 ±0.05 (0.020 ±0.002)	0.25 +0.05/-0.10 (0.010 +0.002/-0.004)	Solder Reflow Only



www.kemet.com/CBR