



Chipsmall Limited consists of a professional team with an average of over 10 year of expertise in the distribution of electronic components. Based in Hongkong, we have already established firm and mutual-benefit business relationships with customers from,Europe,America and south Asia,supplying obsolete and hard-to-find components to meet their specific needs.

With the principle of “Quality Parts,Customers Priority,Honest Operation,and Considerate Service”,our business mainly focus on the distribution of electronic components. Line cards we deal with include Microchip,ALPS,ROHM,Xilinx,Pulse,ON,Everlight and Freescale. Main products comprise IC,Modules,Potentiometer,IC Socket,Relay,Connector.Our parts cover such applications as commercial,industrial, and automotives areas.

We are looking forward to setting up business relationship with you and hope to provide you with the best service and solution. Let us make a better world for our industry!



## Contact us

Tel: +86-755-8981 8866 Fax: +86-755-8427 6832

Email & Skype: info@chipsmall.com Web: www.chipsmall.com


Address: A1208, Overseas Decoration Building, #122 Zhenhua RD., Futian, Shenzhen, China




## Sample Kit Contents

KEMET Part Number	Case Size	Capacitance	Cap Tolerance	Rated Voltage	Dielectric	Quantity
	EIA/Metric	pF	%	VDC		
CBR06C308BAGAC	0603/1608	0.3	±0.1	250	COG	50
CBR06C408BAGAC	0603/1608	0.4	±0.1	250	COG	50
CBR06C508BAGAC	0603/1608	0.5	±0.1	250	COG	50
CBR06C608BAGAC	0603/1608	0.6	±0.1	250	COG	50
CBR06C708BAGAC	0603/1608	0.7	±0.1	250	COG	50
CBR06C808BAGAC	0603/1608	0.8	±0.1	250	COG	50
CBR06C908BAGAC	0603/1608	0.9	±0.1	250	COG	50
CBR06C109BAGAC	0603/1608	1.0	±0.1	250	COG	50
CBR06C129BAGAC	0603/1608	1.2	±0.1	250	COG	50
CBR06C159BAGAC	0603/1608	1.5	±0.1	250	COG	50
CBR06C189BAGAC	0603/1608	1.8	±0.1	250	COG	50
CBR06C209BAGAC	0603/1608	2.0	±0.1	250	COG	50
CBR06C229BAGAC	0603/1608	2.2	±0.1	250	COG	50
CBR06C279BAGAC	0603/1608	2.7	±0.1	250	COG	50
CBR06C309BAGAC	0603/1608	3.0	±0.1	250	COG	50
CBR06C339BAGAC	0603/1608	3.3	±0.1	250	COG	50
CBR06C399BAGAC	0603/1608	3.9	±0.1	250	COG	50
CBR06C409BAGAC	0603/1608	4.0	±0.1	250	COG	50
CBR06C479BAGAC	0603/1608	4.7	±0.1	250	COG	50
CBR06C509CAGAC	0603/1608	5.0	±0.25	250	COG	50
CBR06C569C5GAC	0603/1608	5.6	±0.25	50	COG	50
CBR06C609CAGAC	0603/1608	6.0	±0.25	250	COG	50
CBR06C689C5GAC	0603/1608	6.8	±0.25	50	COG	50
CBR06C709CAGAC	0603/1608	7.0	±0.25	250	COG	50
CBR06C809C5GAC	0603/1608	8.0	±0.25	50	COG	50
CBR06C829C5GAC	0603/1608	8.2	±0.25	50	COG	50
CBR06C909CAGAC	0603/1608	9.0	±0.25	250	COG	50
CBR06C100J5GAC	0603/1608	10	±5	50	COG	50
CBR06C120J5GAC	0603/1608	12	±5	50	COG	50
CBR06C150J5GAC	0603/1608	15	±5	50	COG	50
CBR06C180JAGAC	0603/1608	18	±5	250	COG	50
CBR06C220J5GAC	0603/1608	22	±5	50	COG	50
CBR06C270JAGAC	0603/1608	27	±5	250	COG	50
CBR06C330J5GAC	0603/1608	33	±5	50	COG	50
CBR06C390JAGAC	0603/1608	39	±5	250	COG	50
CBR06C470JAGAC	0603/1608	47	±5	250	COG	50

## Dimensions – Millimeters (Inches)



Case Size (in.)	Case Size (mm)	L Length	W Width	T Thickness	B Bandwidth	Mounting Technique
0603	1608	1.60±0.10 (0.063±0.004)	0.80±0.10 (0.031±0.004)	0.80±0.07 (0.031±0.003)	0.40±0.15 (0.016±0.006)	Solder Wave or Solder Reflow



[www.kemet.com/CBR](http://www.kemet.com/CBR)