



Chipsmall Limited consists of a professional team with an average of over 10 year of expertise in the distribution of electronic components. Based in Hongkong, we have already established firm and mutual-benefit business relationships with customers from,Europe,America and south Asia,supplying obsolete and hard-to-find components to meet their specific needs.

With the principle of “Quality Parts,Customers Priority,Honest Operation,and Considerate Service”,our business mainly focus on the distribution of electronic components. Line cards we deal with include Microchip,ALPS,ROHM,Xilinx,Pulse,ON,Everlight and Freescale. Main products comprise IC,Modules,Potentiometer,IC Socket,Relay,Connector.Our parts cover such applications as commercial,industrial, and automotives areas.

We are looking forward to setting up business relationship with you and hope to provide you with the best service and solution. Let us make a better world for our industry!



Contact us

Tel: +86-755-8981 8866 Fax: +86-755-8427 6832


Email & Skype: info@chipsmall.com Web: www.chipsmall.com

Address: A1208, Overseas Decoration Building, #122 Zhenhua RD., Futian, Shenzhen, China



Product Type	Current Transformer
Amgis Part Number	CT1150

SCHEMATIC:




ELECTRICAL SPECIFICATION:

Rated input current	= 150Amps
Primary to Secondary isolation	= 2500VAC
Operating Frequency	= 50 / 60 Hz
Turns Ratio	= 1 : 1000
DC Resistance	= 11.00 Ω
Output Voltage	= 15.0V @ 150A / 100Ω, 2.2500W
Io @ Vrms : 16.60V	= 1820μArms
Ratio Correction factor (RCF*)	= 1.002@10% (Multiply current reading by this factor to compensate for transformer losses)


Volt/Amp at rated Ip for different loads			
100Ω	500Ω	2000Ω	5000Ω
0.10	0.37	0.50	0.55

MECHANICAL SPECIFICATION :

Pin Side View




Front View




All dimensions are in mm
Linear dimensional tolerance ±0.2mm

Note : Un-Used pin → #3

OUTPUT RESPONSE vs INPUT CURRENT @ RATED BURDEN :



TYPICAL EXCITATION CURVE :



TRAFO WEIGHT:

Approx. Weight = 0.150 kg / pc

MARKING INFORMATION:

Amgis
CT1150
Yr/Wk code
●
Dot mark for Start pin identification

-----Initial Issue-----	1	0	K.Shanmugam	01-Dec'2015
Changes	Issue	Rev	Initial	Date