



Chipsmall Limited consists of a professional team with an average of over 10 year of expertise in the distribution of electronic components. Based in Hongkong, we have already established firm and mutual-benefit business relationships with customers from,Europe,America and south Asia,supplying obsolete and hard-to-find components to meet their specific needs.

With the principle of "Quality Parts,Customers Priority,Honest Operation,and Considerate Service",our business mainly focus on the distribution of electronic components. Line cards we deal with include Microchip,ALPS,ROHM,Xilinx,Pulse,ON,Everlight and Freescale. Main products comprise IC,Modules,Potentiometer,IC Socket,Relay,Connector.Our parts cover such applications as commercial,industrial, and automotives areas.

We are looking forward to setting up business relationship with you and hope to provide you with the best service and solution. Let us make a better world for our industry!



Contact us

Tel: +86-755-8981 8866 Fax: +86-755-8427 6832

Email & Skype: info@chipsmall.com Web: www.chipsmall.com

Address: A1208, Overseas Decoration Building, #122 Zhenhua RD., Futian, Shenzhen, China



Mini Pocket MultiMeter

*Autoranging with 10 functions including Frequency, Capacitance, and Duty Cycle
With Diode Test and Continuity Beeper.*

Features:

- Large high contrast 4000 count LCD display
- Auto Power off to conserve battery life
- Autoranging with Relative and Data Hold
- Diode Test and Continuity Beeper
- Built-in storage compartment for integrated test leads
- Protective rubber holster provides extra protection on the meter
- Over-range and low battery indication
- Complete with test leads, protective holster, one CR 2032 button battery and carrying case

Applications:

- Home wiring projects
- Testing electrical systems on cars and boats
- Hobby projects



Integrated test leads for accurate readings



Includes holster and pouch carrying case for added protection

Specifications	Range	Max. Resolution	Basic Accuracy (%rdg+digits)
DC Voltage	500V	0.1mV	±(1.3% + 3d)
AC Voltage	500V	1mV	±(2.3% + 5d)
DC Current	400.0mA	0.01mA	±(2.0% + 5d)
AC Current	400.0mA	0.01mA	±(2.5% + 10d)
Resistance	400 to 40MΩ	0.1Ω	±(2.0% + 5d)
Capacitance	200μF	0.001nF	±(3.0% + 15d)
Frequency	9Hz to 10MHz	0.001Hz	±(2% + 5d)
Duty Cycle	0.1% to 99.9%	0.1%	±(2% + 5d)
Diode Test	Test Current at 0.6mA		
Continuity Test	Audible beep <60Ω		
Dimensions	4.25 x 2.2 x 0.5" (108 x 56 x 11.5mm)		
Weight	1.7oz (50g)		

Ordering Information:

DM110Mini Pocket MultiMeter

