

Chipsmall Limited consists of a professional team with an average of over 10 year of expertise in the distribution of electronic components. Based in Hongkong, we have already established firm and mutual-benefit business relationships with customers from, Europe, America and south Asia, supplying obsolete and hard-to-find components to meet their specific needs.

With the principle of "Quality Parts, Customers Priority, Honest Operation, and Considerate Service", our business mainly focus on the distribution of electronic components. Line cards we deal with include Microchip, ALPS, ROHM, Xilinx, Pulse, ON, Everlight and Freescale. Main products comprise IC, Modules, Potentiometer, IC Socket, Relay, Connector. Our parts cover such applications as commercial, industrial, and automotives areas.

We are looking forward to setting up business relationship with you and hope to provide you with the best service and solution. Let us make a better world for our industry!



Contact us

Tel: +86-755-8981 8866 Fax: +86-755-8427 6832

Email & Skype: info@chipsmall.com Web: www.chipsmall.com

Address: A1208, Overseas Decoration Building, #122 Zhenhua RD., Futian, Shenzhen, China









CAT IV Pocket MultiMeter

Autoranging DMM with Non-Contact Voltage Detector and Built-in Flashlight Includes Diode Test and Continiuity Beeper Functions

Features:

- · Large high contrast 4000 count LCD display
- Non-Contact Voltage detection identifies live circuits
- · Built-in Flashlight
- 11 functions including Frequency, Capacitance, and Duty Cycle
- Built-in storage clips for integrated test leads
- Double molded housing provides extra protection
- Over-range and low battery indication
- Complete with test leads and two AAA batteries

Applications:

- · Electrical repair
- Appliance repair
- · Home wiring projects
- Testing electrical systems on cars and boats
- · Hobby projects



Built-in Non-Contact Voltage Detector. Red LED bar lights when live wire detected.





| Specifications | Range | Max. Resolution | Basic Accuracy (%rdg+digits) |
|-----------------|--------------------------------------|-----------------|------------------------------|
| NC Voltage | 100 to 600VAC | | |
| DC Voltage | 600V | 0.1mV | ±0.8% |
| AC Voltage | 600V | 1mV | ±1.0% |
| Resistance | $40M\Omega$ | 0.1Ω | ±0.8% |
| DC Current | 200mA | 0.1μΑ | ±2.0% |
| AC Current | 200mA | 0.1µA | ±2.5% |
| Frequency | 10kHz | 0.001Hz | ±1.0% |
| Capacitance | 200μF | 0.001nF | ±3.0% |
| Duty Cycle | Yes | | |
| Diode Test | Yes | | |
| Continuity Test | Yes | | |
| Dimensions | 4.72 x 2.2 x 01.6" (120 x 55 x 40mm) | | |
| Weight | 5.12oz (145g) | | |

Ordering Information:

DM220Mini Pocket MultiMeter **409992**Vinyl pouch case



