# mail

Chipsmall Limited consists of a professional team with an average of over 10 year of expertise in the distribution of electronic components. Based in Hongkong, we have already established firm and mutual-benefit business relationships with customers from, Europe, America and south Asia, supplying obsolete and hard-to-find components to meet their specific needs.

With the principle of "Quality Parts, Customers Priority, Honest Operation, and Considerate Service", our business mainly focus on the distribution of electronic components. Line cards we deal with include Microchip, ALPS, ROHM, Xilinx, Pulse, ON, Everlight and Freescale. Main products comprise IC, Modules, Potentiometer, IC Socket, Relay, Connector. Our parts cover such applications as commercial, industrial, and automotives areas.

We are looking forward to setting up business relationship with you and hope to provide you with the best service and solution. Let us make a better world for our industry!



## Contact us

Tel: +86-755-8981 8866 Fax: +86-755-8427 6832 Email & Skype: info@chipsmall.com Web: www.chipsmall.com Address: A1208, Overseas Decoration Building, #122 Zhenhua RD., Futian, Shenzhen, China



DSC8101 DSC8121



#### **General Description**

The DSC8101 & DSC8121 series of high performance field-programmable oscillators utilizes a proven silicon MEMS technology to provide excellent jitter and stability over a of wide range supply voltages and temperatures. Using the TIMEFLASH programmer, the end user can easily program the oscillators' frequency in the field for immediate testing or use in advance prototype development or production.

DSC8101 has a standby feature allowing it to completely power-down when EN pin is pulled low; whereas for DSC8121, only the outputs are disabled when EN is low. Both oscillators are available in industry standard packages, including the small 3.2x2.5 mm<sup>2</sup>, and are "drop-in" replacement for standard 4-pin CMOS quartz oscillators.

#### **Block Diagram**



#### **Output Enable Modes**

EN Pin	DSC8101	DSC8121
High	Output Active	Output Active
NC	Output Active	Output Active
Low	Standby	Output Disabled

#### **Features**

- Low RMS Phase Jitter: <1 ps (typ)
- High Stability: ±10, ±25, ±50 ppm
- Wide Temperature Range Automotive: -55° to 125° C
  - Ext. Industrial: -40° to 105° C
  - Industrial: -40° to 85° C
  - Ext. commercial: -20° to 70° C
- High Supply Noise Rejection: -50 dBc
- Wide Freq. Range: 10 to 170 MHz
- Small Industry Standard Footprints o 2.5x2.0, 3.2x2.5, 5.0x3.2, & 7.0x5.0 mm
- Excellent Shock & Vibration Immunity o Oualified to MIL-STD-883
- High Reliability 20x better MTF than quartz oscillators
- Low Current Consumption
- Supply Range of 2.25 to 3.6 V
- Standby & Output Enable Function
- Lead Free & RoHS Compliant

#### **Applications**

- Storage Area Networks SATA, SAS, Fibre Channel
- Passive Optical Networks o EPON, 10G-EPON, GPON, 10G-PON
- Ethernet 1G, 10GBASE-T/KR/LR/SR, and FCoE
- HD/SD/SDI Video & Surveillance
- PCI Express
- DisplayPort

All Rights Reserved. No part of this document may be copied or reproduced in any form without the prior written permission of Micrel, Inc. Micrel Inc. may update or make changes to the contents, products, programs or services described at any time without notice. This document neither states nor implies any kind of warranty, including, but not limited to implied warranties of merchantability or fitness for a particular use. Page 1 |



#### **Absolute Maximum Ratings**

Item	Min	Мах	Unit	Condition
Supply Voltage	-0.3	+4.0	V	
Input Voltage	-0.3	V <sub>DD</sub> +0.3	V	
Junction Temp	-	+150	°C	
Storage Temp	-55	+150	°C	
Soldering Temp	-	+260	°C	40sec max.
ESD	-		V	
HBM		4000		
MM		400		
CDM		1500		

**Ordering Code** 



Note: 1000+ years of data retention on internal memory

#### **Specifications**

Parameter		Condition M		Тур.	Max.	Unit
Supply Voltage <sup>1</sup>	$V_{DD}$		2.25		3.6	V
Supply Current	I <sub>DD</sub>	EN pin low – output is disabled DSC8101 DSC8121	put is disabled 101 121 20		0.095 22	mA
Frequency Stability Ext Comm. & Ind. only All temp ranges All temp ranges	Δf	Includes frequency variations due to initial tolerance, temp. and power supply voltage			±10 ±25 ±50	ppm
Aging	Δf	1 year @25°C			±5	ppm
Startup Time <sup>2</sup>	t <sub>su</sub>	T=25°C			5	ms
Input Logic Levels Input logic high Input logic low	V <sub>IH</sub> V <sub>IL</sub>		0.75xV <sub>DD</sub> -		- 0.25xV <sub>DD</sub>	V
Output Disable Time <sup>3</sup>	t <sub>DA</sub>				5	ns
Output Enable Time	t <sub>EN</sub>	DSC8101 DSC8121			5 20	ms ns
Enable Pull-Up Resistor <sup>4</sup>		Pull-up resistor exist		40		kΩ
CMOS Output						
Supply Current <sup>4</sup>	I <sub>DD</sub>	output is enabled $C_L=15pF$ , $F_0=125 \text{ MHz}$		31	35	mA
Output Logic Levels Output logic high Output logic low	V <sub>OH</sub> V <sub>OL</sub>	I=±6mA	0.9xV <sub>DD</sub> -		- 0.1xV <sub>DD</sub>	v
Output Transition time <sup>3</sup> Rise Time Fall Time	t <sub>R</sub> t <sub>F</sub>	20% to 80% C <sub>L</sub> =15pF		1.1 1.3	2 2	ns
Frequency	f <sub>0</sub>	All temp range except Auto Auto temp range	10		170 100	MHz
Output Duty Cycle	SYM		45		55	%
Period Jitter	J <sub>PER</sub>	Fout=125MHz		3		ps <sub>RMS</sub>
Integrated Phase Noise	J <sub>PH</sub>	200kHz to 20MHz @ 125MHz 100kHz to 20MHz @ 125MHz 12kHz to 20MHz @ 125MHz	5MHz 0.3 5MHz 0.3 MHz 1.		2	ps <sub>RMS</sub>

1.

Pin 6  $V_{\text{DD}}$  should be filtered with 0.1uf capacitor.  $t_{su}$  is time to 100PPM of output frequency after  $V_{\text{DD}}$  is applied and outputs are enabled. Output Waveform and Test Circuit figures below define the parameters. 2. 3.

4. Output is enabled if pad is floated or not connected.

All Rights Reserved. No part of this document may be copied or reproduced in any form without the prior written permission of Micrel, Inc. Micrel Inc. may update or make changes to the contents, products, programs or services described at any time without notice. This document neither states nor implies any kind of warranty, including, but not limited to implied warranties of merchantability or fitness for a particular use. Page 2 |

**MICREL** 

#### Nominal Performance Parameters (Unless specified otherwise: T=25° C, V<sub>DD</sub>=3.3 V)



Phase jitter (integrated phase noise)

#### Power supply rejection ratio

#### **Output Waveform**



#### **Typical Termination Scheme**



All Rights Reserved. No part of this document may be copied or reproduced in any form without the prior written permission of Micrel, Inc. Micrel Inc. may update or make changes to the contents, products, programs or services described at any time without notice. This document neither states nor implies any kind of warranty, including, but not limited to implied warranties of merchantability or fitness for a particular use. Page 3 |



#### **Test Circuit**



#### **Board Layout (recommended)**



#### **Solder Reflow Profile**



MSL 1 @ 260°C refer to JSTD-020C					
Ramp-Up Rate (200°C to Peak Temp)	3°C/Sec Max.				
Preheat Time 150°C to 200°C	60-180 Sec				
Time maintained above 217°C	60-150 Sec				
Peak Temperature	255-260°C				
Time within 5°C of actual Peak	20-40 Sec				
Ramp-Down Rate	6°C/Sec Max.				
Time 25°C to Peak Temperature	8 min Max.				

All Rights Reserved. No part of this document may be copied or reproduced in any form without the prior written permission of Micrel, Inc. Micrel Inc. may update or make changes to the contents, products, programs or services described at any time without notice. This document neither states nor implies any kind of warranty, including, but not limited to implied warranties of merchantability or fitness for a particular use. Page 4 | MK-Q-B-P-D-110410-01-2

#### **Package Dimensions**



#### 7.0 x 5.0 mm Plastic Package

#### 5.0 x 3.2 mm Plastic Package



**MICREL** 

All Rights Reserved. No part of this document may be copied or reproduced in any form without the prior written permission of Micrel, Inc. Micrel Inc. may update or make changes to the contents, products, programs or services described at any time without notice. This document neither states nor implies any kind of warranty, including, but not limited to implied warranties of merchantability or fitness for a particular use. Page 5 |

### MICREL

#### 3.2 x 2.5 mm Plastic Package



#### 2.5 x 2.0 mm Plastic Package



#### **Disclaimer:**

Micrel makes no representations or warranties with respect to the accuracy or completeness of the information furnished in this data sheet. This information is not intended as a warranty and Micrel does not assume responsibility for its use. Micrel reserves the right to change circuitry, specifications and descriptions at any time without notice. No license, whether express, implied, arising by estoppel or otherwise, to any intellectual property rights is granted by this document. Except as provided in Micrel's terms and conditions of sale for such products, Micrel assumes no liability whatsoever, and Micrel disclaims any express or implied warranty relating to the sale and/or use of Micrel products including liability or warranties relating to fitness for a particular purpose, merchantability, or infringement of any patent, copyright or other intellectual property right.

MICREL, Inc.	•	2180 Fortune Drive,	San Jose, California	95131	•	USA
Phone: +1 (408) 944-0800	•	Fax: +1 (408) 474-1000	• Email: hbwhelp@micrel.	com	•	www.micrel.com

All Rights Reserved. No part of this document may be copied or reproduced in any form without the prior written permission of Micrel, Inc. Micrel Inc. may update or make changes to the contents, products, programs or services described at any time without notice. This document neither states nor implies any kind of warranty, including, but not limited to implied warranties of merchantability or fitness for a particular use. Page 6 |