# imall

Chipsmall Limited consists of a professional team with an average of over 10 year of expertise in the distribution of electronic components. Based in Hongkong, we have already established firm and mutual-benefit business relationships with customers from, Europe, America and south Asia, supplying obsolete and hard-to-find components to meet their specific needs.

With the principle of "Quality Parts, Customers Priority, Honest Operation, and Considerate Service", our business mainly focus on the distribution of electronic components. Line cards we deal with include Microchip, ALPS, ROHM, Xilinx, Pulse, ON, Everlight and Freescale. Main products comprise IC, Modules, Potentiometer, IC Socket, Relay, Connector. Our parts cover such applications as commercial, industrial, and automotives areas.

We are looking forward to setting up business relationship with you and hope to provide you with the best service and solution. Let us make a better world for our industry!



## Contact us

Tel: +86-755-8981 8866 Fax: +86-755-8427 6832 Email & Skype: info@chipsmall.com Web: www.chipsmall.com Address: A1208, Overseas Decoration Building, #122 Zhenhua RD., Futian, Shenzhen, China



### **EuroMag Series PCB Mount Terminal Blocks**

#### EM3675 Series **EuroMag Terminal Blocks** 5.00 Centers

**SPECIFICATIONS** 

Rating: 10A, 300V Center Spacing: 0.197" (5.00mm) Wire Range: #14-26 AWG Housing Material: UL rated 94V0 Thermoplastic Contact Material: Tin-Plated Brass Screw Size: M2.6 Zinc-Plated Steel Operating Temperature: 105°C (221°F) max., -40°C (-40°F) min. Torque Rating: 4.0 lb-in. Recommended PCB Hole Diameters: 0.055" (1.40mm) Construction: Mold to Length Connector Style: Spring and Screw Agency Information: File E62622; CE Certified

**Dimensions - (in) mm** 

0.39

(10.0) ¥.

0.19

(4.8)

0.32

				→ (8.0)
Poles	L (mm)	Poles	L (mm)	
2 3 4 5 6 7 8 9 10 11 12	10.0 15.0 20.0 25.0 30.0 35.0 40.0 45.0 50.0 55.0 60.0	15 16 17 18 19 20 21 22 23 24		0.039 (1.00)

#### **Part Numbering System**

65.0

70.0

Series


13

14

To convert to inches, divide by 25.4

# of Poles





0.15

(3.7)

4

0.197

(5.00)

 $\overline{\mathbb{C}}$ 


Edge Connectors

Board

Blocks:

Spring & Screw **EuroMag Series** 





0.024

(0.60)



33