

Chipsmall Limited consists of a professional team with an average of over 10 year of expertise in the distribution of electronic components. Based in Hongkong, we have already established firm and mutual-benefit business relationships with customers from, Europe, America and south Asia, supplying obsolete and hard-to-find components to meet their specific needs.

With the principle of "Quality Parts, Customers Priority, Honest Operation, and Considerate Service", our business mainly focus on the distribution of electronic components. Line cards we deal with include Microchip, ALPS, ROHM, Xilinx, Pulse, ON, Everlight and Freescale. Main products comprise IC, Modules, Potentiometer, IC Socket, Relay, Connector. Our parts cover such applications as commercial, industrial, and automotives areas.

We are looking forward to setting up business relationship with you and hope to provide you with the best service and solution. Let us make a better world for our industry!



### Contact us

Tel: +86-755-8981 8866 Fax: +86-755-8427 6832

Email & Skype: info@chipsmall.com Web: www.chipsmall.com

Address: A1208, Overseas Decoration Building, #122 Zhenhua RD., Futian, Shenzhen, China







## F3300 RFI Filters





#### Features:

- · General Purpose "L-Type" Circuit Effective in Reducing Both Incoming and Outgoing Powerline Noise Levels in FCC "A" Applications
- · Integral 5 X 20mm Single or Dual Fused IEC Connector
- · Optional SST Switched IEC Connector
- · Low-Leakage
- Available to UL/IEC 60601 Standard and Meets UL 544 Specification for Medical and Dental Applications
- · Available in Labor-Saving PC Mounted Case Style

#### Specifications:

Rated Voltage: 250VAC Maximum - 50/60 Hz **Rated Current:** 115VAC 250VAC 3A 3A

6A 6A

Current Overload: 6X for 8 seconds

Hi-Pot Test (1 min):

Line to Ground 1500VAC Line to Line 1768VDC

Insulation Resistance: 9 x 109 Ω at 100VDC Ambient Temperature: 40°C Max. at Rated Current

Humidity Range: 0% to 95% R.H.

Termination:

A: QC - Quick Connect

F: Fused IEC J: Switched IEC P: PC - P.C. Board W: Dual Fused IEC

**Maximum Leakage Current:** Each Line to Ground F3300 115VAC, 60Hz: .015mA 250VAC, 50Hz: .025mA

**Agency Approvals:** 










#### F3300F Simplified Schematic




Nominal Current Rating	Part Number	Termination Line/Load	MINIMUM INSERTION LOSS - dB (50 ohm Circuit)						
			MODE	Frequency - MHz					
				.15	.50	1.0	5.0	10	30
3A	F3300FA03 F3300FP03	Fused IEC/QC Fused IEC/PC	Common Differential	21 <b>8</b>	32 <b>18</b>	36 <b>24</b>	30 <b>35</b>	28 <b>35</b>	28 <b>35</b>
6A	F3300FA06 F3300FP06	Fused IEC/QC Fused IEC/PC	Common Differential	18 <b>8</b>	30 <b>18</b>	34 <b>24</b>	26 <b>35</b>	25 <b>35</b>	25 <b>35</b>
3A	F3300WA03 F3300WP03	Dual Fused IEC/QC Dual Fused IEC/PC	Common Differential	21 <b>8</b>	32 18	36 <b>24</b>	30 <b>35</b>	28 <b>35</b>	28 <b>35</b>
6A	F3300WA06 F3300WP06	Dual Fused IEC/QC Dual Fused IEC/PC	Common Differential	18 <b>8</b>	30 <b>18</b>	34 <b>24</b>	26 <b>35</b>	25 <b>35</b>	25 <b>35</b>
3A	F3300JA03 F3300JP03	Switched IEC/QC Switched IEC/PC	Common Differential	21 <b>8</b>	32 <b>18</b>	36 <b>24</b>	30 <b>35</b>	28 <b>35</b>	28 <b>35</b>
6A	F3300JA06 F3300JP06	Switched IEC/QC Switched IEC/PC	Common Differential	18 <b>8</b>	30 <b>18</b>	34 <b>24</b>	26 <b>35</b>	25 <b>35</b>	25 <b>35</b>

NOTE: Other combinations of terminals may be specified on special order.




# F3300 Series (continued)

#### F3300FA (3 and 6Amp) Dimensions




F3300WA (3 and 6Amp) Dimensions


#### **F3300W Simplified Schematic**





# **F3300JA** (3 and 6Amp) Dimensions **F3300J Simplified Schematic**



#### F3300FP (3 and 6Amp) Dimensions











# **Standard Mounting Cutouts**

# F2199CA, F2200CA, F2300CA, F2400CA, F2500CA, F2700CA, F3100CA, F3200CA, F3400CA, F3500CA



**Back Mounting** 



# F2600FP, F3300FP .062 Dia. (1,57) 5 Holes .600 (15,24) (7,62)

