



Chipsmall Limited consists of a professional team with an average of over 10 year of expertise in the distribution of electronic components. Based in Hongkong, we have already established firm and mutual-benefit business relationships with customers from,Europe,America and south Asia,supplying obsolete and hard-to-find components to meet their specific needs.

With the principle of “Quality Parts,Customers Priority,Honest Operation,and Considerate Service”,our business mainly focus on the distribution of electronic components. Line cards we deal with include Microchip,ALPS,ROHM,Xilinx,Pulse,ON,Everlight and Freescale. Main products comprise IC,Modules,Potentiometer,IC Socket,Relay,Connector.Our parts cover such applications as commercial,industrial, and automotives areas.

We are looking forward to setting up business relationship with you and hope to provide you with the best service and solution. Let us make a better world for our industry!



Contact us

Tel: +86-755-8981 8866 Fax: +86-755-8427 6832

Email & Skype: info@chipsmall.com Web: www.chipsmall.com

Address: A1208, Overseas Decoration Building, #122 Zhenhua RD., Futian, Shenzhen, China





American Hakko Products, Inc.

PRODUCT BULLETIN

Bulletin No: PB308

Issue Date: April 26, 2011

Available: May 10, 2011


Product Description:

FA-430 Fume Extraction System

Part No:

FA430-16

Specifications:

Power Consumption	120 W
Max. Airflow (One Port)	4.1 m ³ /min (145 cfm)
Max. Airflow (Two Ports)	4.7 m ³ /min (167 cfm)
Filtering Efficiency	>98% @ 0.3µm (Capable of 99.97% @ 0.3µm)
Noise Level	44 - 53dB @ 1m
Dimensions (W x H x D)	330 x 366 x 343 mm 13.0 x 14.4 x 13.5 in.
Weight	7.5 kg (16.5 lb.)
Static Pressure	1500 Pa (0.44 in. Hg)
Safety Approval	



C1571 Duct Kit



C1572 Duct Kit

Features:

- Powerful suction
- Quiet operation – as low as 44dB
- 3-airflow adjustment modes: High, Medium, Low
- Compatible with existing HJ3100 Duct Kits or NEW Free standing ducts kits (pictured above)
- Special filter replacement notification function *detects the fan speed and notifies the operator of the appropriate time to replace the filters via indicator lights on the front panel.*

Note: Duct Kits sold separately

For more information, visit our website at www.HakkoUSA.com

CONTENTS		
Model Name	Description	Part Number
FA-430	Pre-filter	A1585
	Main Filter	A1586
	Power Cord	

For additional information:

- End-User Customers – Call Customer Support at 1-800-88-HAKKO (42556)
- Authorized Distributors – Call Distributor Support at 661-294-0090

From...

American Hakko Products, Inc.
 28920 Avenue Williams.
 Valencia, CA 91355
 Tel: (661) 294-0090
 Fax: (661) 294-0096
www.HakkoUSA.com
 AHP14 Rev 2007-12