



Chipsmall Limited consists of a professional team with an average of over 10 year of expertise in the distribution of electronic components. Based in Hongkong, we have already established firm and mutual-benefit business relationships with customers from,Europe,America and south Asia,supplying obsolete and hard-to-find components to meet their specific needs.

With the principle of “Quality Parts,Customers Priority,Honest Operation,and Considerate Service”,our business mainly focus on the distribution of electronic components. Line cards we deal with include Microchip,ALPS,ROHM,Xilinx,Pulse,ON,Everlight and Freescale. Main products comprise IC,Modules,Potentiometer,IC Socket,Relay,Connector.Our parts cover such applications as commercial,industrial, and automotives areas.

We are looking forward to setting up business relationship with you and hope to provide you with the best service and solution. Let us make a better world for our industry!



## Contact us

Tel: +86-755-8981 8866 Fax: +86-755-8427 6832

Email & Skype: info@chipsmall.com Web: www.chipsmall.com

Address: A1208, Overseas Decoration Building, #122 Zhenhua RD., Futian, Shenzhen, China



# 365 True-rms AC Clamp Meter

Rugged meters where access is difficult

The Fluke 365 is a new, innovative Fluke clamp meter, offering a thin, small jaw design that makes it easy to get around tightly packed wires. The detachable jaw on a flexible lead makes access to wires and viewing the display easier than ever. The Fluke 365 measures current up to 200 A ac and dc with true-rms measurement.

**New**



**True  
RMS**



## Technical Data

### Measurement capability

- 200 A ac and dc current measurement with detachable jaw
- 600 V ac and dc voltage measurement
- True-rms ac voltage and current for accurate measurements on non-linear signals
- 6000  $\Omega$  resistance measurement with continuity detection

### Features

- Detachable jaw makes accessing wires and viewing the display easier
- Built in flashlight/torch allows for easy illumination and identification of wires
- CAT III 600 V safety rating
- Compact design fits in your hand and can be used while wearing personal protective equipment
- State of the art signal processing allows for use in noisy electrical environments while providing stable readings
- Large, easy to read backlight display automatically sets the correct measurement range so you do not need to change switch positions while taking a measurement
- Three-year warranty
- Soft case



## Specifications

Fluke 365	Range	Resolution	Accuracy
AC current	200 A	0.1 A	2 % ± 5 digits
DC current	200 A	0.1 A	2 % ± 5 digits
AC voltage	600 V	0.1 V	2 % ± 5 digits
DC voltage	600 V	0.1 V	2 % ± 5 digits
Resistance	6000 Ω	0.1 Ω	1 % ± 5 digits
True-rms	•		
Continuity	•		
Hold	•		
Backlight	•		
Flashlight/torch	•		
Wire capacity	17 mm		
Safety rating	CAT III 600 V		

## Ordering information

365 True-rms AC/DC  
Clamp Meter

### Included

Clamp meter, test leads, soft case, users manual.

**Fluke.** *Keeping your world up and running.*®

**Fluke Corporation**  
PO Box 9090, Everett, WA 98206 U.S.A.

**Fluke Europe B.V.**  
PO Box 1186, 5602 BD  
Eindhoven, The Netherlands

**For more information call:**  
In the U.S.A. (800) 443-5853 or  
Fax (425) 446-5116  
In Europe/M-East/Africa +31 (0) 40 2675 200 or  
Fax +31 (0) 40 2675 222  
In Canada (800)-36-FLUKE or  
Fax (905) 890-6866  
From other countries +1 (425) 446-5500 or  
Fax +1 (425) 446-5116  
Web access: <http://www.fluke.com>

©2010 Fluke Corporation.  
Specifications subject to change without notice.  
Printed in U.S.A. 8/2010 3805299A D-EN-N

**Modification of this document is not permitted without written permission from Fluke Corporation.**