

Chipsmall Limited consists of a professional team with an average of over 10 year of expertise in the distribution of electronic components. Based in Hongkong, we have already established firm and mutual-benefit business relationships with customers from, Europe, America and south Asia, supplying obsolete and hard-to-find components to meet their specific needs.

With the principle of "Quality Parts, Customers Priority, Honest Operation, and Considerate Service", our business mainly focus on the distribution of electronic components. Line cards we deal with include Microchip, ALPS, ROHM, Xilinx, Pulse, ON, Everlight and Freescale. Main products comprise IC, Modules, Potentiometer, IC Socket, Relay, Connector. Our parts cover such applications as commercial, industrial, and automotives areas.

We are looking forward to setting up business relationship with you and hope to provide you with the best service and solution. Let us make a better world for our industry!



Contact us

Tel: +86-755-8981 8866 Fax: +86-755-8427 6832

Email & Skype: info@chipsmall.com Web: www.chipsmall.com

Address: A1208, Overseas Decoration Building, #122 Zhenhua RD., Futian, Shenzhen, China









Gas Discharge Tube Three Electrode Q Series

Overvoltage Protection Device

Raychem Circuit Protection Products

PRODUCT: GTCx38-xxxx-Q10

DOCUMENT: SCD 25913

REV LETTER: D

REV DATE: JULY 7, 2008 PAGE NO.: 1 OF 7

Specification Status: Released

GENERAL DESCRIPTION

BENEFITS

- Helps provide overvoltage fault protection against high energy surges
- Suitable for sensitive equipment due to excellent impulse sparkover response
- Suitable for high-frequency applications
- Highly reliable performance

FEATURES

- Crowbar device with low arc-voltage
- Low capacitance and insertion loss
- · High accuracy spark-over voltages for high precision designs
- Tested per ITU K.12 recommendations
- Optional Fail-Short mechanism
- Non-radioactive materials


APPLICATIONS

- Telecommunications:
 - MDF modules, xDSL equipment, RF system protection
- Industrial Electronics and Commercial Electronics, such as
 - Power Supplies, Surge Protectors, Alarm systems

SYMBOL



TYPICAL APPLICATION SCHEMATIC





Gas Discharge Tube Three Electrode Q Series

Overvoltage Protection Device

Raychem Circuit Protection Products

PRODUCT: GTCx38-xxxx-Q10

DOCUMENT: SCD 25913

REV LETTER: D

251: 25 x 10 ^ 1 = 250V 351: 35 x 10 ^ 1 = 350V 421: 42 x 10 ^ 1 = 421V 501: 50 x 10 ^ 1 = 501V

REV DATE: JULY 7, 2008


PAGE NO.: 2 OF 7

PART NUMBERING

EXAMPLE: - Packaging Series No Suffix: standard Tray packaging GT: Gas Tube -B: Bulk packaging (only upon special request) Material C: Ceramic with Fail-Short mechanism **Surge Rating Type** 10: 10kA (10 times 8 x 20μs) N: No Leads R: Radial Leaded **Product Family Number of Electrodes Voltage Tolerance** 3: Three M: ± 20% Diameter 8:8mm **Voltage Designator** 900 : 90 x 10 ^ 0 = 90V 151:15 x 10 ^ 1 = 151V 231 : 23 x 10 ^ 1 = 230V

DEVICE MARKING

EXAMPLE: GTCR38-231M-Q10





Gas Discharge Tube Three Electrode Q Series

Overvoltage Protection Device

Raychem Circuit Protection Products

PRODUCT: GTCx38-xxxx-Q10

DOCUMENT: SCD 25913

REV LETTER: D REV DATE: JULY 7, 2008

PAGE NO.: 3 OF 7

GENERAL CHARACTERISTICS

No Radioactive Material

Storage temperature:


Devices without Fail-Short Mechanism: -40°C ... +90°C Devices with Fail-Short Mechanism: -20°C ... +65°C

Operating temperature:

Devices without Fail-Short Mechanism: -40°C ... +90°C Devices with Fail-Short Mechanism: -20°C ... +65°C

Body: Nickel Plated

Leads: Tin Plated



MATERIALS INFORMATION

ROHS Compliant ELV Compliant

Directive 2002/95/EC Compliant

Directive 2000/53/EC Compliant



Gas Discharge Tube Three Electrode Q Series

Overvoltage Protection Device

Raychem Circuit Protection Products

PRODUCT: GTCx38-xxxx-Q10

DOCUMENT: SCD 25913

REV LETTER: D

REV DATE: JULY 7, 2008

PAGE NO.: 4 OF 7

DEVICE RATINGS AND CHARACTERISTICS

	DC Sparkover Voltage (A-E) (B-E)	Impulse Sparkover Voltage (A-E) (B-E)		Insulation Resistance	Capacitance	DC Holdover Voltage	Impulse Life (A + B - E)	Impulse Discharge Current 8/20µs (A + B - E)	AC Discharge Current, 50Hz (A + B - E)
Part Number	@ 100V/s	@ 100V/μs	@ 1kV/µs	@ 100V _{DC}	@ 1MHz	Per ITU K.12	10/1000μs, 200A	Repeat 10 times (5 times each polarity)	Repeat 5 times (1s interval)
GTCN38-900M-Q10 GTCN38-900M-Q10-FS GTCR38-900M-Q10 GTCR38-900M-Q10-FS	72-108	≤ 450	≤ 500V	≥ 10,000MΩ	≤ 3.0pF	≤ 52V	300 times	10kA	10A
GTCN38-151M-Q10 GTCN38-151M-Q10-FS GTCR38-151M-Q10 GTCR38-151M-Q10-FS	120 - 180	≤ 500	≤ 600	≥ 10,000MΩ	≤ 3.0pF	≤ 52V	300 times	10kA	10A
GTCN38-231M-Q10 GTCN38-231M-Q10-FS GTCR38-231M-Q10 GTCR38-231M-Q10-FS	184 - 280V	≤ 600	≤ 700V	≥ 10,000MΩ	≤ 3.0pF	≤ 135V	300 times	10kA	10A
GTCN38-251M-Q10 GTCN38-251M-Q10-FS GTCR38-251M-Q10 GTCR38-251M-Q10-FS	200 - 300V	≤ 600	≤ 700V	≥ 10,000MΩ	≤ 3.0pF	≤ 135V	300 times	10kA	10A
GTCN38-351M-Q10 GTCN38-351M-Q10-FS GTCR38-351M-Q10 GTCR38-351M-Q10-FS	280 - 420V	≤ 900	≤ 900V	≥ 10,000MΩ	≤ 3.0pF	≤ 135V	300 times	10kA	10A
GTCN38-421M-Q10 GTCN38-421M-Q10-FS GTCR38-421M-Q10 GTCR38-421M-Q10-FS	300 - 500	≤ 900	≤ 1000	≥ 10,000MΩ	≤ 3.0pF	≤ 135V	300 times	10kA	10A
GTCN38-501M-Q10 GTCN38-501M-Q10-FS GTCR38-501M-Q10 GTCR38-501M-Q10-FS	400 - 600	≤ 1100	≤ 1200	≥ 10,000MΩ	≤ 3.0pF	≤ 135V	300 times	10kA	10A



Gas Discharge Tube Three Electrode Q Series

Overvoltage Protection Device

Raychem Circuit Protection Products

PRODUCT: GTCx38-xxxx-Q10


DOCUMENT: SCD 25913

REV LETTER: D REV DATE: JULY 7, 2008

PAGE NO.: 5 OF 7

DIMENSIONS

No Leads, no Fail-Short mechanism (GTCN38-xxxx-Q10)






mm: in*:

A	4	С		
MIN	MAX	MIN	MAX	
9.7	10.3	7.8	8.2	
0.38	0.41	0.31	0.32	

No Leads, with Fail-Short mechanism (GTCN38-xxxx-10-FS)



mm: in*:

Α		E	3	С		F		G	
MIN	MAX	MIN	MAX	MIN	MAX	MIN	MAX	MIN	MAX
9.7	10.3		9.5		8.2		10.5		3.0
0.38	0.41	-	0.37	1	0.32	1	0.41	1	0.12

Rounded off approximation



Gas Discharge Tube Three Electrode Q Series

Overvoltage Protection Device

Raychem Circuit Protection Products

PRODUCT: GTCx38-xxxx-Q10


DOCUMENT: SCD 25913

REV LETTER: D

REV DATE: JULY 7, 2008

PAGE NO.: 6 OF 7

Radial Leads, no Fail-Short mechanism (GTCR38-xxxx-Q10)







mm: in*:

A	4	С		D		E		Ød
MIN	MAX	MIN	MAX	MIN	MAX	MIN	MAX	NOM
9.7	10.3	7.8	8.2	6.5	7.5	4.1	4.7	1.0
0.38	0.41	0.31	0.32	0.26	0.30	0.16	0.19	0.04

^{*} Rounded off approximation

Radial Leads, with Fail-Short mechanism (GTCR38-xxxxQ10-FS)





mm: in*:

1	4	В		С			D		E	
MIN	MAX	MIN	MAX	MIN	MAX	MIN	MAX	MIN	MAX	NOM
9.7	10.3		9.5		8.5	6.0		4.1	4.7	1.0
0.38	0.41		0.37		0.34	0.24		0.16	0.19	0.04

^{*} Rounded off approximation



Gas Discharge Tube Three Electrode Q Series

Overvoltage Protection Device

Raychem Circuit Protection Products


PRODUCT: GTCx38-xxxx-Q10

DOCUMENT: SCD 25913

REV LETTER: D REV DATE: JULY 7, 2008

PAGE NO.: 7 OF 7

FAIL-SHORT MECHANISM RESPONSE TIME (Graph represents typical values)



Note: Both electrodes simultaneously powered, each with the AC current value in the graph

PACKAGING

Packaging	Bulk* (vacuum bags)	Tray	Standard Box	
Quantity	200	100	1,000**	

 ^{*} Standard packaging is in trays.
 Bulk packaging is only available upon request.

Information furnished is believed to be accurate and reliable. However, users should independently evaluate the suitability of each product for their applications. Tyco Electronics Corporation assumes no responsibility for the use of its product or for any infringement of patents or other rights of third parties resulting from the use of its product. No license is granted by implication or otherwise under any patent or proprietary right of Tyco Electronics except the right to use such product for the purpose for which it is sold. Tyco Electronics reserves the right to change or update, without notice, any information contained in this publication; to change, without notice, the design, construction, processing, or specification of any product; and to discontinue or limit production or distribution of any product. This publication supersedes and replaces all information previously supplied. Without expressed or written consent by an officer of Tyco Electronics, Tyco Electronics does not authorize the use of any of its products as components in nuclear facility applications, aerospace, or in critical life support devices or systems. Tyco Electronics' only obligations are those in the Tyco Electronics Standard Terms and Conditions of Sale and in no case will Tyco Electronics be liable for any incidental, indirect, or consequential damages arising from the sale, resale, use, or misuse of its products.

^{** 5} bags or 10 trays