# imall

Chipsmall Limited consists of a professional team with an average of over 10 year of expertise in the distribution of electronic components. Based in Hongkong, we have already established firm and mutual-benefit business relationships with customers from, Europe, America and south Asia, supplying obsolete and hard-to-find components to meet their specific needs.

With the principle of "Quality Parts, Customers Priority, Honest Operation, and Considerate Service", our business mainly focus on the distribution of electronic components. Line cards we deal with include Microchip, ALPS, ROHM, Xilinx, Pulse, ON, Everlight and Freescale. Main products comprise IC, Modules, Potentiometer, IC Socket, Relay, Connector. Our parts cover such applications as commercial, industrial, and automotives areas.

We are looking forward to setting up business relationship with you and hope to provide you with the best service and solution. Let us make a better world for our industry!



# Contact us

Tel: +86-755-8981 8866 Fax: +86-755-8427 6832 Email & Skype: info@chipsmall.com Web: www.chipsmall.com Address: A1208, Overseas Decoration Building, #122 Zhenhua RD., Futian, Shenzhen, China







v04.0110

# HMC232LP4 / 232LP4E

# GaAs MMIC SPDT NON-REFLECTIVE SWITCH, DC - 12 GHz


# Typical Applications

The HMC232LP4(E) is ideal for:

Available

- Telecom Infrastructure
- Microwave Radio & VSAT
- Military Radios, Radar & ECM
- Test Instrumentation

### Functional Diagram



#### **Features**

Isolation: 60 dB @ 3 GHz 52 dB @ 6 GHz

Input P1dB: +27 dBm

Insertion Loss: 1.5 dB Typical @ 6 GHz

Non-Reflective Design

24 Lead 4x4mm QFN Package: 16mm<sup>2</sup>

Included in the HMC-DK005 Designer's Kit

## General Description

The HMC232LP4(E) is a broadband high isolation non-reflective GaAs MESFET SPDT switch in a low cost leadless QFN surface mount plastic package. Covering DC to 12 GHz, the switch features >60 dB isolation up to 3 GHz and >42 dB isolation up to 12 GHz. Input P1dB compression is +27 dBm typical, while input IP3 is +50 dBm. The switch operates using complementary negative control voltage logic lines of -5/0V and requires no bias supply.

#### Electrical Specifications, $T_A = +25^{\circ}$ C, With 0/-5V Control, 50 Ohm System

Parameter	Frequency	Min.	Тур.	Max.	Units
Insertion Loss	DC - 3.0 GHz DC - 6.0 GHz DC - 9.0 GHz DC - 12.0 GHz		1.4 1.5 2.0 2.7	1.7 1.8 2.3 3.1	dB dB dB dB
Isolation	DC - 3.0 GHz DC - 6.0 GHz DC - 9.0 GHz DC - 12.0 GHz	55 47 40 37	60 52 45 42		dB dB dB dB
Return Loss "On State"	DC - 6.0 GHz DC - 9.0 GHz DC - 12.0 GHz		18 16 11		dB dB dB
Return Loss RF1, RF2 "Off State"	DC - 12.0 GHz		14		dB
Input Power for 1 dB Compression	0.5 - 12.0 GHz	24	27		dBm
Input Third Order Intercept (Two-Tone Input Power= +7 dBm Each Tone, 1 MHz Tone Separation)	0.5 - 12.0 GHz	45	50		dBm
Switching Characteristics tRISE, tFALL (10/90% RF) tON, tOFF (50% CTL to 10/90% RF)	DC - 12.0 GHz		3 6		ns ns

Information furnished by Analog Devices is believed to be accurate and reliable. However, no responsibility is assumed by Analog Devices for its use, nor for any infringements of patents or other rights of third parties that may result from its use. Specifications subject to change without notice. No license is granted by implication or otherwise under any patent or patent rights of Analog Devices. Trademarks and registered trademarks are the property of their respective owners.




# GaAs MMIC SPDT NON-REFLECTIVE SWITCH, DC - 12 GHz

Isolation




### **Insertion Loss**




v04.0110

#### **Return Loss**




-10 -20 RF1 -30 -RF2 **ISOLATION (dB)** -40 -50 -60 -70 -80 2 3 4 7 8 10 11 12 13 0 1 5 6 9

0.1 and 1 dB Input Compression Point



## Input Third Order Intercept Point



Information furnished by Analog Devices is believed to be accurate and reliable. However, no responsibility is assumed by Analog Devices for its use, nor for any infringements of patents or other rights of third parties that may result from its use. Specifications subject to change without notice. No license is granted by implication or otherwise under any patent or patent rights of Analog Devices. Trademarks and registered trademarks are the property of their respective owners.



GaAs MMIC SPDT NON-REFLECTIVE



v04.0110

# SWITCH, DC - 12 GHz

### Absolute Maximum Ratings

RF Input Power (VctI = -5V) (0.5 - 12 GHz)	+30 dBm (@ +50 °C)
RF1, RF2 Termination	+23.5 dBm
Control Voltage Range (A & B)	+1V to -7.5V
Channel Temperature	150 °C
Thermal Resistance (R <sub>TH</sub> ) (junction to lead)	94 °C/W
Storage Temperature	-65 to +150 °C
Operating Temperature	-40 to +85 °C
ESD Sensitivity (HBM)	Class 1A



#### ELECTROSTATIC SENSITIVE DEVICE **OBSERVE HANDLING PRECAUTIONS**

# **Outline Drawing**


#### **Control Voltages**

State	Bias Condition	
Low	0 to -0.2V @ 10 uA Max.	
High	-5V @ 10 uA Typ. to -7V @ 45 uA Typ. (±0.5 Vdc)	

#### **Truth Table**

Control Input		Signal Path State		
A	В	RFC to RF1	RFC to RF2	
High	Low	ON	OFF	
Low	High	OFF	ON	

Caution: Do not "Hot Switch" power levels greater than +27 dBm (Vctl = 0/-5 Vdc).



PLANE

-C-

- 2. DIMENSIONS ARE IN INCHES [MILLIMETERS]
- 3. LEAD SPACING TOLERANCE IS NON-CUMULATIVE.
- 4. PAD BURR LENGTH SHALL BE 0.15mm MAXIMUM. PAD BURR HEIGHT SHALL BE 0.05mm MAXIMUM.
- 5. PACKAGE WARP SHALL NOT EXCEED 0.05mm.
- 6 ALL GROUND LEADS AND GROUND PADDLE MUST BE
- SOLDERED TO PCB RF GROUND. 7. REFER TO HITTITE APPLICATION NOTE FOR SUGGESTED
  - LAND PATTERN.

#### Package Marking [3] Part Number Package Body Material Lead Finish MSL Rating H232 HMC232LP4 Sn/Pb Solder MSL1 [1] Low Stress Injection Molded Plastic XXXX <u>H232</u> MSL1 [2] HMC232LP4E RoHS-compliant Low Stress Injection Molded Plastic 100% matte Sn XXXX

[1] Max peak reflow temperature of 235 °C

.003[0.08] C

Package Information

[2] Max peak reflow temperature of 260 °C

[3] 4-Digit lot number XXXX

Information furnished by Analog Devices is believed to be accurate and reliable. However, no responsibility is assumed by Analog Devices for its use, nor for any infringements of patents or other rights of third parties that may result from its use. Specifications subject to change without notice. No license is granted by implication or otherwise under any patent or patent rights of Analog Devices. Trademarks and registered trademarks are the property of their respective owners.




v04.0110



# GaAs MMIC SPDT NON-REFLECTIVE SWITCH, DC - 12 GHz

## **Suggested Driver Circuit**



## **Pin Descriptions**

Pin Number	Function	Description	Interface Schematic
1, 2, 6, 7, 11, 12, 13, 14, 17, 18, 19, 20, 24	N/C	The pins are not connected internally; however, all data shown herein was measured with these pins connected to RF/DC ground externally.	
3, 5, 8, 10, 21, 23	GND	Package bottom must also be connected to PCB RF ground.	
4, 9, 22	RFC, RF1, RF2	This pin is DC coupled and matched to 50 Ohm. Blocking capacitors are required if RF line potential is not equal to 0V.	
15	В	See truth table and control voltage table.	R
16	А	See truth table and control voltage table.	i ⊂ c




v04.0110



# GaAs MMIC SPDT NON-REFLECTIVE SWITCH, DC - 12 GHz

## **Evaluation PCB**



## List of Materials for Evaluation PCB 107723 [1]

Item	Description
J1 - J3	PCB Mount SMA RF Connector
J4 - J6	DC Pin
C1, C2	100 pF Capacitor, 0603 Pkg.
U1	HMC232LP4 / HMC232LP4E SPDT Switch
PCB [2]	107602 Evaluation PCB

Reference this number when ordering complete evaluation PCB
Circuit Board Material: Rogers 4350

The circuit board used in the application should be generated with proper RF circuit design techniques. Signal lines at the RF port should have 50 Ohm impedance and the package ground leads and package bottom should be connected directly to the ground plane similar to that shown above. The evaluation circuit board shown above is available from Hittite Microwave Corporation upon request.

11



v04.0110



GaAs MMIC SPDT NON-REFLECTIVE SWITCH, DC - 12 GHz

Notes:

Information furnished by Analog Devices is believed to be accurate and reliable. However, no responsibility is assumed by Analog Devices for its use, nor for any infringements of patents or other rights of third parties that may result from its use. Specifications subject to change without notice. No license is granted by implication or otherwise under any patent or patent rights of Analog Devices. Trademarks and registered trademarks are the property of their respective owners.