

Chipsmall Limited consists of a professional team with an average of over 10 year of expertise in the distribution of electronic components. Based in Hongkong, we have already established firm and mutual-benefit business relationships with customers from, Europe, America and south Asia, supplying obsolete and hard-to-find components to meet their specific needs.

With the principle of "Quality Parts, Customers Priority, Honest Operation, and Considerate Service", our business mainly focus on the distribution of electronic components. Line cards we deal with include Microchip, ALPS, ROHM, Xilinx, Pulse, ON, Everlight and Freescale. Main products comprise IC, Modules, Potentiometer, IC Socket, Relay, Connector. Our parts cover such applications as commercial, industrial, and automotives areas.

We are looking forward to setting up business relationship with you and hope to provide you with the best service and solution. Let us make a better world for our industry!



Contact us

Tel: +86-755-8981 8866 Fax: +86-755-8427 6832

Email & Skype: info@chipsmall.com Web: www.chipsmall.com

Address: A1208, Overseas Decoration Building, #122 Zhenhua RD., Futian, Shenzhen, China








Reflective Sensor

FEATURES

- Choice of phototransistor or photodarlington output
- Low profile package
- · Hermetic style emitter and detector
- · Focused for maximum response
- 24.0 in.(610 mm) min. 26 AWG Teflon insulated lead wires



DESCRIPTION

The HOA1406 series consists of an infrared emitting diode facing an NPN silicon phototransistor (HOA1406-001) or photodarlington (HOA1406-003) encased side- by- side on converging optical axes, in a black thermoplastic housing. The detector responds to radiation from the IRED only when a reflective object passes within its field of view. This low profile sensor is ideally suited for applications where space is limited, or stacking of sensors is required. The HOA1406 series employs hermetically sealed metal can packaged components. For additional component information see SE2460, SD2440, SD2410.


Housing material is polycarbonate. Housings are soluble in chlorinated hydrocarbons and ketones. Recommended cleaning agents are methanol and isopropanol.

Wire color code and functions are:

IRFD anode - red IRED cathode - black Collector - white Emitter - green

OUTLINE DIMENSIONS in inches (mm)

3 plc decimals ±0.010(0.25) 2 plc decimals ±0.020(0.51)



DIM_072.ds4



Reflective Sensor

ELECTRICAL CHARACTERISTICS (25°C unless otherwise noted)

PARAMETER	SYMBOL	MIN	TYP	MAX	UNITS	TEST CONDITIONS
IR EMITTER						
Forward Voltage	VF			1.6	V	I _F =20 mA
Reverse Leakage Current	I _R			10	μΑ	V _R =3 V
DETECTOR Collector-Emitter Breakdown Voltage HOA1406-001 HOA1406-003	V _(BR) CEO	30 15			٧	Ic=100 μA
Emitter-Collector Breakdown Voltage	V _{(BR)ECO}	5.0			V	I _E =100 μA
Collector Dark Current HOA 1406-001 HOA1406-003	ICEO			100 250	nA	V _{CE} =10 V, I _F =0
COUPLED CHARACTERISTICS On-State Collector Current HOA1406-001 HOA1406-003	Ic(on)	25 2.0			μΑ mA	VcE=5 V I _F =40 mA
Crosstalk (2)	lcx			2.0	μΑ	V _{CE} =5 V, I _F =40 mA
Collector-Emitter Saturation Voltage HOA1406-001 HOA1406-003	VCE(SAT)			0.4 1.1	V	I _F =40 mA ⁽¹⁾ I _C =10 µA I _C =1 mA
Rise And Fall Time HOA1406-001 HOA1406-003	t _r , t _f		15 75		μs	V_{CC} =5 V, I_{C} =1 mA R_{L} =1000 Ω R_{L} =100 Ω

ABSOLUTE MAXIMUM RATINGS


(25°C Free-Air Temperature unless otherwise noted) Operating Temperature Range -40°C to 100°C Storage Temperature Range -40°C to 100°C

IR EMITTER

80 mW (1) Power Dissipation Reverse Voltage 3 V Continuous Forward Current 50 mA

DARLINGTON **DETECTOR** TRANS.

Collector-Emitter Voltage 30 V 15 V 5 V Emitter-Collector Voltage 5 V Power Dissipation 75 mW (2) 75 mW (2) Collector DC Current 30 mA 30 mA




Honeywell reserves the right to make changes in order to improve design and supply the best products possible. Honeywell

Notes
1. Test surface is a Eastman Kodak neutral white card with 90% diffuse reflectance located 0.20 in. (5.0 mm) from the front surface of the device.


2. Crosstalk (lcx) is the collector current measured with current to emitter and no reflecting surface.


Reflective Sensor


IRED Forward Bias Characteristics




Non-Saturated Switching Time vs Load Resistance gra_079.ds4 1000 ≡ı≡⊞ Response time - µs 100 Photodarlington = | | Phototransistor ŦI#I# 10 100 1000 10000 Load resistance - Ohms









All Performance Curves Show Typical Values

Honeywell

Honeywell reserves the right to make changes in order to improve design and supply the best products possible.

Reflective Sensor

