imall

Chipsmall Limited consists of a professional team with an average of over 10 year of expertise in the distribution of electronic components. Based in Hongkong, we have already established firm and mutual-benefit business relationships with customers from, Europe, America and south Asia, supplying obsolete and hard-to-find components to meet their specific needs.

With the principle of "Quality Parts, Customers Priority, Honest Operation, and Considerate Service", our business mainly focus on the distribution of electronic components. Line cards we deal with include Microchip, ALPS, ROHM, Xilinx, Pulse, ON, Everlight and Freescale. Main products comprise IC, Modules, Potentiometer, IC Socket, Relay, Connector. Our parts cover such applications as commercial, industrial, and automotives areas.

We are looking forward to setting up business relationship with you and hope to provide you with the best service and solution. Let us make a better world for our industry!



Contact us

Tel: +86-755-8981 8866 Fax: +86-755-8427 6832 Email & Skype: info@chipsmall.com Web: www.chipsmall.com Address: A1208, Overseas Decoration Building, #122 Zhenhua RD., Futian, Shenzhen, China





DESCRIPTION

The ICPL3120 consists of an Infrared Light Emitting Diode optically coupled to an Integrated Circuit with a Power Driving Output. ICPL3120 is ideally suitable to drive the Power IGBT and MOSFET in Inverters of Motor Controls and in Power Supplies.

The 2.5A peak output current is capable to direct drive IGBT/MOSFET up to ratings of 1200V/100A. For IGBTs with higher ratings, ICPL3120 can be used to drive a discrete power stage which drives the IGBT gate.

FEATURES


- ±2.5A Maximum Peak Output Current
- 35kV/µs Minimum Common Mode Rejection at V_{CM} 1500V
- Maximum Propagation Delay 500ns
- Maximum Propagation Delay Difference 100ns
- Wide Operating Voltage Range V_{CC} 15 to 30 V
- Maximum Supply Current I_{CC} 3.5mA
- Under Voltage Lock Out (UVLO) Protection with Hysteresis
- Guaranteed Performance over Temperature Range - 40°C to +105°C
- MSL 1
- Lead Free and RoHS Compliant
- Safety Approvals Pending

APPLICATIONS

- IGBT/MOSFET Gate Drive
- UPS
- Inverters
- AC Brushless and DC Motor Drives

ORDER INFORMATION

- Add G after PN for 10mm lead spacing
- Add SM after PN for Surface Mount
- Add SMT&R after PN for Surface Mount Tape & Reel



A 0.1µF bypass Capacitor must be connected between Pins 8 and 5.

ABSOLUTE MAXIMUM RATINGS (T_A = 25°C)

Stresses exceeding the absolute maximum ratings can cause permanent damage to the device.

Exposure to absolute maximum ratings for long periods of time can adversely affect reliability.

Input

Forward Current	20mA
Forward Peak Current (Pulse Width ≤ 1µs, 300pps)	1A
Forward Current Rise / Fall Time	500ns
Reverse Voltage	5V
Power dissipation	45mW
Output	
Peak Output Current (Exponential waveform, Pulse Width ≤ 0.3µs, f ≤ = 15kHz)	±2.5A
Operating Frequency (Exponential waveform, I _{O(Peak)} ≤ I2.5AI, Pulse Width ≤ 0.3µs)	50kHz
Supply Voltage ($V_{CC} - V_{EE}$)	0V to 35V
Output Voltage	$0V$ to V_{CC}
Power Dissipation	250mW
Total Package	
Isolation Voltage	$5000V_{RMS}$
Total Power Dissipation	295mW
Operating Temperature	-40 to 105 °C
Storage Temperature	-55 to 125 °C
Junction Temperature	125 °C Max
Lead Soldering Temperature (10s)	260°C

ISOCOM COMPONENTS 2004 LTD

Unit 25B, Park View Road West, Park View Industrial Estate Hartlepool, Cleveland, TS25 1PE, United Kingdom Tel : +44 (0)1429 863 609 Fax : +44 (0)1429 863 581 e-mail : sales@isocom.co.uk http://www.isocom.com

ISOCOM COMPONENTS ASIA LTD

Hong Kong Office, Block A, 8/F, Wah Hing Industrial mansion, 36 Tai Yau Street, San Po Kong, Kowloon, Hong Kong. Tel : +852 2995 9217 Fax : +852 8161 6292 e-mail : sales@isocom.com.hk



Truth Table

LED	V _{cc} – V _{EE} (Turn ON, +ve going)	V _{cc} − V _{EE} (Turn OFF –ve going)	Vo
OFF	0-30V	0-30V	LOW
ON	0 – 11.0V	0-9.5V	LOW
ON	11.0 - 13.5V	9.5 – 12.0V	TRANSITION
ON	13.5 – 30V	12 - 30V	HIGH

Recommended Operating Conditions

Parameter	Symbol	Min	Max	Unit
Operating Temperature	T _A	- 40	105	°C
Supply Voltage	$V_{CC} - V_{EE}$	15	30	V
Input Current (ON)	I _{F(ON)}	7	16	mA
Input Voltage (OFF)	V _{F(OFF)}	0	0.8	V



ELECTRICAL CHARACTERISTICS (Typical Values at V_{CC} – V_{EE} = 30V and T_A = 25°C, Minimum and Maximum Values at Recommended Operating Conditions, unless otherwise specified)

INPUT

Parameter	Symbol	Test Condition	Min	Тур.	Мах	Unit
Forward Voltage	\mathbf{V}_{F}	$I_F = 10 mA$	1.2	1.37	1.8	V
Forward Voltage Temperature Coefficient	$\Delta V_F / \Delta T$	$I_F = 10 \text{mA}$		-1.237		mV/°C
Reverse Voltage	V_R	$I_R = 10 \mu A$	5			V
Input Threshold Current (Low to High)	$I_{\rm FLH}$	$V_{CC} = 30V$ $V_O > 5V$		1.8	5	mA
Input Threshold Voltage (High to Low)	$\mathrm{V}_{\mathrm{FHL}}$	$V_{CC} = 30V$ $V_{O} < 5V$	0.8			V
Input Capacitance	C _{IN}	$V_F = 0V, f = 1MHz$		33		pF

OUTPUT

Parameter	Symbol	Test Condition	Min	Тур.	Max	Unit
High Level Supply Current	I _{CCH}	$I_F = 10mA$, $V_{CC} = 30V$ $V_O = Open$		2.4	3.5	mA
Low Level Supply Current	I _{CCL}	$I_F = 0mA$, $V_{CC} = 30V$ $V_O = Open$		2.5	3.5	mA
High Level Output Current	I _{OH}	Maximum Pulse Width = $50\mu s$ $V_{\rm O} = V_{\rm CC} - 1.5V$			-1.0	А
		Maximum Pulse Width = $10\mu s$ $V_O = V_{CC} - 4V$			-2.5	
Low Level Output Current	I _{OL}	Maximum Pulse Width = $50\mu s$ $V_O = V_{EE} + 1.5V$	1.0			А
		Maximum Pulse Width = $10\mu s$ $V_O = V_{EE} + 4V$	2.5			
High Level Output Voltage	V _{OH}	$I_F = 10 \text{mA}, I_O = -100 \text{mA}$ V		V _{CC} -0.1		V
Low Level Output Voltage	02 1 , 0			V _{EE} +0.1	V _{EE} +0.25	V
UVLO Threshold	V _{UVLO+}	$V_0 > 5V, I_F = 10mA$	11.0	12.7	13.5	V
	V _{UVLO-}	$V_0 < 5V, I_F = 10mA$	9.5	11.2	12.0	V
UVLO Hysteresis	UVLO _{HYS}			1.5		V



ELECTRICAL CHARACTERISTICS (Typical Values at V_{CC} – V_{EE} = 30V and T_A = 25°C, Minimum and Maximum Values at Recommended Operating Conditions, unless otherwise specified)

SWITCHING

Parameter	Symbol	Test Condition	Min	Тур.	Мах	Unit
Propagation Delay Time to High Output Level	t _{PLH}	$I_F = 7 \text{ to } 16\text{mA},$ $V_{CC} = 15 \text{ to } 30\text{V},$ $V_{CC} = 0\text{V}$	50	130	500	ns
Propagation Delay Time to Low Output Level	t _{PHL}	$V_{EE} = 0V,$ $Rg = 10\Omega,$ Cg = 25nF, $c_{E} = 101 H_{\odot}$	50	130	500	
Pulse Width Distortion $ t_{PHL} - t_{PLH} $ for any given device	PWD	f = 10kHz, Duty Cycle = 50%		5	70	
Propagation Delay Difference (t _{PHL} - t _{PLH}) between any two Devices	PDD		-100		100	
Output Rise Time (10% to 90%)	t _r			35		
Output Fall Time (90% to 10%)	t _f			35		
UVLO Turn On Delay	t _{UVLO ON}	$I_{\rm F} = 10 {\rm mA}, {\rm V}_{\rm O} > 5 {\rm V}$		1.6		μs
UVLO Turn Off Delay	t _{UVLO OFF}	$I_{\rm F} = 10 {\rm mA}, {\rm V}_{\rm O} < 5 {\rm V}$		0.4		μs
Common Mode Transient Immunity at High Output Level	CM _H	$I_F = 10 \text{ to } 16\text{mA},$ $V_{CC} = 30\text{V},$ $V_{CM} = 1500\text{V},$ $T_A = 25^{\circ}\text{C}$	35	50		kV/μs
Common Mode Transient Immunity at Low Output Level	CML	$V_{F} = 0V,$ $V_{CC} = 30V,$ $V_{CM} = 1500V,$ $T_{A} = 25^{\circ}C$	35	50		kV/μs



ELECTRICAL CHARACTERISTICS (Typical Values at V_{CC} – V_{EE} = 30V and T_A = 25°C, Minimum and Maximum Values at Recommended Operating Conditions, unless otherwise specified)

ISOLATION

Parameter	Symbol	Test Condition	Min	Тур.	Max	Unit
Insulation Voltage	V _{ISO}	R.H. = $40\% - 60\%$, T _A = 25° C t = 1 min,	5000			V
Input - Output Resistance	R _{I-O}	$V_{I-O} = 500 VDC$		10 ¹²		Ω
Input - Output Capacitance	C _{I-O}	f=1MHz		0.92		pF


Note :


1. A 0.1uF or bigger bypass capacitor must be connected across pin 8 and pin 5.


ISOCOM COMPONENTS

- 2. PDD is the difference of t_{PHL} and t_{PLH} between any two ICPL3120 under same test conditions.
- 3. Common Mode Transient Immunity in High stage is the maximum tolerable negative dV_{CM}/dt on the trailing edge of the common mode impulse signal, V_{CM} , to assure that the output will remain high ($V_0 > 15V$).
- 4. Common Mode Transient Immunity in Low stage is the maximum tolerable positive dV_{CM}/dt on the leading edge of the common mode impulse signal, V_{CM} , to assure that the output will remain low ($V_0 < 1V$).
















Fig 4 Output Low Voltage vs Ambient Temperature

















Fig 10 Propagation Delay vs Supply Voltage










ORDER INFORMATION

ICPL3120						
After PN	PN	Description	Packing quantity			
None	ICPL3120	Standard DIP8	50 pcs per tube			
G	ICPL3120G	10mm Lead Spacing	50 pcs per tube			
SM	ICPL3120SM	Surface Mount	50 pcs per tube			
SMT&R	ICPL3120SMT&R	Surface Mount Tape & Reel	1000 pcs per reel			


DEVICE MARKING





- ICPL3120 denotes Device Part Number
- I denotes Isocom
- Y denotes 1 digit Year code
- WW denotes 2 digit Week code



PACKAGE DIMENSIONS in mm (inch)









DISCLAIMER

Isocom Components is continually working to improve the quality and reliability of its products. Nevertheless, semiconductor devices in general can malfunction or fail due to their inherent electrical sensitivity and vulnerability to physical stress. It is the responsibility of the buyer, when utilizing Isocom Components products, to comply with the standards of safety in making a safe design for the entire system, and to avoid situations in which a malfunction or failure of such Isocom Components products could cause loss of human life, bodily injury or damage to property.

In developing your designs, please ensure that Isocom Components products are used within specified operating ranges as set forth in the most recent Isocom Components products specifications.

The Isocom Components products listed in this document are intended for usage in general electronics applications (computer, personal equipment, office equipment, measuring equipment, industrial robotics, domestic appliances, etc.). These Isocom Components products are neither intended nor warranted for usage in equipment that requires extraordinarily high quality and/or reliability or a malfunction or failure of which may cause loss of human life or bodily injury ("Unintended Usage"). Unintended Usage include atomic energy control instruments, airplane or spaceship instruments, transportation Instruments, traffic signal instruments, combustion control instruments, medical Instruments, all types of safety devices, etc... Unintended Usage of Isocom Components products listed in this document shall be made at the customer's own risk.

Gallium arsenide (GaAs) is a substance used in the products described in this document. GaAs dust and fumes are toxic. Do not break, cut or pulverize the product, or use chemicals to dissolve them. When disposing of the products, follow the appropriate regulations. Do not dispose of the products with other industrial waste or with domestic garbage.

The products described in this document are subject to the foreign exchange and foreign trade laws.

The information contained herein is presented only as a guide for the applications of our products. No responsibility is assumed by Isocom Components for any infringements of intellectual property or other rights of the third parties which may result from its use. No license is granted by implication or otherwise under any intellectual property or other rights of Isocom Components or others.

The information contained herein is subject to change without notice.