

Chipsmall Limited consists of a professional team with an average of over 10 year of expertise in the distribution of electronic components. Based in Hongkong, we have already established firm and mutual-benefit business relationships with customers from, Europe, America and south Asia, supplying obsolete and hard-to-find components to meet their specific needs.

With the principle of "Quality Parts, Customers Priority, Honest Operation, and Considerate Service", our business mainly focus on the distribution of electronic components. Line cards we deal with include Microchip, ALPS, ROHM, Xilinx, Pulse, ON, Everlight and Freescale. Main products comprise IC, Modules, Potentiometer, IC Socket, Relay, Connector. Our parts cover such applications as commercial, industrial, and automotives areas.

We are looking forward to setting up business relationship with you and hope to provide you with the best service and solution. Let us make a better world for our industry!



Contact us

Tel: +86-755-8981 8866 Fax: +86-755-8427 6832

Email & Skype: info@chipsmall.com Web: www.chipsmall.com

Address: A1208, Overseas Decoration Building, #122 Zhenhua RD., Futian, Shenzhen, China











Hall Effect Current Sensors L31S***S05FS Series

Features:

- Open Loop type
- · Panel mounting
- Unipolar power supply
- Ferrite core
- Sulfur tolerant sensors (Resistors:Gold internal Electrodes)
- Insulated plastic case according to UL94V0
- UL Recognition

Advantage:


- Excellent accuracy and linearity
- · Wide nominal current range
- Low temperature drift
- Wide frequency bandwidth
- No insertion loss
- High Immunity To External Interference
- Optimised response time
- Current overload capability


 $T_A=25^{\circ}C, V_{CC}=+5V, R_1=10k\Omega$

Parameters	Symbol	L31S050S05FS	L31S100S05FS	L31S200S05FS	L31S300S05FS	L31S400S05FS	L31S500S05FS	L31S600S05FS	
Primary nominal current	I _f	50A	100A	200A	300A	400A	500A	600A	
Saturation current	I _{fmax}	≥ ±150A	≥ ±300A	≥ ±600A	≥ ±900A	≥ ±900A	≥ ±900A	≥ ±900A	
Rated output voltage	V _o	Vof+0.625V ± 0.015V (at If)							
Offset voltage ¹	V _{of}	V _{REF} ± 0.025V (at If = 0A)							
Reference voltage	V _{REF}	2.5V ± 0.020V							
Output Linearity ² (0A, 0.5l _f , l _f)	٤٤	≤ ± 0.5% (at If)							
Power supply voltage	V _{cc}	+ 5V ±5 %							
Consumption current	lcc	≤ 15mA							
Response time ³	t _r	≤ 5µs (at di/dt = 100A / µs)							
Thermal drift of gain⁴	TcVo	≤ ± 1.5mV/°C							
Thermal drift of offset	TcVof	≤ ± 1.0 mV/°C (at If = 0A)				≤ ± 0.3 mV/°C (at If = 0A)			
Thermal drift of reference	TcVref	≤ ± 0.012% / °C							
Hysteresis error (at If=0A→If→0A)	V _{OH}	≤ 10mV				≤ 2.5mV			
Insulation voltage	V _d	AC3300V for 1minute (sensing current 0.5mA), inside of through hole ⇔ terminal							
Insulation resistance	R _{IS}	≥ 500MΩ (at DC500V) , inside of through hole ⇔ terminal							
Ambient operation temperature	T _A	-40°C~+85°C							
Ambient storage temperature	Ts	-40°C~+85°C							

¹ After removal of core hysteresis— ² Without offset — ³ Time between 10% input current full scale and 90% of sensor output full scale — ⁴ Without Thermal drift of offset

Electrical Performances















Hall Effect Current Sensors L31S***S05FS Series

Mechanical dimensions in mm



Electrical connection diagram



UL Standard

UL 508 , CSA C22.2 No.14 (UL FILE No.E243511)

- For use in Pollution Degree 2 Environment.
- Maximum Surrounding air temperature rating, 85°C.

Package & Weight Information

Weight	Pcs/box	Pcs/carton	Pcs/pallet
37g	20	200	3600





