

Chipsmall Limited consists of a professional team with an average of over 10 year of expertise in the distribution of electronic components. Based in Hongkong, we have already established firm and mutual-benefit business relationships with customers from, Europe, America and south Asia, supplying obsolete and hard-to-find components to meet their specific needs.

With the principle of "Quality Parts, Customers Priority, Honest Operation, and Considerate Service", our business mainly focus on the distribution of electronic components. Line cards we deal with include Microchip, ALPS, ROHM, Xilinx, Pulse, ON, Everlight and Freescale. Main products comprise IC, Modules, Potentiometer, IC Socket, Relay, Connector. Our parts cover such applications as commercial, industrial, and automotives areas.

We are looking forward to setting up business relationship with you and hope to provide you with the best service and solution. Let us make a better world for our industry!



# Contact us

Tel: +86-755-8981 8866 Fax: +86-755-8427 6832

Email & Skype: info@chipsmall.com Web: www.chipsmall.com

Address: A1208, Overseas Decoration Building, #122 Zhenhua RD., Futian, Shenzhen, China







# LV5609V

# Bi-CMOS LSI Vertical Clock Driver for CCD



http://onsemi.com

#### **Overview**

The LV5609V is vertical clock driver for CCD.

#### **Functions**

- Ternary output ×2ch
- Binary output ×2ch
- SHT output ×1ch
- Output ON resistance :  $30\Omega$  typ

#### **Specifications**

Absolute Maximum Ratings at Ta = 25°C,  $V_{SS} = VM = 0V$ 

Parameter	Symbol	Conditions	Ratings	Unit
Maximum supply voltage	V <sub>DD</sub> max		6	V
	VH max		20	V
	VL max		-10	V
	VH-VL max		24	V
Allowable power dissipation	Pd max	with specified substrate *	0.67	W
Operating temperature	Topr		-20 to +80	°C
Storage temperature	Tstg		-40 to +125	°C

 $<sup>^{\</sup>star}$  : Specified substrate : 114.3×76.1×1.6mm³, glass epoxy board

Stresses exceeding Maximum Ratings may damage the device. Maximum Ratings are stress ratings only. Functional operation above the Recommended Operating Conditions is not implied. Extended exposure to stresses above the Recommended Operating Conditions may affect device reliability.

#### Allowable Operating Ratings at $Ta = 25^{\circ}C$ , $V_{SS} = VM = 0V$

Parameter	Completed	O and this are	Ratings			11.5
	Symbol	Conditions	Conditions min	typ	max	Unit
Supply voltage	$V_{DD}$		2.0	3.3	5.5	V
	VH			15	17	V
	VL		-8.5	-7.5	-4	V
	VH-VL				23.5	V
CMOS input High voltage	V <sub>IN</sub> H		0.8V <sub>DD</sub>		$V_{DD}$	V
CMOS input Low voltage	V <sub>IN</sub> L		-0.1		0.4	V

#### LV5609V


## $\textbf{Electrical Characteristics} \ at \ Ta=25^{\circ}C, \ V_{DD}=3.3V, \ V_{SS}=0V, \ VH=15V, \ VL=-7.5V, \ VM=0V, \ VM=15V, \ VL=-7.5V, \ VM=0V, \ VM=15V, \ VM=$

Unless otherwise specified

Devemeter	Cumbal	Conditions		Ratings			
Parameter	Symbol	Conditions	min	typ	max	Unit	
Static current drain	I <sub>DD</sub>	V <sub>DD</sub> pin			1	μΑ	
	IH	VH pin			10	μΑ	
	IL	VL pin			1	μΑ	
Dynamic current drain	I <sub>DD</sub>	V <sub>DD</sub> pin See *1 and *2.			1	mA	
	IH	VH pin See *1 and *2.		2.4	4.5	mA	
	IL	VL pin See *1 and *2.		3	5	mA	
Output ON resistance	RL	I <sub>O</sub> = +10mA		20	30	Ω	
	RM	$I_O = \pm 10 \text{mA}$		30	45	Ω	
	RH	I <sub>O</sub> = -10mA		30	40	Ω	
	RSHT	I <sub>O</sub> = -10mA		30	40	Ω	
Propagation delay time	TPLM	No load			200	ns	
	TPMH	No load			200	ns	
	TPLH	No load			200	ns	
	TPML	No load			200	ns	
	TPHM	No load			200	ns	
	TPHL	No load			200	ns	
Rise time	TTLM	VL → VM V1, V3 See *1.			800	ns	
		VL → VM V2, V4 See *1.			800	ns	
	TTMH	VM → VL V1, V3 See *1.			800	ns	
	TTLH	VL → VH SHT See *1.			200	ns	
Fall time	TTML	VM → VL V1, V3 See *1.			800	ns	
		VM → VL V2, V4 See *1.			800	ns	
	TTHM	VH → VM V1, V3 See *1.			800	ns	
	TTHL	VH → VL SHT See *1.			200	ns	


<sup>\*1 :</sup> Refer to the CCD equivalent load shown below.


 $<sup>\</sup>ensuremath{^{\star}2}$  : Refer to the timing waveform on Page 7.




#### **Package Dimensions**

unit: mm (typ) 3179C






### **Pin Assignment**



#### **Pin Function**

Pin No.	Name	Mode
1	V3	Level shift output (ternary VH, VM, VL)
2	V2	Level shift output (binary VM, VL)
3	V1	Level shift output (ternary VH, VM, VL)
4	VM	GND for output
5	NC	
6	VH	Hi power supply (15V system) for output
7	XV1	V1 transfer pulse input
8	XSG1	V1 read pulse input
9	XV2	V2 transfer pulse input
10	XV3	V3 transfer pulse input
11	XSG3	V3 read pulse input
12	XV4	V4 transfer pulse input
13	NC1	
14	XSHT	SHT pulse input
15	$v_{DD}$	Power supply (3.3V system) for input buffer
16	V <sub>SS</sub>	GND for input buffer
17	VL	LO power supply (-7.5V system) for output
18	NC	
19	SHT	Level shift output (binary VH, VL)
20	V4	Level shift output (ternary VM, VL)


### **Block Diagram**




#### **Logical Function Table**

Input					Output			
XV1 XV3	XSG1 XSG3	XV2 XV4	XSHT	V1 V3	V2 V4	SHT		
L	L	Х	Х	VH	Х	Х		
L	Н	Х	Х	VM	X	Х		
Н	L	Х	Х	VL	Х	Х		
Н	Н	Х	Х	VL	X	Х		
Х	Х	L	X	X	VM	X		
Х	Х	Н	X	X	VL	X		
Х	Х	Х	L	Х	X	VH		
Х	Х	Х	Н	Х	Х	VL		


#### **Timing Chart**



#### **CCD Equivalent Load Measurement Timing Waveform**



#### **Enlarged View of overlapped portion**



ON Semiconductor and the ON logo are registered trademarks of Semiconductor Components Industries, LLC (SCILLC). SCILLC owns the rights to a number of patents, trademarks, copyrights, trade secrets, and other intellectual property. A listing of SCILLC's product/patent coverage may be accessed at www.onsemi.com/site/pdf/Patent-Marking.pdf. SCILLC reserves the right to make changes without further notice to any products herein. SCILLC makes no warranty, representation or guarantee regarding the suitability of its products for any particular purpose, nor does SCILLC assume any liability arising out of the application or use of any product or circuit, and specifically disclaims any and all liability, including without limitation special, consequential or incidental damages. "Typical" parameters which may be provided in SCILLC data sheets and/or specifications can and do vary in different applications and actual performance may vary over time. All operating parameters, including "Typicals" must be validated for each customer application by customer's technical experts. SCILLC does not convey any license under its patent rights nor the rights of others. SCILLC products are not designed, intended, or authorized for use as components in systems intended for surgical implant into the body, or other applications intended to support or sustain life, or for any other application in which the failure of the SCILLC product could create a situation where personal injury or death may occur. Should Buyer purchase or use SCILLC products for any such unintended or unauthorized application, Buyer shall indemnify and hold SCILLC and its officers, employees, subsidiaries, affiliates, and distributors harmless against all claims, costs, damages, and expenses, and reasonable attorney fees arising out of, directly or indirectly, any claim of personal injury or death associated with such unintended or unauthorized use, even if such claim alleges that SCILLC was negligent regarding the design or manufacture of the part. SCILLC is an Equa