

Chipsmall Limited consists of a professional team with an average of over 10 year of expertise in the distribution of electronic components. Based in Hongkong, we have already established firm and mutual-benefit business relationships with customers from, Europe, America and south Asia, supplying obsolete and hard-to-find components to meet their specific needs.

With the principle of "Quality Parts, Customers Priority, Honest Operation, and Considerate Service", our business mainly focus on the distribution of electronic components. Line cards we deal with include Microchip, ALPS, ROHM, Xilinx, Pulse, ON, Everlight and Freescale. Main products comprise IC, Modules, Potentiometer, IC Socket, Relay, Connector. Our parts cover such applications as commercial, industrial, and automotives areas.

We are looking forward to setting up business relationship with you and hope to provide you with the best service and solution. Let us make a better world for our industry!



Contact us

Tel: +86-755-8981 8866 Fax: +86-755-8427 6832

Email & Skype: info@chipsmall.com Web: www.chipsmall.com

Address: A1208, Overseas Decoration Building, #122 Zhenhua RD., Futian, Shenzhen, China









MA610 600A Clamp Meter + NCV



The MA610 is a fully loaded clamp meter with multimeter functions including AC Current, AC/DC Voltage, Resistance, Frequency, and Capacitance. It also has a built-in non-contact voltage (NCV) detector to quickly check circuits and wires for live voltages.



Features

- Pocket-sized meter with 1.2" (30mm) jaw size fits conductors up to 500MCM
- Built-in Non-Contact Voltage (NCV) detector
- MultiMeter functions include Resistance, Capacitance and Frequency
- Relative Mode for Capacitance
- · Data Hold freezes reading on display
- · Auto Power Off with disable and Low Battery indication

- · Large backlit LCD display
- Complete with test leads, three AAA batteries, and pouch

Range	Max Resolution	Basic Accuracy	
600.0A	1mA	±2.0%	
600V	0.1mV	±0.8%	
600V	1mV	±1.2%	
100 to 600V			
40ΜΩ	0.1Ω		
100μF	0.01nF		
1MHz	0.01Hz		
Yes			
9x3x1.6" (228x77x41mm)/ 9.3oz (265g)			
	600.0A 600V 600V 100 to 600V 40MΩ 100μF 1MHz Yes	600.0A 1mA 600V 0.1mV 600V 1mV 100 to 600V 40MΩ 0.1Ω 100μF 0.01nF 1MHz 0.01Hz Yes	600.0A 1mA ±2.0% 600V 0.1mV ±0.8% 600V 1mV ±1.2% 100 to 600V 40MΩ 0.1Ω 100μF 0.01nF 1MHz 0.01Hz Yes

Ordering

MA610 N 600A AC Clamp Meter

N Indicates products that are available with optional calibration traceable to NIST. Order with -NIST after part number.

