



Chipsmall Limited consists of a professional team with an average of over 10 year of expertise in the distribution of electronic components. Based in Hongkong, we have already established firm and mutual-benefit business relationships with customers from,Europe,America and south Asia,supplying obsolete and hard-to-find components to meet their specific needs.

With the principle of "Quality Parts,Customers Priority,Honest Operation,and Considerate Service",our business mainly focus on the distribution of electronic components. Line cards we deal with include Microchip,ALPS,ROHM,Xilinx,Pulse,ON,Everlight and Freescale. Main products comprise IC,Modules,Potentiometer,IC Socket,Relay,Connector.Our parts cover such applications as commercial,industrial, and automotives areas.

We are looking forward to setting up business relationship with you and hope to provide you with the best service and solution. Let us make a better world for our industry!



## Contact us

Tel: +86-755-8981 8866 Fax: +86-755-8427 6832

Email & Skype: info@chipsmall.com Web: www.chipsmall.com

Address: A1208, Overseas Decoration Building, #122 Zhenhua RD., Futian, Shenzhen, China



# MultiMaster™ Series Precision MultiMeters

**50,000 / 500,000 count and high accuracy multimeters**

Full range multimeter functions with high resolution to 0.1µA/0.1mV and CAT IV-600V Safety Rating

## Multimaster Features:

- 0.02% (MM570A) and 0.03% (MM560A) basic DCV accuracy
- 50,000 count (500,000 for DCV and Hz) backlit LCD display with bargraph
- Filtered frequency function with adjustable trigger levels for variable speed motor drives and high voltage applications
- Special True RMS combination AC+DC function for measurements of rectified AC (non-symmetrical) voltage & current waveforms
- AC/DC current to 10A with 0.01µA resolution
- 4 to 20mA, displayed as 0-100% for process current measurements
- Max/Min recording with autoranging
- Capacitance, Frequency, Resistance, Continuity, Duty cycle and Diode tests
- High resolution to 1µV, 0.0001Hz, 0.01Ω, 0.01µA and 0.1°
- dBm measurements with 20 selectable impedances
- Features include Auto Power off, Relative & Hold
- Peak function captures transient pulses

- On power-up, meter defaults to last set function
- Audible and visible test lead misconnection warning
- Optional Windows<sup>®</sup> 95/98/NT/2000/ME/XP compatible PC communication software and optically isolated cable
- Complete with test leads, Type K thermocouple probe (-22 to 572°F/ -30 to 300°C)(MM570A), protective holster with stand and 9V battery

### Additional Features Model MM560A:

- Up to 20kHz True RMS ACV bandwidth
- 600V input protection on all functions (1000V on Voltage)

### Additional Features Model MM570A:

- Up to 100kHz True RMS ACV bandwidth
- 1000V input protection on all functions
- T1, T2 and T1-T2 dual Type K input temperature display in °F or °C



Model MM560A

Model MM570A



Optional Windows<sup>®</sup> 95/98/NT/2000/ME/XP compatible PC communication software and optically isolated cable for data collection.



All models include Double injection molded CAT IV - 600V Test Leads for safety, better grip and added durability.

Specifications	Range	Max. Resolution	Basic Accuracy (%rdg+digit)
DC Voltage	500mV, 5V, 50V, 500V, 1000V	0.01mV	±(0.02% + 2d) MM570A ±(0.03% + 2d) MM560A
AC Voltage	500mV, 5V, 50V, 500V, 1000V	0.01mV	±(0.4% + 40d) MM570A ±(0.8% + 60d) MM560A
DC Current	500µA, 5000µA, 50mA, 500mA, 5A, 10A	0.01µA	±(0.1% + 20d)
AC Current	500µA, 5000µA, 50mA, 500mA, 5A, 10A	0.01µA	±(0.7% + 50d) MM570A ±(1% + 40d) MM560A
Resistance (Ω)	500, 5k, 50k, 500k, 5M, 50M	0.01Ω	±(0.07% + 2d) MM570A ±(0.1% + 6d) MM560A
Capacitance	50nF to 9999µF	0.01nF	±(0.8% + 3d)
Line Frequency	5Hz to 200kHz	0.0001Hz	±(0.002% + 4d)
Logic Frequency	5Hz to 2MHz	0.0001Hz	±(0.002% + 4d)
Temperature (MM570A)	-58 to 1832°F (-50 to 1000°C)	0.1°	±(0.3% + 1°C/2°F)
Duty Cycle	0.1% to 99.99%	0.01%	±(3d/kHz + 2d)
Dimensions/ Wt	7.32 x 3.42 x 1.39" (186 x 87 x 35.5mm) / 0.75lb (340g)		

## Ordering Information:

- MM560A .....MultiMaster™ Precision MultiMeter
- MM560A-NIST ..MultiMaster™ MM560A with Calibration Traceable to NIST.
- MM570A .....MultiMaster™ Precision MultiMeter with Temperature
- MM570A-NIST ..MultiMaster™ MM570A & Temperature with Calibration Traceable to NIST
- SW810A .....Software CD and Serial Cable
- TL805 .....Spare set of CAT IV - 600V Test Leads
- TL807 .....Set of Alligator Clips (2pk) for TL805
- TP873 .....Spare Bead Wire Temperature Probe
- CA899 .....Vinyl Pouch Carrying Case

