

Chipsmall Limited consists of a professional team with an average of over 10 year of expertise in the distribution of electronic components. Based in Hongkong, we have already established firm and mutual-benefit business relationships with customers from, Europe, America and south Asia, supplying obsolete and hard-to-find components to meet their specific needs.

With the principle of "Quality Parts, Customers Priority, Honest Operation, and Considerate Service", our business mainly focus on the distribution of electronic components. Line cards we deal with include Microchip, ALPS, ROHM, Xilinx, Pulse, ON, Everlight and Freescale. Main products comprise IC, Modules, Potentiometer, IC Socket, Relay, Connector. Our parts cover such applications as commercial, industrial, and automotives areas.

We are looking forward to setting up business relationship with you and hope to provide you with the best service and solution. Let us make a better world for our industry!



# Contact us

Tel: +86-755-8981 8866 Fax: +86-755-8427 6832

Email & Skype: info@chipsmall.com Web: www.chipsmall.com

Address: A1208, Overseas Decoration Building, #122 Zhenhua RD., Futian, Shenzhen, China









# Is Now Part of



# ON Semiconductor®

To learn more about ON Semiconductor, please visit our website at <a href="https://www.onsemi.com">www.onsemi.com</a>

ON Semiconductor and the ON Semiconductor logo are trademarks of Semiconductor Components Industries, LLC dba ON Semiconductor or its subsidiaries in the United States and/or other countries. ON Semiconductor owns the rights to a number of patents, trademarks, copyrights, trade secrets, and other intellectual property. A listing of ON Semiconductor's product/patent coverage may be accessed at www.onsemi.com/site/pdf/Patent-Marking.pdf. ON Semiconductor reserves the right to make changes without further notice to any products herein. ON Semiconductor makes no warranty, representation or guarantee regarding the suitability of its products for any particular purpose, nor does ON Semiconductor assume any liability arising out of the application or use of any product or circuit, and specifically disclaims any and all liability, including without limitation special, consequential or incidental damages. Buyer is responsible for its products and applications using ON Semiconductor products, including compliance with all laws, regulations and safety requirements or standards, regardless of any support or applications information provided by ON Semiconductor. "Typical" parameters which may be provided in ON Semiconductor data sheets and/or specifications can and do vary in different applications and actual performance may vary over time. All operating parameters, including "Typicals" must be validated for each customer application by customer's technical experts. ON Semiconductor does not convey any license under its patent rights nor the rights of others. ON Semiconductor products are not designed, intended, or authorized for use as a critical component in life support systems or any EDA Class 3 medical devices with a same or similar classification in a foreign jurisdiction or any devices intended for implantation in the human body. Should Buyer purchase or use ON Semiconductor products for any such unintended or unauthorized application, Buyer shall indemnify and hold ON Semiconductor and its officers, employees, emplo



September 1983 Revised May 2005

# MM74HC373 3-STATE Octal D-Type Latch

# **General Description**

The MM74HC373 high speed octal D-type latches utilize advanced silicon-gate CMOS technology. They possess the high noise immunity and low power consumption of standard CMOS integrated circuits, as well as the ability to drive 15 LS-TTL loads. Due to the large output drive capability and the 3-STATE feature, these devices are ideally suited for interfacing with bus lines in a bus organized sys-

When the LATCH ENABLE input is HIGH, the Q outputs will follow the D inputs. When the LATCH ENABLE goes LOW, data at the D inputs will be retained at the outputs until LATCH ENABLE returns HIGH again. When a high logic level is applied to the OUTPUT CONTROL input, all outputs go to a high impedance state, regardless of what signals are present at the other inputs and the state of the storage elements.

The 74HC logic family is speed, function, and pin-out compatible with the standard 74LS logic family. All inputs are protected from damage due to static discharge by internal diode clamps to V<sub>CC</sub> and ground.

#### **Features**

- Typical propagation delay: 18 ns
- Wide operating voltage range: 2 to 6 volts
- Low input current: 1 µA maximum
- Low quiescent current: 80 µA maximum (74 Series)
- Output drive capability: 15 LS-TTL loads


# **Ordering Code:**

Order Number	Package Number	Package Description
MM74HC373WM	M20B	20-Lead Small Outline Integrated Circuit (SOIC), JEDEC MS-013, 0.300" Wide
MM74HC373SJ	M20D	20-Lead Small Outline Package (SOP), EIAJ TYPE II, 5.3mm Wide
MM74HC373MTC	MTC20	20-Lead Thin Shrink Small Outline Package (TSSOP), JEDEC MO-153, 4.4mm Wide
MM74HC373N	N20A	20-Lead Plastic Dual-In-Line Package (PDIP), JEDEC MS-001, 0.300" Wide

Devices also available in Tape and Reel. Specify by appending the suffix letter "X" to the ordering code.

#### **Connection Diagram**

#### Pin Assignments for DIP, SOIC, SOP and TSSOP



## **Truth Table**

Output	Latch	Data	373
Control	Enable		Output
L	Н	Н	Н
L	Н	L	L
L	L	X	$Q_0$
Н	X	X	Z

- $\mathbf{Q}_0 = \mathbf{Level}$  of output before steady-state input conditions were established.  $\mathbf{Z} = \mathbf{High}$  Impedance

# Absolute Maximum Ratings(Note 1)

(Note 2)

Supply Voltage (V <sub>CC</sub> )	-0.5 to +7.0V
DC Input Voltage (V <sub>IN</sub> )	-1.5 to V <sub>CC</sub> +1.5V
DC Output Voltage (V <sub>OUT</sub> )	$-0.5$ to $V_{CC} + 0.5V$
Clamp Diode Current (I <sub>IK</sub> , I <sub>OK</sub> )	±20 mA
DC Output Current, per pin (I <sub>OUT</sub> )	±35 mA
DC $V_{CC}$ or GND Current, per pin ( $I_{CC}$ )	±70 mA
Storage Temperature Range (T <sub>STG</sub> )	-65°C to +150°C
Power Dissipation (P <sub>D</sub> )	
(Note 3)	600 mW
S.O. Package only	500 mW
Lead Temperature (T <sub>L</sub> )	
(Soldering 10 seconds)	260°C

# **Recommended Operating Conditions**

	Min	Max	Units
Supply Voltage (V <sub>CC</sub> )	2	6	V
DC Input or Output Voltage			
$(V_{IN}, V_{OUT})$	0	$V_{CC}$	V
Operating Temperature Range (T <sub>A</sub> )	-40	+85	°C
Input Rise or Fall Times			
$(t_r, t_f) V_{CC} = 2.0V$		1000	ns
V <sub>CC</sub> = 4.5V		500	ns
$V_{CC} = 6.0V$		400	ns

Note 1: Absolute Maximum Ratings are those values beyond which damage to the device may occur.

Note 2: Unless otherwise specified all voltages are referenced to ground.

Note 3: Power Dissipation temperature derating — plastic "N" package: –
12 mW/°C from 65°C to 85°C.

# **DC Electrical Characteristics**

Symbol	Parameter	Conditions	v <sub>cc</sub>	T <sub>A</sub> = 25°C		T <sub>A</sub> = -40 to 85°C	T <sub>A</sub> = -55 to 125°C	Units
Syllibol		Conditions	*CC	Тур	Guaranteed Limits		imits	Units
V <sub>IH</sub>	Minimum HIGH Level		2.0V		1.5	1.5	1.5	٧
	Input Voltage		4.5V		3.15	3.15	3.15	٧
			6.0V		4.2	4.2	4.2	V
V <sub>IL</sub>	Maximum LOW Level		2.0V		0.5	0.5	0.5	٧
	Input Voltage		4.5V		1.35	1.35	1.35	٧
			6.0V		1.8	1.8	1.8	V
V <sub>OH</sub>	Minimum HIGH Level	$V_{IN} = V_{IH}$ or $V_{IL}$						
	Output Voltage	$ I_{OUT}  \leq 20~\mu A$	2.0V	2.0	1.9	1.9	1.9	V
			4.5V	4.5	4.4	4.4	4.4	٧
			6.0V	6.0	5.9	5.9	5.9	V
		$V_{IN} = V_{IH}$ or $V_{IL}$						
		$ I_{OUT}  \le 6.0 \text{ mA}$	4.5V	4.2	3.98	3.84	3.7	٧
		$ I_{OUT}  \le 7.8 \text{ mA}$	6.0V	5.7	5.48	5.34	5.2	V
V <sub>OL</sub>	Maximum LOW Level	$V_{IN} = V_{IH}$ or $V_{IL}$						
	Output Voltage	$ I_{OUT}  \le 20 \ \mu A$	2.0V	0	0.1	0.1	0.1	٧
			4.5V	0	0.1	0.1	0.1	V
			6.0V	0	0.1	0.1	0.1	V
		$V_{IN} = V_{IH}$ or $V_{IL}$						
		$ I_{OUT}  \le 6.0 \text{ mA}$	4.5V	0.2	0.26	0.33	0.4	V
		$ I_{OUT}  \le 7.8 \text{ mA}$	6.0V	0.2	0.26	0.33	0.4	V
I <sub>IN</sub>	Maximum Input	V <sub>IN</sub> = V <sub>CC</sub> or GND	6.0V		±0.1	±1.0	±1.0	μА
	Current							
loz	Maximum 3-STATE	$V_{IN} = V_{IH}$ or $V_{IL}$ , $OC = V_{IH}$	6.0V		±0.5	±5	±10	μА
	Output Leakage	$V_{OUT} = V_{CC}$ or GND						
	Current							
Icc	Maximum Quiescent	V <sub>IN</sub> = V <sub>CC</sub> or GND	6.0V		8.0	80	160	μА
	Supply Current	$I_{OUT} = 0 \mu A$						

Note 4: For a power supply of 5V  $\pm$ 10% the worst case output voltages ( $V_{OH}$ , and  $V_{OL}$ ) occur for HC at 4.5V. Thus the 4.5V values should be used when designing with this supply. Worst case  $V_{IH}$  and  $V_{IL}$  occur at  $V_{CC} = 5.5V$  and 4.5V respectively. (The  $V_{IH}$  value at 5.5V is 3.85V.) The worst case leakage current ( $I_{IN}$ ,  $I_{CC}$ , and  $I_{OZ}$ ) occur for CMOS at the higher voltage and so the 6.0V values should be used.

# **AC Electrical Characteristics**

 $V_{CC} = 5V, T_A = 25^{\circ}C, t_r = t_f = 6 \text{ ns}$ 

Symbol	Parameter	Conditions	Тур	Guaranteed Limit	Units
t <sub>PHL</sub> , t <sub>PLH</sub>	Maximum Propagation Delay, Data to Q	C <sub>L</sub> = 45 pF	18	25	ns
t <sub>PHL</sub> , t <sub>PLH</sub>	Maximum Propagation Delay, LE to Q	C <sub>L</sub> = 45 pF	21	30	ns
t <sub>PZH</sub> , t <sub>PZL</sub>	Maximum Output Enable Time	$R_L = 1 \text{ k}\Omega$ $C_L = 45 \text{ pF}$	20	28	ns
t <sub>PHZ</sub> , t <sub>PLZ</sub>	Maximum Output Disable Time	$\begin{aligned} R_L &= 1 \ k\Omega \\ C_L &= 5 \ pF \end{aligned}$	18	25	ns
t <sub>S</sub>	Minimum Set Up Time			5	ns
t <sub>H</sub>	Minimum Hold Time			10	ns
t <sub>W</sub>	Minimum Pulse Width		9	16	ns

# **AC Electrical Characteristics**


 $V_{CC} = 2.0-6.0V$ ,  $C_L = 50$  pF,  $t_r = t_f = 6$  ns (unless otherwise specified)


Symbol	Parameter	Conditions	v <sub>cc</sub>	<b>T</b> <sub>A</sub> =	25°C	$T_A = -40 \text{ to } 85^{\circ}\text{C}$ $T_A = -55 \text{ to } 125^{\circ}\text{C}$		Units	
Cymbol	Faiailietei		• 66	Тур		Guaranteed L	imits	Onno	
t <sub>PHL</sub> , t <sub>PLH</sub>	Maximum Propagation	C <sub>L</sub> = 50 pF	2.0V	50	150	188	225	ns	
	Delay, Data to Q	$C_L = 150 \text{ pF}$	2.0V	80	200	250	300	ns	
		$C_L = 50 pF$	4.5V	22	30	37	45	ns	
		$C_L = 150 pF$	4.5V	30	40	50	60	ns	
		$C_L = 50 pF$	6.0V	19	26	31	39	ns	
		$C_L = 150 pF$	6.0V	26	35	44	53	ns	
t <sub>PHL</sub> , t <sub>PLH</sub>	Maximum Propagation	C <sub>L</sub> = 50 pF	2.0V	63	175	220	263	ns	
	Delay, LE to Q	$C_L = 150 pF$	2.0V	110	225	280	338	ns	
		C <sub>L</sub> = 50 pF	4.5V	25	35	44	52	ns	
		C <sub>L</sub> = 150 pF	4.5V	35	45	56	68	ns	
		C <sub>L</sub> = 50 pF	6.0V	21	30	37	45	ns	
		C <sub>L</sub> = 150 pF	6.0V	28	39	49	59	ns	
$t_{PZH}$ , $t_{PZL}$	Maximum Output	$R_L = 1 k\Omega$							
	Enable Time	C <sub>L</sub> = 50 pF	2.0V	50	150	188	225	ns	
		C <sub>L</sub> = 150 pF	2.0V	80	200	250	300	ns	
		C <sub>L</sub> = 50 pF	4.5V	21	30	37	45	ns	
		C <sub>L</sub> = 150 pF	4.5V	30	40	50	60	ns	
		C <sub>L</sub> = 50 pF	6.0V	19	26	31	39	ns	
		C <sub>L</sub> = 150 pF	6.0V	26	35	44	53	ns	
t <sub>PHZ</sub> , t <sub>PLZ</sub>	Maximum Output Disable	$R_L = 1 k\Omega$	2.0V	50	150	188	225	ns	
	Disable Time	C <sub>L</sub> = 50 pF	4.5V	21	30	37	45	ns	
			6.0V	19	26	31	39	ns	
t <sub>S</sub>	Minimum Set Up Time		2.0V		50	60	75	ns	
			4.5V		9	13	15	ns	
			6.0V		9	11	13	ns	
t <sub>H</sub>	Minimum Hold Time		2.0V		5	5	5	ns	
			4.5V		5	5	5	ns	
			6.0V		5	5	5	ns	
t <sub>W</sub>	Minimum Pulse Width		2.0V	30	80	100	120	ns	
			4.5V	10	16	20	24	ns	
			6.0V	9	14	18	20	ns	
t <sub>THL</sub> , t <sub>TLH</sub>	Maximum Output Rise	C <sub>L</sub> = 50 pF	2.0V	25	60	75	90	ns	
	and Fall Time		4.5V	7	12	15	18	ns	
			6.0V	6	10	13	15	ns	
C <sub>PD</sub>	Power Dissipation	(per latch)				İ			
=	Capacitance (Note 5)	OC = V <sub>CC</sub>		30				pF	
		OC = GND		50				pF	
C <sub>IN</sub>	Maximum Input Capacitance			5	10	10	10	pF	

# AC Electrical Characteristics (Continued)


Symbol	Parameter	Conditions	v <sub>cc</sub>	T <sub>A</sub> = 25°C		T <sub>A</sub> = -40 to 85°C	T <sub>A</sub> = -55 to 125°C	Units	
C)	T didilicter			Тур		Guaranteed L	imits	00	
C <sub>OUT</sub>	Maximum Output			15	20	20	20	pF	
	Capacitance								


Note 5:  $C_{PD}$  determines the no load dynamic power consumption,  $P_D = C_{PD} \ V_{CC}^2 \ f + I_{CC} \ V_{CC}$ , and the no load dynamic current consumption,  $I_S = C_{PD} \ V_{CC} \ f + I_{CC}$ .






# Physical Dimensions inches (millimeters) unless otherwise noted (Continued)









SEE DETAIL A

### DIMENSIONS ARE IN MILLIMETERS

#### NOTES:

- A. CONFORMS TO JEDEC REGISTRATION MD-153, VARIATION AC, REF NOTE 6, DATE 7/93.
- B. DIMENSIONS ARE IN MILLIMETERS.
- C. DIMENSIONS ARE EXCLUSIVE OF BURRS, MOLDS FLASH, AND TIE BAR EXTRUSIONS.
- D. DIMENSIONS AND TOLERANCES PER ANSI Y14.5M, 1982.


# R0.09min GAGE PLANE - 8-7 -0.6±0.1-0.09min R0.09min

DETAIL A

# MTC20REVD1

20-Lead Thin Shrink Small Outline Package (TSSOP), JEDEC MO-153, 4.4mm Wide Package Number MTC20

# Physical Dimensions inches (millimeters) unless otherwise noted (Continued)



20-Lead Plastic Dual-In-Line Package (PDIP), JEDEC MS-001, 0.300" Wide Package Number N20A

Fairchild does not assume any responsibility for use of any circuitry described, no circuit patent licenses are implied and Fairchild reserves the right at any time without notice to change said circuitry and specifications.

### LIFE SUPPORT POLICY

FAIRCHILD'S PRODUCTS ARE NOT AUTHORIZED FOR USE AS CRITICAL COMPONENTS IN LIFE SUPPORT DEVICES OR SYSTEMS WITHOUT THE EXPRESS WRITTEN APPROVAL OF THE PRESIDENT OF FAIRCHILD SEMICONDUCTOR CORPORATION. As used herein:

- Life support devices or systems are devices or systems which, (a) are intended for surgical implant into the body, or (b) support or sustain life, and (c) whose failure to perform when properly used in accordance with instructions for use provided in the labeling, can be reasonably expected to result in a significant injury to the user.
- A critical component in any component of a life support device or system whose failure to perform can be reasonably expected to cause the failure of the life support device or system, or to affect its safety or effectiveness.

www.fairchildsemi.com

ON Semiconductor and are trademarks of Semiconductor Components Industries, LLC dba ON Semiconductor or its subsidiaries in the United States and/or other countries. ON Semiconductor owns the rights to a number of patents, trademarks, copyrights, trade secrets, and other intellectual property. A listing of ON Semiconductor's product/patent coverage may be accessed at <a href="https://www.onsemi.com/site/pdf/Patent-Marking.pdf">www.onsemi.com/site/pdf/Patent-Marking.pdf</a>. ON Semiconductor reserves the right to make changes without further notice to any products herein. ON Semiconductor and severally, representation or guarantee regarding the suitability of its products for any particular purpose, nor does ON Semiconductor assume any liability arising out of the application or use of any product or circuit, and specifically disclaims any and all liability, including without limitation special, consequential or incidental damages. Buyer is responsible for its products and applications using ON Semiconductor products, including compliance with all laws, regulations and safety requirements or standards, regardless of any support or applications information provided by ON Semiconductor. "Typical" parameters which may be provided in ON Semiconductor data sheets and/or specifications can and do vary in different applications and actual performance may vary over time. All operating parameters, including "Typicals" must be validated for each customer application by customer's technical experts. ON Semiconductor does not convey any license under its patent rights nor the rights of others. ON Semiconductor products are not designed, intended, or authorized for use as a critical component in life support systems or any FDA Class 3 medical devices or medical devices with a same or similar classification in a foreign jurisdiction or any devices intended for implantation in the human body. Should Buyer purchase or use ON Semiconductor products for any such unintended or unauthorized application, Buyer shall indemnify and ho

## **PUBLICATION ORDERING INFORMATION**

#### LITERATURE FULFILLMENT:

Literature Distribution Center for ON Semiconductor 19521 E. 32nd Pkwy, Aurora, Colorado 80011 USA Phone: 303-675-2175 or 800-344-3860 Toll Free USA/Canada Fax: 303-675-2176 or 800-344-3867 Toll Free USA/Canada Email: orderlit@onsemi.com N. American Technical Support: 800–282–9855 Toll Free USA/Canada
Europe, Middle East and Africa Technical Support:
Phone: 421 33 790 2910
Japan Customer Focus Center
Phone: 81–3–5817–1050

ON Semiconductor Website: www.onsemi.com

Order Literature: http://www.onsemi.com/orderlit

For additional information, please contact your local Sales Representative