imall

Chipsmall Limited consists of a professional team with an average of over 10 year of expertise in the distribution of electronic components. Based in Hongkong, we have already established firm and mutual-benefit business relationships with customers from, Europe, America and south Asia, supplying obsolete and hard-to-find components to meet their specific needs.

With the principle of "Quality Parts, Customers Priority, Honest Operation, and Considerate Service", our business mainly focus on the distribution of electronic components. Line cards we deal with include Microchip, ALPS, ROHM, Xilinx, Pulse, ON, Everlight and Freescale. Main products comprise IC, Modules, Potentiometer, IC Socket, Relay, Connector. Our parts cover such applications as commercial, industrial, and automotives areas.

We are looking forward to setting up business relationship with you and hope to provide you with the best service and solution. Let us make a better world for our industry!



Contact us

Tel: +86-755-8981 8866 Fax: +86-755-8427 6832 Email & Skype: info@chipsmall.com Web: www.chipsmall.com Address: A1208, Overseas Decoration Building, #122 Zhenhua RD., Futian, Shenzhen, China



Ultra-Low 0.35 Ω Dual SPDT Analog Switch

The NLAS5223B is an advanced CMOS analog switch fabricated in Sub–micron silicon gate CMOS technology. The device is a dual Independent Single Pole Double Throw (SPDT) switch featuring Ultra–Low R_{ON} of 0.35 Ω , at V_{CC} = 4.3 V.

The part also features guaranteed Break Before Make (BBM) switching, assuring the switches never short the driver.

Features

- Ultra–Low R_{ON}, 0.35 Ω (typ) at V_{CC} = 4.3 V
- NLAS5223B Interfaces with 2.8 V Chipset
- NLAS5223BL Interfaces with 1.8 V Chipset
- Single Supply Operation from 1.65–4.5 V
- Full 0–V_{CC} Signal Handling Capability
- High Off-Channel Isolation
- Low Standby Current, < 50 nA
- Low Distortion
- R_{ON} Flatness of 0.15 Ω
- High Continuous Current Capability
 ±320 mA Through Each Switch
- Large Current Clamping Diodes at Analog Inputs
 ±100 mA Continuous Current Capability
- Package:
 - 1.4 x 1.8 x 0.75 mm WQFN10 Pb-Free
 - 1.4 x 1.8 x 0.55 mm UQFN10 Pb-Free
- These are Pb–Free Devices

Applications


- Cell Phone Audio Block
- Speaker and Earphone Switching
- Ring–Tone Chip/Amplifier Switching
- Modems



ON Semiconductor®


www.onsemi.com

MARKING DIAGRAM



| | AD = NLAS5223BMNR2G |
|---|-------------------------------|
| | AE = NLAS5223BLMNR2G |
| | AP = NLAS5223BMUR2G |
| М | = Date Code/Assembly Location |
| • | = Pb-Free Device |

(Note: Microdot may be in either location)



FUNCTION TABLE

| IN 1, 2 | NO 1, 2 | NC 1, 2 |
|---------|---------|---------|
| 0 | OFF | ON |
| 1 | ON | OFF |

ORDERING INFORMATION

See detailed ordering and shipping information in the package dimensions section on page 9 of this data sheet.




Figure 1. Logic Equivalent Circuit

PIN DESCRIPTION

| QFN PIN # | Symbol | Name and Function |
|-------------|------------------------|-------------------------|
| 2, 5, 7, 10 | NC1 to NC2, NO1 to NO2 | Independent Channels |
| 4, 8 | IN1 and IN2 | Controls |
| 3, 9 | COM1 and COM2 | Common Channels |
| 6 | GND | Ground (V) |
| 1 | V _{CC} | Positive Supply Voltage |

MAXIMUM RATINGS

| Symbol | Parameter | Value | Unit |
|----------------------|---|------------------------------------|------|
| V _{CC} | Positive DC Supply Voltage | –0.5 to +5.5 | V |
| V _{IS} | Analog Input Voltage (V _{NO} , V _{NC} , or V _{COM}) | $-0.5 \le V_{IS} \le V_{CC} + 0.5$ | V |
| V _{IN} | Digital Select Input Voltage | $-0.5 \le V_{\text{IN}} \le +5.5$ | V |
| I _{anl1} | Continuous DC Current from COM to NC/NO | ±320 | mA |
| I _{anl-pk1} | Peak Current from COM to NC/NO, 10% Duty Cycle, 100 ms = t_{ON} (Note 1) | ±600 | mA |
| I _{anl-pk2} | Instantaneous Peak Current from COM to NC/NO, 10% Duty Cycle, t_{ON} < 1 μs | ±850 | mA |
| I _{cImp} | Continuous DC Current into COM/NO/NC with Respect to V_{CC} or GND | ±100 | mA |

Stresses exceeding those listed in the Maximum Ratings table may damage the device. If any of these limits are exceeded, device functionality should not be assumed, damage may occur and reliability may be affected. 1. Defined as 10% ON, 90% OFF Duty Cycle.

RECOMMENDED OPERATING CONDITIONS

| Symbol | Parameter | Min | Max | Unit |
|---------------------------------|---|------|-----------------|------|
| V _{CC} | DC Supply Voltage | 1.65 | 4.5 | V |
| V _{IN} | Digital Select Input Voltage (OVT) Overvoltage Tolerance | GND | 4.5 | V |
| V _{IS} | Analog Input Voltage (NC, NO, COM) | GND | V _{CC} | V |
| T _A | Operating Temperature Range | -40 | +85 | °C |
| t _r , t _f | Input Rise or Fall Time, SELECT $V_{CC} = 1.6 V - 2.7 V$ $V_{CC} = 3.0 V - 4.5 V$ | | 20 10 | ns/V |

Functional operation above the stresses listed in the Recommended Operating Ranges is not implied. Extended exposure to stresses beyond the Recommended Operating Ranges limits may affect device reliability.

NLAS5223B DC CHARACTERISTICS - DIGITAL SECTION (Voltages Referenced to GND)

| | | | | Guaranteed Limit | | |
|------------------|--|--|-----------------|------------------|----------------|------|
| Symbol | Parameter | Condition | V _{cc} | 25°C | –40°C to +85°C | Unit |
| V _{IH} | Minimum High-Level Input Voltage, Select Inputs | | 3.0 4.3 | 1.4 2.0 | 1.4 2.0 | V |
| V _{IL} | Maximum Low-Level Input Voltage, Select Inputs | | 3.0 4.3 | 0.7 0.8 | 0.7 0.8 | V |
| I _{IN} | Maximum Input Leakage Current, Select Inputs | $V_{IN} = V_{CC}$ or GND | 4.3 | ±0.1 | ±1.0 | μA |
| I _{OFF} | Power Off Leakage Current | V _{IN} = V _{CC} or GND | 0 | ±0.5 | ±2.0 | μA |
| I _{CC} | Maximum Quiescent Supply Current (Note 2) | Select and $V_{IS} = V_{CC}$ or GND | 1.65 to 4.5 | ±1.0 | ±2.0 | μA |

Product parametric performance is indicated in the Electrical Characteristics for the listed test conditions, unless otherwise noted. Product performance may not be indicated by the Electrical Characteristics if operated under different conditions.

2. Guaranteed by design. Resistance measurements do not include test circuit or package resistance.

NLAS5223B DC ELECTRICAL CHARACTERISTICS - ANALOG SECTION

| | | | | Gua | ranteed | l Maximur | n Limit | |
|--|---|---|-----------------|------|--------------|-----------|--------------|------|
| | | | | 25 | °C | –40°C t | o +85°C | |
| Symbol | Parameter | Condition | V _{CC} | Min | Max | Min | Max | Unit |
| R _{ON} | NC/NO On–Resistance (Note 3) | | 3.0 4.3 | | 0.4 0.35 | | 0.5 0.4 | Ω |
| R _{FLAT} | NC/NO On–Resistance Flatness (Notes 3 and 4) | $I_{COM} = 100 \text{ mA}$ $V_{IS} = 0 \text{ to } V_{CC}$ | 3.0 4.3 | | 0.16 0.11 | | 0.20 0.14 | Ω |
| ΔR _{ON} | On-Resistance Match Between Channels (Notes 3 and 5) | $V_{IS} = 1.5 V; \\ I_{COM} = 100 \text{ mA} \\ V_{IS} = 2.2 V; \\ I_{COM} = 100 \text{ mA} \end{cases}$ | 3.0 4.3 | | 0.05 0.05 | | 0.05 0.05 | Ω |
| I _{NC(OFF)} I _{NO(OFF)} | NC or NO Off Leakage Current (Note 3) | $ \begin{array}{l} V_{\text{IN}} = V_{\text{IL}} \text{ or } V_{\text{IH}} \\ V_{\text{NO}} \text{ or } V_{\text{NC}} = 0.3 \text{ V} \\ V_{\text{COM}} = 4.0 \text{ V} \end{array} $ | 4.3 | -5.0 | 5.0 | -50 | 50 | nA |
| I _{COM(ON)} | COM ON Leakage Current (Note 3) | $\label{eq:VIN} \begin{array}{l} V_{IN} = V_{IL} \mbox{ or } V_{IH} \\ V_{NO} \mbox{ 0.3 V or 4.0 V with} \\ V_{NC} \mbox{ floating or} \\ V_{NC} \mbox{ 0.3 V or 4.0 V with} \\ V_{NO} \mbox{ floating} \\ V_{COM} = \mbox{ 0.3 V or 4.0 V} \end{array}$ | 4.3 | -10 | 10 | -100 | 100 | nA |

Product parametric performance is indicated in the Electrical Characteristics for the listed test conditions, unless otherwise noted. Product performance may not be indicated by the Electrical Characteristics if operated under different conditions.

3. Guaranteed by design. Resistance measurements do not include test circuit or package resistance.

4. Flatness is defined as the difference between the maximum and minimum value of On-resistance as measured over the specified analog signal ranges.

5. $\Delta R_{ON} = R_{ON(MAX)} - R_{ON(MIN)}$ between NC1 and NC2 or between NO1 and NO2.

NLAS5223BL DC CHARACTERISTICS - DIGITAL SECTION (Voltages Referenced to GND)

| | | | | Guaranteed Limit | | |
|------------------|--|-------------------------------------|-----------------|------------------|----------------|------|
| Symbol | Parameter | Condition | V _{cc} | 25°C | –40°C to +85°C | Unit |
| V _{IH} | Minimum High-Level Input Voltage, Select Inputs | | 3.0 4.3 | 1.3 1.6 | 1.3 1.6 | V |
| V _{IL} | Maximum Low-Level Input Voltage, Select Inputs | | 3.0 4.3 | 0.5 0.6 | 0.5 0.6 | V |
| I _{IN} | Maximum Input Leakage Current, Select Inputs | V _{IN} = 4.5 V or GND | 4.3 | ±0.1 | ±1.0 | μA |
| I _{OFF} | Power Off Leakage Current | V _{IN} = 4.5 V or GND | 0 | ±0.5 | ±2.0 | μA |
| ICC | Maximum Quiescent Supply Current (Note 6) | Select and $V_{IS} = V_{CC}$ or GND | 1.65 to 4.5 | ±1.0 | ±2.0 | μΑ |

Product parametric performance is indicated in the Electrical Characteristics for the listed test conditions, unless otherwise noted. Product performance may not be indicated by the Electrical Characteristics if operated under different conditions.

6. Guaranteed by design. Resistance measurements do not include test circuit or package resistance.

NLAS5223BL DC ELECTRICAL CHARACTERISTICS – ANALOG SECTION

| | | | | Gua | ranteed | Maximur | n Limit | |
|--|---|---|-----------------|-----|--------------|---------|--------------|------|
| | | | | 25 | S°C | –40°C t | o +85°C | |
| Symbol | Parameter | Condition | v _{cc} | Min | Max | Min | Max | Unit |
| R _{ON} | NC/NO On-Resistance (Note 7) | | 3.0 4.3 | | 0.4 0.35 | | 0.5 0.4 | Ω |
| R _{FLAT} | NC/NO On–Resistance Flatness (Notes 7 and 8) | $I_{COM} = 100 \text{ mA}$ $V_{IS} = 0 \text{ to } V_{CC}$ | 3.0 4.3 | | 0.16 0.11 | | 0.20 0.14 | Ω |
| ΔR _{ON} | On-Resistance Match Between Channels (Notes 7 and 9) | $V_{IS} = 1.5 V; \\ I_{COM} = 100 \text{ mA} \\ V_{IS} = 2.2 V; \\ I_{COM} = 100 \text{ mA} \end{cases}$ | 3.0 4.3 | | 0.05 0.05 | | 0.05 0.05 | Ω |
| I _{NC(OFF)} I _{NO(OFF)} | NC or NO Off Leakage Current (Note 7) | $ \begin{array}{l} V_{IN} = V_{IL} \text{ or } V_{IH} \\ V_{NO} \text{ or } V_{NC} = 0.3 \text{ V} \\ V_{COM} = \ 4.0 \text{ V} \end{array} $ | 4.3 | -10 | 10 | -100 | 100 | nA |
| I _{COM(ON)} | COM ON Leakage Current (Note 7) | $\label{eq:VIN} \begin{array}{l} V_{IN} = V_{IL} \mbox{ or } V_{IH} \\ V_{NO} \mbox{ 0.3 V or 4.0 V with} \\ V_{NC} \mbox{ floating or} \\ V_{NC} \mbox{ 0.3 V or 4.0 V with} \\ V_{NO} \mbox{ floating} \\ V_{COM} = \mbox{ 0.3 V or 4.0 V} \end{array}$ | 4.3 | -10 | 10 | -100 | 100 | nA |

Product parametric performance is indicated in the Electrical Characteristics for the listed test conditions, unless otherwise noted. Product performance may not be indicated by the Electrical Characteristics if operated under different conditions.

7. Guaranteed by design. Resistance measurements do not include test circuit or package resistance.

8. Flatness is defined as the difference between the maximum and minimum value of On-resistance as measured over the specified analog signal ranges.

9. $\Delta R_{ON} = R_{ON(MAX)} - R_{ON(MIN)}$ between NC1 and NC2 or between NO1 and NO2.

AC ELECTRICAL CHARACTERISTICS (Input $t_r = t_f = 3.0$ ns)

| | | Guarante | | teed M | aximum L | .imit | | | | |
|------------------|-----------------------------------|--|-----------|--------|----------|-------|-----|----------------|-----|------|
| | | | Vcc | VIS | 25°C | | | –40°C to +85°C | | |
| Symbol | Parameter | Test Conditions | (V) | (V) | Min | Тур* | Max | Min | Max | Unit |
| t _{ON} | Turn–On Time | $R_L = 50 \ \Omega$, $C_L = 35 \ pF$ (Figures 3 and 4) | 2.3 – 4.5 | 1.5 | | | 50 | | 60 | ns |
| tOFF | Turn–Off Time | $R_L = 50 \ \Omega$, $C_L = 35 \ pF$ (Figures 3 and 4) | 2.3 – 4.5 | 1.5 | | | 30 | | 40 | ns |
| t _{BBM} | Minimum Break–Before–Make Time | | 3.0 | 1.5 | 2 | 15 | | | | ns |


| | | Typical @ 25, V _{CC} = 3.6 V | |
|--------------------|---|---------------------------------------|----|
| C _{IN} | Control Pin Input Capacitance | 3.5 | pF |
| C _{NO/NC} | NO, NC Port Capacitance | 60 | pF |
| C _{COM} | COM Port Capacitance When Switch is Enabled | 200 | pF |


*Typical Characteristics are at 25° C.


ADDITIONAL APPLICATION CHARACTERISTICS (Voltages Referenced to GND Unless Noted)

| | | | V _{cc} | 25°C | |
|------------------|--|---|-----------------|---------|------|
| Symbol | Parameter | Condition | (V) | Typical | Unit |
| BW | Maximum On–Channel –3 dB Bandwidth or Minimum Frequency Response | V_{IN} centered between V_{CC} and GND (Figure 5) | 1.65 – 4.5 | 19 | MHz |
| V _{ONL} | Maximum Feed-through On Loss | $V_{IN} = 0 \text{ dBm } @ 100 \text{ kHz to 50 MHz}$ V_{IN} centered between V_{CC} and GND (Figure 5) | 1.65 – 4.5 | -0.06 | dB |
| V _{ISO} | Off-Channel Isolation | f = 100 kHz; V_{IS} = 1 V RMS; C_L = 5.0 pF V_{IN} centered between V_{CC} and GND (Figure 5) | 1.65 – 4.5 | -68 | dB |
| Q | Charge Injection Select Input to Common I/O | $V_{IN} = V_{CC to} \text{ GND}, \text{R}_{IS} = 0 \Omega, \text{C}_{L} = 1.0 \text{nF}$ Q = C _L x DV _{OUT} (Figure 6) | 1.65 – 4.5 | 38 | рС |
| THD | Total Harmonic Distortion THD + Noise | F_{IS} = 20 Hz to 20 kHz, R_L = R_{gen} = 600 $\Omega,~C_L$ = 50 pF V_{IS} = 2.0 V RMS | 3.0 | 0.08 | % |
| VCT | Channel-to-Channel Crosstalk | f = 100 kHz; V _{IS} = 1.0 V RMS, C _L = 5.0 pF, R _L = 50 Ω V _{IN} centered between V _{CC} and GND (Figure 5) | 1.65 – 4.5 | -70 | dB |

10. Off-Channel Isolation = 20log10 (V_{COM}/V_{NO}), V_{COM} = output, V_{NO} = input to off switch.













Figure 3. t_{ON}/t_{OFF}








Channel switch control/s test socket is normalized. Off isolation is measured across an off channel. On loss is the bandwidth of an On switch. V_{ISO} , Bandwidth and V_{ONL} are independent of the input signal direction.

$$\begin{split} V_{ISO} &= Off \ Channel \ Isolation = 20 \ Log\Bigl(\frac{V_{OUT}}{V_{IN}}\Bigr) for \ V_{IN} \ at \ 100 \ kHz \\ V_{ONL} &= On \ Channel \ Loss = 20 \ Log\Bigl(\frac{V_{OUT}}{V_{IN}}\Bigr) for \ V_{IN} \ at \ 100 \ kHz \ to \ 50 \ MHz \end{split}$$

Bandwidth (BW) = the frequency 3 dB below V_{ONL} V_{CT} = Use V_{ISO} setup and test to all other switch analog input/outputs terminated with 50 Ω







Figure 6. Charge Injection: (Q)




ORDERING INFORMATION

| Device | Package | Shipping [†] |
|-----------------|---------------------|-----------------------|
| NLAS5223BMNR2G | WQFN10 (Pb-Free) | 3000 / Tape & Reel |
| NLAS5223BLMNR2G | WQFN10 (Pb-Free) | 3000 / Tape & Reel |
| NLAS5223BMUR2G | UQFN10 (Pb-Free) | 3000 / Tape & Reel |

+For information on tape and reel specifications, including part orientation and tape sizes, please refer to our Tape and Reel Packaging Specifications Brochure, BRD8011/D.

PACKAGE DIMENSIONS


WQFN10, 1.4x1.8, 0.4P CASE 488AQ **ISSUE C**




- NOTES: 1. DIMENSIONING AND TOLERANCING PER ASME Y14.5M, 1994. 2. CONTROLLING DIMENSION: MILLIMETERS 3. DIMENSION & APPLIES TO PLATED TERMINAL AND IS MEASURED BETWEEN 0.25 AND 0.30 MM FROM TERMINAL.
- FROM TERMINAL. COPLANARITY APPLIES TO THE EXPOSED PAD AS WELL AS THE TERMINALS. EXPOSED PADS CONNECTED TO DIE FLAG. USED AS TEST CONTACTS. 4. 5.


| | MILLIMETERS | | |
|-----|-------------|-------|--|
| DIM | MIN | MAX | |
| Α | 0.70 | 0.80 | |
| A1 | 0.00 | 0.050 | |
| A3 | 0.20 REF | | |
| b | 0.15 | 0.25 | |
| D | 1.40 BSC | | |
| Ε | 1.80 BSC | | |
| е | 0.40 BSC | | |
| L | 0.30 | 0.50 | |
| L1 | 0.40 | 0.60 | |
| M1 | 0.00 | 0.05 | |

MOUNTING FOOTPRINT



PACKAGE DIMENSIONS





ON Semiconductor and the intervent and the intervent of the product of the property of the property. A listing of SCILLC's product/patent coverage may be accessed at www.onsemi.com/site/pdt/Patent-Marking.pdf. SCILLC reserves the right to make changes without further notice to any products herein. SCILLC makes no warranty, representation or guarantee regarding the suitability of its products for any particular purpose, nor does SCILLC assume any liability arising out of the application or use of any product or circuit, and specifically disclaims any and all liability, including without limitation special, consequential or incidental damages. "Typical" parameters which may be provided in SCILLC data sheets and/or specifications can and do vary in different applications and actual performance may vary over time. All operating parameters, including "Typicals" must be validated for each customer application by customer's technical experts. SCILLC does not convey any license under tights nor the rights of others. SCILLC products are not designed, intended, or authorized for use as components in systems intended for surgical implant into the body, or other applications intended to support or sustain life, or for any other application in which the failure of the SCILLC product area a situation where personal injury or death may occur. Should Buyer purchase or use SCILLC for any such unintended or unauthorized application. Buyer shall indemnity and hold SCILLC and its officers, employees, subsidiaries, affliates, and distributors harmless against all claims, costs, damages, and expenses, and reasonable attorney fees arising out of, directly or indirectly, any claim of personal injury or death associated with such unintended or unauthorized use, even if such claim alleges that SCILLC was negligent regarding the design or manufacture of the part. SCILLC is an Equal Opportunity/Affirmative Action Employer. This literature is subject to all applicable copyright laws and is not for resale in any manner.

PUBLICATION ORDERING INFORMATION

LITERATURE FULFILLMENT:

Literature Distribution Center for ON Semiconductor 19521 E. 32nd Pkwy, Aurora, Colorado 80011 USA Phone: 303–675–2175 or 800–344–3860 Toll Free USA/Canada Fax: 303–675–2176 or 800–344–3867 Toll Free USA/Canada Email: orderlit@onsemi.com N. American Technical Support: 800–282–9855 Toll Free USA/Canada Europe, Middle East and Africa Technical Support:

Phone: 421 33 790 2910 Japan Customer Focus Center Phone: 81–3–5817–1050 ON Semiconductor Website: www.onsemi.com

Order Literature: http://www.onsemi.com/orderlit

For additional information, please contact your local Sales Representative