mail

Chipsmall Limited consists of a professional team with an average of over 10 year of expertise in the distribution of electronic components. Based in Hongkong, we have already established firm and mutual-benefit business relationships with customers from, Europe, America and south Asia, supplying obsolete and hard-to-find components to meet their specific needs.

With the principle of "Quality Parts, Customers Priority, Honest Operation, and Considerate Service", our business mainly focus on the distribution of electronic components. Line cards we deal with include Microchip, ALPS, ROHM, Xilinx, Pulse, ON, Everlight and Freescale. Main products comprise IC, Modules, Potentiometer, IC Socket, Relay, Connector. Our parts cover such applications as commercial, industrial, and automotives areas.

We are looking forward to setting up business relationship with you and hope to provide you with the best service and solution. Let us make a better world for our industry!



Contact us

Tel: +86-755-8981 8866 Fax: +86-755-8427 6832 Email & Skype: info@chipsmall.com Web: www.chipsmall.com Address: A1208, Overseas Decoration Building, #122 Zhenhua RD., Futian, Shenzhen, China



Crystal Oscillator



NT3225SA

Temperature Compensated Crystal Oscillator (TCXO)

Main Application

Smartphone / Mobile phone, Wireless module, and GPS / GNSS module, etc.

Features

- Supports low power supply voltage. (Supports DC +1.7 V to +3.3 V.)
- Compact and light with a height, cubic volume, and weight of Max. 1.0 mm, 0.007 cm³, and 0.024 g, respectively.
- Low power consumption.
- A surface-mount crystal oscillator. (Reflow soldering is possible.)
- Lead-free. Meets the requirements for re-flow profiling using lead-free solder.


Specifications

NT3225SA	
10 to 40	
10, 12, 12.288, 12.8, 13, 14.4, 14.7456, 15, 15.36, 16, 16.368, 16.369, 16.384, 16.8, 18, 19.2, 19.44, 19.68, 20, 21.25, 22.4, 24, 24.576, 25, 26	38.4, 40
+1.8, +3.0	
10 kΩ//10 pF	
Max. 1.5	Max 1.7
Min. 0.8 V(p-p) (DC Coupling *1)	
Max. ±2.5×10⁻⁴	
-30 to +75	
-40 to +85	
Max. ±0.3×10 ⁻⁶ /Vcc±5 %	
Max. ±0.2×10 ⁻⁶ /(10 kΩ//10 pF) ±10 %	
Max. ±1.0×10 ⁻⁶ /year	
	$\begin{array}{c} 10 \text{ to } 40 \\ 10, \ 12, \ 12.288, \ 12.8, \ 13, \ 14.4, \ 14.7456, \\ 15, \ 15.36, \ 16, \ 16.368, \ 16.369, \ 16.384, \\ 16.8, \ 18, \ 19.2, \ 19.44, \ 19.68, \ 20, \ 21.25, \\ 22.4, \ 24, \ 24.576, \ 25, \ 26 \\ & +1.8, +3.0 \\ \hline 10 \ \text{k}\Omega //10 \ \text{pF} \\ \hline \text{Max. } 1.5 \\ \hline \text{Min. } 0.8 \ \text{V}(\text{p-p}) \ (\text{DC Coupling *1} \\ \hline \text{Max. } \pm 2.5 \times 10^{-6} \\ \hline -30 \ \text{to } +75 \\ \hline -40 \ \text{to } +85 \\ \hline \text{Max. } \pm 0.3 \times 10^{-6} / \text{Vcc} \pm 5 \ \% \\ \hline \text{Max. } \pm 0.2 \times 10^{-6} / (10 \ \text{k}\Omega //10 \ \text{pF}) \pm 10 \\ \hline \end{array}$

• Frequency setting conditions : Frequencies are set at normal temperatures (+25±2 °C).

*1. A DC-cut capacitor is not embedded in this crystal oscillator. Connect a DC-cut capacitor (1,000 pF) to the line-out terminal of the oscillator.

Dimensions



Please specify the model name, frequency, and specification number when you order products. For further questions regarding specifications, please feel free to contact us.





RoHS Compliant Directive 2011/65/EU

Specification Number

Frequency	Supply voltage	
(MHz)	+1.8V	+3.0V
10	NSA3631A	NSA3632A
12	NSA3631A	NSA3632A
12.288	NSA3631A	NSA3632A
12.8	NSA3631A	NSA3632A
13	NSA3631A	NSA3632A
14.4	NSA3631A	NSA3632A
14.7456	NSA3631A	NSA3632A
15	NSA3631A	NSA3632A
15.36	NSA3631A	NSA3632A
16	NSA3631A	NSA3632A
16.368	NSA3631A	NSA3632A
16.369	NSA3631A	NSA3632A
16.384	NSA3631A	NSA3632A
16.8	NSA3631A	NSA3632A
18	NSA3631A	NSA3632A
19.2	NSA3631A	NSA3632A
19.44	NSA3631A	NSA3632A
19.68	NSA3631A	NSA3632A
20	NSA3631A	NSA3632A
21.25	NSA3631B	NSA3632B
22.4	NSA3631B	NSA3632B
24	NSA3631B	NSA3632B
24.576	NSA3631B	NSA3632B
25	NSA3631B	NSA3632B
26	NSA3631B	NSA3632B
38.4	NSA3631C	NSA3632C
40	NSA3631C	NSA3632C