

Chipsmall Limited consists of a professional team with an average of over 10 year of expertise in the distribution of electronic components. Based in Hongkong, we have already established firm and mutual-benefit business relationships with customers from, Europe, America and south Asia, supplying obsolete and hard-to-find components to meet their specific needs.

With the principle of "Quality Parts, Customers Priority, Honest Operation, and Considerate Service", our business mainly focus on the distribution of electronic components. Line cards we deal with include Microchip, ALPS, ROHM, Xilinx, Pulse, ON, Everlight and Freescale. Main products comprise IC, Modules, Potentiometer, IC Socket, Relay, Connector. Our parts cover such applications as commercial, industrial, and automotives areas.

We are looking forward to setting up business relationship with you and hope to provide you with the best service and solution. Let us make a better world for our industry!



Contact us

Tel: +86-755-8981 8866 Fax: +86-755-8427 6832

Email & Skype: info@chipsmall.com Web: www.chipsmall.com

Address: A1208, Overseas Decoration Building, #122 Zhenhua RD., Futian, Shenzhen, China











OAC Series

AC Output Modules

cas File E29244

Users should thoroughly review the technical data before selecting a product part number. It is recommended that users also seek out the pertinent approvals files of the agencies/laboratories and review them to ensure the product meets the requirements for a given application.

Features

- .6" (15.2mm) thick package.
- 4000V rms optical isolation.
- High immunity to false operation.
- · Series compatible.
- Output modules can be controlled from sinking or sourcing logic.
- Compatible with 2IOM series mounting boards.

Engineering Data

Switch Form: 1 Form A (SPST-NO)

Duty: Continuous.

Operating Temperature: -30°C to +80°C. Storage Temperature: -30°C to +100°C. Potting Compound Flammability: UL94V-0. Solderability: 260°C for 5 seconds, maximum.

Approximate Weight: 1.38 oz. (35g).

Ordering Information

Typical Part Number >

OAC

A

-5

1. Basic Series: OAC = AC output module — black case

2. Input Voltage: 5 = 5VDC 15 = 15VDC

24 = 24VDC

3. Output: Blank = 3A, 12-120VAC, zero voltage turn-on output

A = 3A, 24-280VAC, zero voltage turn-on output H = 5A, 24-280VAC, zero voltage turn-on output

R = 24-280VAC, Random Turn-On

Our authorized distributors are more likely to maintain the following items in stock for immediate delivery.

OAC-5 OAC-5H OAC-24 OAC-5A OAC-15 OAC-24A

Input Specifications

Parameter	Conditions	Units	OAC-5 OAC-5A OAC-5H OAC-5R			OAC-15 OAC-15A OAC-15H OAC-15R			OAC-24 OAC-24A OAC-24H OAC-24R		
			Min.	Тур.	Max.	Min.	Тур.	Max.	Min.	Тур.	Max.
Control Voltage Range VIN		VDC	3	5	8	9	15	18	18	24	32
Must Operate Voltage VIN(OP) (Min.)		VDC			3			9			18
Must release Voltage VIN(REL) (Min.)		VDC	1			1			1		
Input Current (Max.)	@VIN=Nominal	mADC	2 - 10			6 - 12			4 - 12		
Input Resistance RIN		Ohms	800			1500			2600		

PIN-3 must be positive with respect to PIN-4 for correct operation.



OAC Series (Continued)


AC Output Modules


Output Specifications (47 to 63 Hz.,@+25°C unless otherwise specified)

Parameter	Conditions Units		OAC-5 OAC-15 OAC-24		OAC-5A OAC-15A OAC-24A			OAC-5H OAC-15H OAC-24H			OAC-5R OAC-15R OAC-24R			
			Min.	Тур.	Max	Min.	Тур.	Max	Min.	Тур.	Max.	Min.	Тур.	Max.
Load Voltage V∟		V rms	12		120	24		280	24		280	24		280
Repetitive Blocking Voltage		V peak			400			600			600			600
Load Current I∟*		A rms	.05		3	.05		3	.05		5	.05		5
Single Cycle Surge Current		A peak		208			208			300			300	
Leakage Current (Off-State)	VL=280VAC	mA rms			5			5			5			5
On-State Voltage Drop	IL=Max.	V rms			1.8			1.8			1.6			1.6
Static dv / dt (Off-State)		V/µs		475			475			300			300	
Turn-On Time	@f co/50 LI=	ms		8.3 / 10			8.3 / 10)		8.3 / 10)		0.1	
Turn-Off Time	@f=60/50 Hz.	ms		8.3 / 10			8.3 / 10)		.3 / 10			8.3	
HP / Rating	@ 240VAC	HP		1/4			1/4			1/2			1/2	


^{*} See Derating curve


OAC Operating Diagram





OAC Derating Diagram





Outline Dimensions

