

Chipsmall Limited consists of a professional team with an average of over 10 year of expertise in the distribution of electronic components. Based in Hongkong, we have already established firm and mutual-benefit business relationships with customers from, Europe, America and south Asia, supplying obsolete and hard-to-find components to meet their specific needs.

With the principle of "Quality Parts, Customers Priority, Honest Operation, and Considerate Service", our business mainly focus on the distribution of electronic components. Line cards we deal with include Microchip, ALPS, ROHM, Xilinx, Pulse, ON, Everlight and Freescale. Main products comprise IC, Modules, Potentiometer, IC Socket, Relay, Connector. Our parts cover such applications as commercial, industrial, and automotives areas.

We are looking forward to setting up business relationship with you and hope to provide you with the best service and solution. Let us make a better world for our industry!



Contact us

Tel: +86-755-8981 8866 Fax: +86-755-8427 6832

Email & Skype: info@chipsmall.com Web: www.chipsmall.com

Address: A1208, Overseas Decoration Building, #122 Zhenhua RD., Futian, Shenzhen, China







PRO-57

Tweezer Digital Multimeter

The PRO-57 Capabilities:

Resistance Measurement

Capacitance Measurement

Continuity Measurement

Diode Test





- Resistance
- Capacitance
- Continuity
- Diode Test
- Data Hold
- Auto Check Mode
- Manual Selectable Range



The PRO-57 Tweezer Digital Multimeter is a compact Digital Multimeter (DMM) with a tweezer form factor. Small enough for one-hand operation, it is ideally suited to measure Surface Mount Devices (SMD).

Although the PRO-57 is much smaller and lighter than traditional multimeters, it is able to measure resistance in six ranges which are from 300 Ω to 30 M Ω , to measure continuity under 300 Ω , to measure capacitance in 8 ranges from 3 nF to 30 mF, and to test diodes.

The Tweezer Digital Multimeter has
Auto Check Mode which automatically
switches to the applicable measurement
for resistance, capacitance, continuity
or diode test.





Tweezer Digital Multimeter

PRO-57 comes with the following items:

Operating Instructions Manual

Specifications:	
Resistance accuracy	1-5% depending on the range
Capacitance accuracy	3-5% depending on the range
Diode test accuracy	3%
Display	3000 counts
Polarity	Automatic, (-)negative polarity indication
Over range	"OL" mark indication
Low battery indication	The " is displayed when the battery voltage drops below the operating level
Measurement rate	4 times per second, nominal
Auto power off	Approx. 10 minutes
Operating environment	0°C - 40°C (32°F - 104°F) at < 70% R.H.
Storage temperature	-20°C - 60°C (-4°F - 140°F) at < 80% R.H. with battery removed from meter
Power	3.0 V button-type lithium battery ×1, CR2032
Battery life	100 hours continuous operation
Dimensions	205mm(H) × 40 mm(W) ×24.5mm(D)
Weight	Approx. 3.5 oz (100g) including battery

Specifications subject to change without notice. Go to globalspecialties.com for the latest update.





