

Chipsmall Limited consists of a professional team with an average of over 10 year of expertise in the distribution of electronic components. Based in Hongkong, we have already established firm and mutual-benefit business relationships with customers from, Europe, America and south Asia, supplying obsolete and hard-to-find components to meet their specific needs.

With the principle of "Quality Parts, Customers Priority, Honest Operation, and Considerate Service", our business mainly focus on the distribution of electronic components. Line cards we deal with include Microchip, ALPS, ROHM, Xilinx, Pulse, ON, Everlight and Freescale. Main products comprise IC, Modules, Potentiometer, IC Socket, Relay, Connector. Our parts cover such applications as commercial, industrial, and automotives areas.

We are looking forward to setting up business relationship with you and hope to provide you with the best service and solution. Let us make a better world for our industry!



Contact us

Tel: +86-755-8981 8866 Fax: +86-755-8427 6832

Email & Skype: info@chipsmall.com Web: www.chipsmall.com

Address: A1208, Overseas Decoration Building, #122 Zhenhua RD., Futian, Shenzhen, China







Industrial Relay Type RCP Monostable





- 8 or 11-pin socket mounting
- 2 or 3 change over contacts
- Long life (minimun 100.000 electrical operations) at 10 A 250 VAC /30 VDC
- Switching capacity 12 A (5x10⁴ cycles)
- AC coils 6 to 230 VAC
- DC coils 6 to 110 VDC
- Matched sockets available
- Standard with LED, Push with arm and Flag
- IP 40
- . Conform to CE low voltage directive
- IMQ, UL, TÜV, CSA approved

Product Description

The RCP relay can be used for a wide range of industrial applications.

Available in 2 or 3 changeover contact configuration, Octal or Undecal version.

Type Selection

Contact configuration		Contact rating	Contact code
2 change over contacts	(DPDT {2-form C})	10 A	002
3 change over contacts	(3PDT {3-form C})	 10 A	003

Coil Characteristics, DC

	At 20°C		At 40°C		
Nominal voltage VDC	Pick-up voltage VDC	Drop-out voltage VDC	Pick-up voltage VDC	Drop-out voltage VDC	Coil resistance Ω
6	4.8	0.6	5.2	0.6	23.5 ±10%
12	9.6	1.2	10.3	1.3	95.0 ±10%
24	19.2	2.4	20.7	2.6	430.0 ±10%
48	38.4	4.8	41.4	5.1	1630.0 ±15%
60	45.0	6.0	48.6	6.4	3000.0 ±15%
100	80.0	10.0	86.4	10.8	6800.0 ±15%
110	88.0	11.0	95.0	11.8	6800.0 ±15%

Coil Characteristics, AC

	At 2	20°C	At 4	Ю°С	
Nominal voltage VAC	Pick-up voltage VAC	Drop-out voltage VAC	Pick-up voltage VAC	Drop-out voltage VAC	Coil resistance Ω
6 12 24 48 115/120 230	4.8 9.6 19.2 38.4 88.0 176.0	1.8 3.6 7.2 14.4 36.0 72.0	5.2 10.3 20.7 41.4 95.0 190.0	1.9 3.8 7.7 15.5 38.8 77.7	40.0 ±10% 160.0 ±10% 650.0 ±10% 2600.0 ±15% 11000.0 ±15%

Coil operating range: see diagram n° 1 pag. 18



Contact Characteristics

Arrangement		002 / 003	
Contact rating (with resistive load)		10 A - 250 VAC / 30 VDC	
UL rating		10 A - 250 VAC / 30VDC 1/3 HP at 240 VAC	
Usually rating	(1x10 ⁵ ops)	10 A - 250 VAC / 30 VDC	
Max. rating	(5x104 ops)	12 A - 250 VAC / 30 VDC	
Material		Silver alloy	

Current Max. switching current	10 A
Initial contact resistance	50 mΩ (at 1 A 6 VDC)
Max. switch. voltage	250 VAC / 30 VDC
Max. switch. power	2500 VA / 300 W
Life Electrical life Mechanical life	1x10 ⁵ ops 1x10 ⁷ ops

Insulation

Test Voltage (1 min.) Between coil and contacts Between open contacts Contact/Contact	3750 VAC Vr.m.s 750 VAC Vr.m.s 1250 VA Vr.m.s
Initial insulation resistance	500 M Ω - 500 VAC

Insulation according to EN61810-5 Rated insulation voltage Impulsive insulation voltage Pollution degree Overvoltage category

250 V 3.6 KV 2 III


General Data


Nominal coil power	1.5 W / 2.5 VA
Operating time (At nominal voltage)	30 ms max.
Release time (At nominal voltage)	20 ms max.
Temperature rise (At nominal voltage)	-40° C to +55° C
Ambient temperature	+50° C

Vibration resistance	10 to 55 Hz 1.5 mm
Shock resistance	
Funktional	100 m/s ² /10 g
Destructive	500 m/s ² /50 g
Humidity	98%, +40°C%
Termination	Octal/Undecal-type plug
Construction	Dust cover
Weight	~ 85 g

Dimensions


Wiring Diagrams







Diagrams

1 Coil Operating Range





2 Electrical life





3 Max. DC load breaking capacity





Approvals







