

Chipsmall Limited consists of a professional team with an average of over 10 year of expertise in the distribution of electronic components. Based in Hongkong, we have already established firm and mutual-benefit business relationships with customers from, Europe, America and south Asia, supplying obsolete and hard-to-find components to meet their specific needs.

With the principle of "Quality Parts, Customers Priority, Honest Operation, and Considerate Service", our business mainly focus on the distribution of electronic components. Line cards we deal with include Microchip, ALPS, ROHM, Xilinx, Pulse, ON, Everlight and Freescale. Main products comprise IC, Modules, Potentiometer, IC Socket, Relay, Connector. Our parts cover such applications as commercial, industrial, and automotives areas.

We are looking forward to setting up business relationship with you and hope to provide you with the best service and solution. Let us make a better world for our industry!



## Contact us

Tel: +86-755-8981 8866 Fax: +86-755-8427 6832

Email & Skype: info@chipsmall.com Web: www.chipsmall.com

Address: A1208, Overseas Decoration Building, #122 Zhenhua RD., Futian, Shenzhen, China











### Metal thin film chip resistors (precision)

## **■**RR series

#### **Features**

· Precision chip resistors excellent in resistance tolerance, TCR, frequency performance, noise characteristics, and linearity.

# Lead

free






### **Applications**

- · Consumer electronics that requires precision resistors
- · All purpose resistors in any area of electronics


### **♦**Part numbering system



### **◆**Electrical Specification

Туре	Power ratings	Temperature coefficient of resistance	Resistance range( $\Omega$ ) Resistance tolerance			Maximum voltage	Resistance value series	Operating temperature	Packaging quantity
		(ppm/°C)	±0.1% (B)	±0.5% (D)	±1% (F)				
RR0306	1/20W	±25(P)	33≦R≦22k			15V	F 04		5,000pcs
		±100(R)	_	_	10≦R≦30	150	E-24	-55°C <sup>~</sup> 125°C .	5,000pcs
RR0510	1/16W	±25(P)	_	100≦R≦100k	-	25V	E-24, E-96		10,000pcs
		±100(R)		10≦R<100					
RR0816	1/16W	±25(P)	_	100≦R≦360k	-	75V			5,000pcs
		±50(Q)		10≦R<100					
RR1220	1/10W	±25(P)	_	100≦R≦1M		100V			
		±50(Q)	_	10≦R<100	_	. 551			

### **▶**Dimensions



Туре	Size (inch)	L	w	а	b	t
RR0306	0201	0.60±0.05	0.30±0.05	0.12±0.05	0.12±0.05	0.23±0.03
RR0510	0402	1.00±0.05	0.50±0.05	0.20±0.10	0.25±0.05	0.35±0.05
RR0816	0603	1.60±0.20	0.80±0.20	0.30±0.20	0.30±0.20	0.40±0.10
RR1220	0805	2.00±0.20	1.25±0.20	0.40±0.20	0.40±0.20	0.40±0.10

(unit:mm)