

Chipsmall Limited consists of a professional team with an average of over 10 year of expertise in the distribution of electronic components. Based in Hongkong, we have already established firm and mutual-benefit business relationships with customers from, Europe, America and south Asia, supplying obsolete and hard-to-find components to meet their specific needs.

With the principle of "Quality Parts, Customers Priority, Honest Operation, and Considerate Service", our business mainly focus on the distribution of electronic components. Line cards we deal with include Microchip, ALPS, ROHM, Xilinx, Pulse, ON, Everlight and Freescale. Main products comprise IC, Modules, Potentiometer, IC Socket, Relay, Connector. Our parts cover such applications as commercial, industrial, and automotives areas.

We are looking forward to setting up business relationship with you and hope to provide you with the best service and solution. Let us make a better world for our industry!



Contact us

Tel: +86-755-8981 8866 Fax: +86-755-8427 6832

Email & Skype: info@chipsmall.com Web: www.chipsmall.com

Address: A1208, Overseas Decoration Building, #122 Zhenhua RD., Futian, Shenzhen, China









S8JX

Power Supplies



Cost Effective Power Supplies with Multiple Mounting Options

Wide range of DC output voltages

» 5 V, 12 V, 15 V, 24 V, and 15W, 35W, 50W, 100W, 150W, 300W, 600W sizes

Universal input voltage

» 85-264 VAC, 50/60 Hz (15W to 150W); switchable 100-120 VAC/200-240 VAC for 300W and 600W

Multiple mounting options

» For panel design flexibility – DIN, front, bottom, or side

Series operation

» Available for up to 2 power supplies

Parallel operation

» Up to 5 units, 300W and 600W models

Extend machine life

» With built-in overload and overvoltage protection

Approvals

» UL, cUL, UL508 Listed, CE, SEMI F47, VDE

Adjustable voltage output (-10% to 15%) Two-year warranty

Specifications & Ordering Information

| Power Rating | Output Voltage | Output Current | Dimensions H x W x D mm (inches) Max. DIN mount | Part Numbers | | | |
|-----------------|-------------------|-------------------|---|--------------|----------------|---------------|----------------|
| | | | | Open Frame | | Covered Frame | |
| | | | | Front* Mount | DIN-rail Mount | Front* Mount | DIN-rail Mount |
| 15 W | 5 V | 3 A | 96 x 39.5 x 114.5 (3.78 x1.56 x 4.51) | S8JX-G01505 | \$8JX-G01505D | S8JX-G01505C | \$8JX-G01505CD |
| | 12 V | 1.3 A | | \$8JX-G01512 | \$8JX-G01512D | \$8JX-G01512C | \$8JX-G01512CD |
| | 15 V | 1 A | | \$8JX-G01515 | \$8JX-G01515D | S8JX-G01515C | \$8JX-G01515CD |
| | 24 V | 0.65 A | | \$8JX-G01524 | \$8JX-G01524D | 58JX-G01524C | \$8JX-G01524CD |
| 35 W | 5 V | 7 A | 96 x 39.5 x 114.5 (3.78 x1.56 x 4.51) | \$8JX-G03505 | S8JX-G03505D | \$8JX-G03505C | \$8JX-G03505CD |
| | 12 V | 3 A | | S8JX-G03512 | \$8JX-G03512D | 58JX-G03512C | S8JX-G03512CD |
| | 15 V | 2.4 A | | S8JX-G03515 | S8JX-G03515D | S8JX-G03515C | S8JX-G03515CD |
| | 24 V | 1.5 A | | S8JX-G03524 | S8JX-G03524D | S8JX-G03524C | S8JX-G03524CD |
| 50 W | 5 V | 10 A | 97 x 40 x 124.5 (3.82 x 1.57 x 4.90) | S8JX-G05005 | S8JX-G05005D | S8JX-G05005C | S8JX-G05005CD |
| | 12 V | 4.2 A | | \$8JX-G05012 | S8JX-G05012D | S8JX-G05012C | S8JX-G05012CD |
| | 24 V | 2.1 A | | S8JX-G05024 | \$8JX-G05024D | S8JX-G05024C | \$8JX-G05024CD |
| 100 W | 5 V | 20 A | 97 x 50 x 174.5 (3.82 x 1.97 x 6.87) | S8JX-G10005 | S8JX-G10005D | S8JX-G10005C | S8JX-G10005CD |
| | 12 V | 8.5 A | | \$8JX-G10012 | S8JX-G10012D | S8JX-G10012C | S8JX-G10012CD |
| | 24 V | 4.5 A | | S8JX-G10024 | S8JX-G10024D | S8JX-G10024C | S8JX-G10024CD |
| 150 W | 24 V | 6.5 A | 97 x 50 x 174.5 (3.82 x 1.97 x 6.87) | \$8JX-G15024 | \$8JX-G15024D | \$8JX-G15024C | \$8JX-G15024CD |
| 300 W | 24 V | 14 A | 96 x 110 x 204.8 (3.78 x 4.33 x 8.06) | _ | - | 58JX-G30024C | \$8JX-G30024CD |
| 600 W | 24 V | 27 A | 92 x 150 x 184.2 (3.62 x 5.90 x 7.25) | _ | - | \$8JX-G60024C | _ |

^{* -} Front mount models can also be side or bottom mounted. Front mounting bracket included. See datasheet for other optional mounting bracket details.

Optional Mounting Brackets

| Description | Part Numbers |
|--|--------------|
| Mounting Bracket A (bottom mounting for 50 W models) | S82Y-JX05B |
| Mounting Bracket B (bottom mounting for 100 W: 24 V models) | \$82Y-JX10B |
| Mounting Bracket C (bottom mounting for 100 W: 5 V and 12 V models and 150 W models) | \$82Y-JX15B |
| Mounting Bracket D (front mounting for 100 W: 5 V and 12 V models and 150 W models) | S82Y-JX15F |

OMRON ELECTRONICS LLC • THE AMERICAS HEADQUARTERS • Schaumburg, IL USA • 847.843.7900 • 800.556.6766 • www.omron247.com

OMRON CANADA, INC. • HEAD OFFICE

OMRON ELECTRONICS MEXICO SA DE CV • HEAD OFFICE

Apodaca, N.L. • 52.811.156.99.10 • 001.800.556.6766 • mela@omron.com

OMRON ELETRÔNICA DO BRASIL LTDA • HEAD OFFICE

Toronto, ON, Canada • 416.286.6465 • 866.986.6766 • www.omron247.com

São Paulo, SP, Brasil • 55.11.2101.6300 • www.omron.com.br

Note: Specifications are subject to change.

© 2009 Omron Electronics LLC

Printed in U.S.A.