

Chipsmall Limited consists of a professional team with an average of over 10 year of expertise in the distribution of electronic components. Based in Hongkong, we have already established firm and mutual-benefit business relationships with customers from, Europe, America and south Asia, supplying obsolete and hard-to-find components to meet their specific needs.

With the principle of "Quality Parts, Customers Priority, Honest Operation, and Considerate Service", our business mainly focus on the distribution of electronic components. Line cards we deal with include Microchip, ALPS, ROHM, Xilinx, Pulse, ON, Everlight and Freescale. Main products comprise IC, Modules, Potentiometer, IC Socket, Relay, Connector. Our parts cover such applications as commercial, industrial, and automotives areas.

We are looking forward to setting up business relationship with you and hope to provide you with the best service and solution. Let us make a better world for our industry!



Contact us

Tel: +86-755-8981 8866 Fax: +86-755-8427 6832

Email & Skype: info@chipsmall.com Web: www.chipsmall.com


Address: A1208, Overseas Decoration Building, #122 Zhenhua RD., Futian, Shenzhen, China











Electrical Details		
Electrical Configuration	C Filter	
Capacitance Measurement	@ 1000hr Point	<u> </u>
Current Rating	10A	
Insulation Resistance (IR)	$10 \text{G}\Omega$ or $1000 \Omega\text{F}$	<u></u> + c
Temperature Rating	-55°C to +125°C	
Ferrite Inductance (Typical)	Not Applicable	
Mechanical Details		
Head (A/F)	4.75mm (0.187")	
Nut A/F	6.35mm (0.250")	
Washer diameter	8mm (0.315")	
Mounting Torque	0.5Nm <i>(4.42lbf in)</i> m 0.25Nm <i>(2.21lbf in)</i> r	
Mounting Hole Diameter	4.4mm ±0.1 (0.173"	±0.004")
Max. Panel Thickness	2.9mm (0.114")	
Weight (Typical)	1.2g (0.04oz)	
Finish	Silver plate on coppe	r undercoat

Product Code	Capacitance	Dielectric	Rated Voltage	DWV		Typical	No-Load I	insertion	Loss (dB)									
Troduct code	(±20%) UOS	Diciccurc	(Vdc) (Vdc)		0.01MHz	0.1MHz	1MHz	10MHz	100MHz	1GHz								
*SFBCC5000100ZC	10pF -20% / +80%				-	-	-	-	-	4								
SFBCC5000150ZC	15pF -20% / +80%				-	-	-	-	-	7								
SFBCC5000220ZC	22pF -20% / +80%				-	-	-	-	-	10								
SFBCC5000330ZC	33pF -20% / +80%				-	-	-	-	-	12								
*SFBCC5000470ZC	47pF -20% / +80%	C0G/NP0			-	-	-	-	1	15								
*SFBCC5000680MC	68pF	COG/NPO			-	-	-	-	2	18								
*SFBCC5000101MC	100pF				-	-	-	-	4	22								
SFBCC5000151MC	150pF				-	-	-	-	7	25								
*SFBCC5000221MC	220pF				-	-	-	-	10	29								
*SFBCC5000331MC	330pF				-	-	-	-	13	33								
*SFBCC5000471MX	470pF	†X7R	500#	750	-	-	-	1	16	35								
SFBCC5000681MX	680pF		1X/1C 500#	730	-	-	-	2	19	36								
*SFBCC5000102MX	1.0nF				-	-	-	4	23	41								
SFBCC5000152MX	1.5nF												-	-	-	7	26	45
*SFBCC5000222MX	2.2nF												-	-	-	10	30	50
SFBCC5000332MX	3.3nF												-	-	-	13	33	52
*SFBCC5000472MX	4.7nF				-	-	1	16	36	55								
SFBCC5000682MX	6.8nF				-	-	2	19	39	57								
*SFBCC5000103MX	10nF	X7R			-	-	4	22	41	60								
*SFBCC5000153MX	15nF	A/K			-	-	7	25	44	62								
*SFBCC5000223MX	22nF				-	-	10	29	46	65								
SFBCC5000333MX	33nF				-	-	13	33	48	68								
*SFBCC2000473MX	47nF		200	500	-	1	16	35	50	70								
SFBCC2000683MX	68nF		200	300	-	2	19	39	54	>70								
*SFBCC1000104MX	100nF		100	250	-	4	22	41	57	>70								
*SFBCC0500154MX	150nF		50	125	-	7	25	45	60	>70								

[#] Also rated for operation at 115Vac 400Hz. Self heating will occur - evaluation in situ recommended. * Recommended values. † Also available in COG/NPO.


Orderi	Ordering Information - SFBCC range											
SF	В	С	С	500	0102	M	X	0				
Туре	Case style	Thread	Electrical configuration	Voltage (dc)	Capacitance in picofarads (pF)	Tolerance	Dielectric	Hardware				
Syfer Filter	4.75mm Hex Head	8-32 UNC	C = C Filter	050 = 50V 100 = 100V 200 = 200V 500 = 500V	First digit is 0. Second and third digits are significant figures of capacitance code. The fourth digit is number of zeros following Example: 0101 = 100pF 0332 = 3300pF	M = ±20% Z = -20+80%	C = COG/NP0 X = X7R	0 = Without 1 = With				

Note: The addition of a 4-digit numerical suffix code can be used to denote changes to the standard part.

Options include for example: change of finish / alternative voltage rating / non-standard intermediate capacitance values / test requirements. Please refer specific requests to the factory.







et		
Electrical Details		
Electrical Configuration	L-C Filter	
Capacitance Measurement	@ 1000hr Point	
Current Rating	10A	THREAD
Insulation Resistance (IR)	$10G\Omega$ or 1000Ω F	1-C _
Temperature Rating	-55°C to +125°C	L-C _
Ferrite Inductance (Typical)	50nH	
Mechanical Details		
Head (A/F)	4.75mm (0.187")	
Nut A/F	6.35mm (0.250")	
Washer diameter	8mm (0.315")	
Mounting Torque	0.5Nm <i>(4.42lbf in)</i> m 0.25Nm <i>(2.21lbf in)</i> i	nax. if using nut max. into tapped hole
Mounting Hole Diameter	4.4mm ±0.1 (0.173"	' ±0.004")
Max. Panel Thickness	2.9mm (0.114")	
Weight (Typical)	1.2g (0.04oz)	
Finish	Silver plate on coppe	er undercoat

Product Code	Capacitance	Dielectric	Rated Voltage	DWV	Typical No-Load Insertion Loss (dB)																
Product Code	(±20%) UOS	Dielectric	(Vdc)	(Vdc)	0.01MHz	0.1MHz	1MHz	10MHz	100MHz	1GHz											
*SFBCL5000100ZC	10pF -20% / +80%				-	-	-	-	-	6											
SFBCL5000150ZC	15pF -20% / +80%				-	-	-	-	-	9											
SFBCL5000220ZC	22pF -20% / +80%				-	-	-	-	-	12											
SFBCL5000330ZC	33pF -20% / +80%				-	-	-	-	1	15											
*SFBCL5000470ZC	47pF -20% / +80%	C0G/NP0			-	-	-	-	2	19											
*SFBCL5000680MC	68pF	COG/NPO			-	-	-	-	4	20											
*SFBCL5000101MC	100pF				-	-	-	-	7	24											
SFBCL5000151MC	150pF				-	-	-	-	10	27											
*SFBCL5000221MC	220pF				-	-	-	-	12	30											
*SFBCL5000331MC	330pF				-	-	-	1	16	34											
*SFBCL5000471MX	470pF	†X7R	500#	750	-	-	-	2	19	38											
SFBCL5000681MX	680pF		1X/K 300#	750	-	-	-	3	22	41											
*SFBCL5000102MX	1.0nF				-	-	-	6	25	44											
SFBCL5000152MX	1.5nF															-	-	-	9	29	48
*SFBCL5000222MX	2.2nF															-	-	-	12	31	51
SFBCL5000332MX	3.3nF																		-	-	-
*SFBCL5000472MX	4.7nF						-	-	1	18	39	57									
SFBCL5000682MX	6.8nF				-	-	2	21	41	60											
*SFBCL5000103MX	10nF	X7R			-	-	4	23	43	63											
*SFBCL5000153MX	15nF	A/K			-	-	7	27	46	66											
*SFBCL5000223MX	22nF				-	-	10	30	48	68											
SFBCL5000333MX	33nF				-	-	13	34	50	70											
*SFBCL2000473MX	47nF		200	500	-	1	17	37	51	>70											
SFBCL2000683MX	68nF		200	500	-	2	20	40	55	>70											
*SFBCL1000104MX	100nF		100	250	-	4	22	44	60	>70											
*SFBCL0500154MX	150nF		50	125	-	7	25	47	62	>70											

Also rated for operation at 115Vac 400Hz. Self heating will occur - evaluation in situ recommended. * Recommended values. † Also available in COG/NPO.


Ordering Information - SFBCL range

SF	В	C	L	500	0102	M	X	0
Туре	Case style	Thread	Electrical configuration	Voltage (dc)	Capacitance in picofarads (pF)	Tolerance	Dielectric	Hardware
Syfer Filter	4.75mm Hex Head	8-32 UNC	L = L-C Filter	050 = 50V 100 = 100V 200 = 200V 500 = 500V	First digit is 0. Second and third digits are significant figures of capacitance code. The fourth digit is number of zeros following Example: 0101 = 100pF 0332 = 3300pF	M = ±20% Z = -20+80%	C = COG/NPO X = X7R	0 = Without 1 = With

Note: The addition of a 4-digit numerical suffix code can be used to denote changes to the standard part.

Options include for example: change of finish / alternative voltage rating / non-standard intermediate capacitance values / test requirements. Please refer specific requests to the factory.





Electrical Details		
Electrical Configuration	Pi Filter	
Capacitance Measurement	@ 1000hr Point	
Current Rating	10A	
Insulation Resistance (IR)	$10G\Omega$ or 1000Ω F	⊥ Pi ⊥
Temperature Rating	-55°C to +125°C	
Ferrite Inductance (Typical)	75nH	
Mechanical Details		
Head (A/F)	4.75mm (0.187")	
Nut A/F	6.35mm (0.250")	
Washer diameter	9.40mm (0.370")	
Mounting Torque	0.5Nm <i>(4.42lbf in)</i> m 0.25Nm <i>(2.21lbf in)</i> r	ax. if using nut max. into tapped hole
Mounting Hole Diameter	4.4mm ±0.1 (0.173"	'±0.004")
Max. Panel Thickness	2.9mm (0.114")	
Weight (Typical)	1.2g (0.04oz)	
Finish	Silver plate on coppe	r undercoat

Product Code	Capacitance	Dielectric	Rated Voltage	Voltage		Typical No-Load Insertion Loss (dB)									
	-20/+80%	2101000110	(Vdc)	(Vdc)	0.01MHz	0.1MHz	1MHz	10MHz	100MHz	1GHz					
*SFBCP5000200ZC	20pF				-	-	-	-	1	11					
SFBCP5000440ZC	44pF	COG/NPO				-	-	-	-	3	19				
SFBCP5000940ZC	94pF				-	-	-	-	6	25					
*SFBCP5000201ZC	200pF								-	-	-	-	11	33	
SFBCP5000441ZC	440pF		500#	750	-	-	-	2	18	45					
SFBCP5000941ZX	940pF					-	-	-	5	25	60				
*SFBCP5000202ZX	2nF						-	-	-	10	40	70			
SFBCP5000442ZX	4.4nF												-	-	1
*SFBCP5000942ZX	9.4nF	X7R			-	-	4	24	60	>70					
*SFBCP2000203ZX	20nF		200	500	-	-	9	28	70	>70					
*SFBCP1000443ZX	44nF		100	250	-	0	14	42	>70	>70					
*SFBCP0500943ZX	94nF		50	125	-	2	18	57	>70	>70					

[#] Also rated for operation at 115Vac 400Hz. Self heating will occur - evaluation in situ recommended. * Recommended values. † Also available in COG/NPO.

Orderi	Ordering Information - SFBCP range											
SF	В	С	P	050	0943	Z	X	0				
Туре	Case style	Thread	Electrical configuration	Voltage (dc)	Capacitance in picofarads (pF)	Tolerance	Dielectric	Hardware				
Syfer Filter	4.75mm Hex Head	8-32 UNC	P = Pi Filter	050 = 50V 100 = 100V 200 = 200V 500 = 500V	First digit is 0. Second and third digits are significant figures of capacitance code. The fourth digit is number of zeros following Example: 0201 = 200pF 0943 = 94000pF	Z = -20+80%	C = COG/NP0 X = X7R	0 = Without 1 = With				
	lote: The addition of a 4-digit numerical suffix code can be used to denote changes to the standard part. ptions include for example: change of finish / alternative voltage rating / non-standard intermediate capacitance values / test requirements. Please refer specific requests to the factory.											