imall

Chipsmall Limited consists of a professional team with an average of over 10 year of expertise in the distribution of electronic components. Based in Hongkong, we have already established firm and mutual-benefit business relationships with customers from, Europe, America and south Asia, supplying obsolete and hard-to-find components to meet their specific needs.

With the principle of "Quality Parts, Customers Priority, Honest Operation, and Considerate Service", our business mainly focus on the distribution of electronic components. Line cards we deal with include Microchip, ALPS, ROHM, Xilinx, Pulse, ON, Everlight and Freescale. Main products comprise IC, Modules, Potentiometer, IC Socket, Relay, Connector. Our parts cover such applications as commercial, industrial, and automotives areas.

We are looking forward to setting up business relationship with you and hope to provide you with the best service and solution. Let us make a better world for our industry!



Contact us

Tel: +86-755-8981 8866 Fax: +86-755-8427 6832 Email & Skype: info@chipsmall.com Web: www.chipsmall.com Address: A1208, Overseas Decoration Building, #122 Zhenhua RD., Futian, Shenzhen, China



LED Driver

Indoor 50w Compact Driver

Non-Dimming : SI-CU87250N1VW Dimming : SI-CU8725001WW



Constant Current LED Driver

Features & Benefits

• Output Current Range: 0.512~0.925 A (adjustable via R-set)

Max 50 W

-20 ~ +50 °C

0-10 V (Min. 3.5%)

FCC Part 15 Class B

120 ~ 277 Vac, 50/60 Hz

50,000 hours at tc < 70 °C

UL / cUL (UL 8750, UL Class 2)

Short Circuit, Over Voltage(Auto Recovery)

- Output Voltage Range: MAX 54 Vdc
- Output Power Range:
- Dimming Control:
- Input Voltage:
- Safety:
- EMI:
- Protections:
- t_a Range:
- Expected lifetime:
- Long lasting & high reliability
- Metal housing

Applications

• Indoor lighting





Table of Contents

1.	Characteristics	 3
2.	Typical Characteristics Graphs	 5
3.	Protection	 6
4.	Dimming Specification	 6
5.	Reliability & standard	 7
6.	Outline Drawing & Dimension	 8
7.	Label Structure	 8
8.	Packing Structure	 9
9.	Precautions in Handling & Use	 10

1. Characteristics

Article		Symbol	Specification Symbol				Note
		Symbol	Min.	Тур.	Max.	Unit	Note
INPUT SPECIFICATIONS							
Nominal Voltage		Vin	120		277	Vac	
Voltage Range			108		300	Vac	
Nominal Frequency		Fin		50 / 60		Hz	
Frequency Range			47		63	Hz	
lana di Orimant	At 120 Vac	lin			0.56	А	At full load
Input Current	At 277 Vac	lin			0.25	А	At full load
Total Harmonic Disto	ortion	THD			20	%	At 120-277 Vac
Power Factor		PF	0.9			-	At 120-277 Vac
Efficiency		η	87 87	88 89		%	At full load, 120 Vac, 60 Hz At full load, 277 Vac, 60 Hz
In-rush Current					30	Apk	NEMA410.
OUTPUT SPECIFIC	ATIONS						
Voltage Range		Vo	37		54	Vdc	70% of MAX power can meet PF,TH
Max. Voltage					60	Vdc	Open circuit, No-load protection
Current Range		lo	0.512		0.925	А	70% of MAX power can meet PF,TH
Line Regulation			-3		3	%	@120~277Vac
Load Regulation			-5		5	%	@120~277Vac, W/O dimming
Current Tolerance			-5		5	%	@120~277Vac, W/O dimming
Ripple Current					50%	%	$\frac{1}{\text{lavg}}$ (Ipeak – Iavg)X100%
Peak current					150%		Ipeak Iavg X100%
Nominal Power		Po			50	W	
Turn-on Delay Time		Td			1	s	@120Vac, W/O dimmer

1) PF, THD, FCC can meet the electrical performance from 70% of MA X power.


 ${\bf 2}$) Measured the unit is thermally stabilized after half an hour, Ta ${\bf 25^\circ\!C}.$

Articlo		Symbol		Specification			Note
Article		Symbol	Min.	Тур.	Max.	Unit	Note
DIMMING SPECIFICATIONS			3.5		100	%	@925mA
Dimming Control				0-10 V			See Dimming Specification section
ENVIRONMENTAL SPECIFICATIONS							
Ambient Temperature		ta	-20		50	°C	
Case Temperature		tc			84	°C	Type TL 84 °C / 72 °C
Storage Temperature		ts	-40		85	°C	
Ambient Humidity			10		90	%	Not condensing
Surge Transient	L/N				±2.5	kV	ANSI/IEEE C62.41 100KHz Ring Wave
Protection	LN / GND				±2.5	kV	ANSWEEL CO2.41 TOURHZ RING WAVE
IP Rating				20		-	Suitable for indoor environment
Expected Lifetime (e-cap)			50,000			h	At tc < 70 $^{\circ}$ C, full load, 120-277 Vac
MTBF			500,000			h	Ta=25°C, Telcordia SR-332, Method I
Dimensions		L x W x H		165 x 43 x 32		mm	
Net Weight				195		g	


2. Typical Characteristics Graphs

a) Operating Window


c) Power Factor vs. Load




b) Efficiency vs. Load




d) Total Harmonic Distortion vs. Load








e) Life time








g) R-set Table

Rset (Kohm)	Iout(A)	Iout(%)
0.00	0.5115	55.3
0.10	0.5174	55.9
0.30	0.5286	57.1
0.42	0.5351	57.8
0.65	0.5467	59.1
1.00	0.5633	60.9
1.43	0.5818	62.9
1.87	0.5989	64.7
2.00	0.6036	65.3
2.32	0.6147	66.4
2.70	0.6268	67.8
3.48	0.6491	70.2
3.92	0.6602	71.4
4.64	0.6766	73.1
5.60	0.6956	75.2
6.80	0.7156	77.4
7.50	0.7257	78.5
8.87	0.7429	80.3
10.00	0.7551	81.6
11.50	0.7689	83.1
13.70	0.7855	84.9
16.20	0.8006	86.5
18.20	0.8105	87.6
20.50	0.8201	88.7
24.00	0.8319	89.9
27.40	0.8412	90.9
32.40	0.8518	92.1
39.00	0.8624	93.2
47.50	0.8722	94.3
60.40	0.8823	95.4
80.60	0.8922	96.5
120.00	0.9025	97.6
205.00	0.9116	98.6
Open	0.9252	100.0



3. Protection

a) Output Short Circuit Protection

The unit is protected when output is short thus avoiding safety hazard, shock hazard and damage to the unit. After the short circuit fault condition is removed, the unit will enter the auto-recovery mode.

b) Output Over Voltage Protection

When no load condition occurs, the unit will clamp output voltage to the OVP Voltage avoiding damage to the unit. After the load is connected, the unit will enter the auto-recovery mode.


The OVP Voltage varies according to the Rset resistor value (see below curve and table) and under 60 V.

4. Diming Specification

1) Control Type : 0-10V

The unit has Analog Dimming (AD) function, using 0-10 Vdc. The typical dimming curve is shown below. The dimming curve is tested with LED electronic load Chroma 63115A/6312A. Rd coefficient is 0.1.

	Symbol	Unit	Min	Тур	Max	Remark
	Range	V	0		10	
	Dim off	V	0		0.5	
Dimming	Dim. Min.	V	0.6	1	1.6	Hysteresis to Dim > 0.8V
	Dim Max.	V	9.2		10	



5. Reliability & Standards

Test Items and Conditions


Test Item		Specification	Condition
Leakage Current		< 0.7 mA	305Vac, IEC 60598-1
Earth Continuity		< 0.5 Ω	IEC 61347-2-13
Hi-Pot	Input – Output	3750 Vac, 60 s, cut-off current 10 mA	100 % tested in production line
ΠΙ-ΡΟΙ	Input – F.G	1857 Vac, 60 s, cut-off current 10 mA	100 % tested in production line
	Output – F.G	1500 Vac, 60 s, cut-off current 10 mA	100 % tested in production line
Insulation Resistance	Input – Output	500 Vdc, 60 s, insulation resistance 10 $\text{M}\Omega$	100 % tested in production line
Surge	L/N	±2.5 kV	ANSI/IEEE C62.41 100KHz Ring
Suige	L-N / GND	±2.5 kV	Wave
ESD	Contact	±4 kV	EN61547(IEC 61000-4-2)
	Air	±8 kV	LN01347 (ILO 01000-4-2)

Safety, EMI and EMC

International Standard	Certification
UL Safety Standards (Class 2 Output)	UL8750
EMC	Comply with FCC Part 15 Class B
Harmonic current emissions: Class C	Comply with IEC/EN 61000-3-2
Electrostatic Discharge (ESD): Contact 4kV, Air 8kV	Comply with IEC/EN 61000-4-2
Radio-frequency Electromagnetic Fields	Comply with IEC/EN 61000-4-3
Electrical Fast Transients (EFT)	Comply with IEC/EN 61000-4-4
Surges: Differential 1kV, Common 2kV	Comply with IEC/EN 61000-4-5
Injected Currents, Conducted disturbances induced by Radio-Frequency fields	Comply with IEC/EN 61000-4-6
Voltage Dips and Short Interruptions (Class B)	Comply with IEC/EN 61000-4-11

6. Outline Drawing & Dimension

Dimension : 165 (L) x 43 (W) x 32 (H) Unit: mm




7. Label Structure

 L 0.75 ~ 1.25 □ N M 	P/N: SX050G002LD INPUT : 120 – 277V ~ 0.56A 50/60Hz OUTPUT : 37 – 54V/0.925A 50W max CONSTANT CURRENT , SELV POWER FACTOR (PF) : > 0.9 DIMMER INTERFACE : 0 – 10V TA : 50°C	- 10 . 04 0	UNG Type TL 84/72°C 0.5~1.25 □ LED+ AD+ AD- Rset Rset	0-10 Dimming
 L 0.75 ~ 1.250 ≥ N ⊕ 	LED POWER SUPPLY MODEL: SI-CU87250N1WW P/N: SX050G001ND INPUT : 120 – 277V ~ 0.56A 50/60Hz OUTPUT: 37 – 54V/0.925A 50W max CONSTANT CURRENT , SELV POWER FACTOR (PF) : > 0.9 TA : 50°C MADE in China Class 2 Power Unit Ver.1.1	s a k c : 84°C E470825 C S b us 9mm wire prepartion 0.5 - 1.25mm ² /AWG 16 - 20	UNG Type TL 84/72°C LED+ 0.5~1.25 □ LED- Rset Rset	Non Dimming

8. Packing Structure

Dacking material	May guartity (age)	Dimension (mm)			
Packing material	Max. quantity (pcs)	Length	Width	Height	
Outer Box	24	400	300	170	
Pallet	960 (40 outer boxes)	1,200	1,000	1110	



9. Precautions in Handling & Use

- 1) To prevent the LED Driver from any defect, please handle and store it with care
 - Do not drop or give shock
 - Do not store in very humid location or at extreme temperature
 - Do not open or disassemble the product
- 2) Static electricity or surge voltage may damage the components inside LED Driver, as such please observe proper antielectrostatic working process
 - People handing the Driver should be well grounded (e.g. using ESD wrist band) and wear anti-static working clothes and gloves
 - All related devices and instruments in the production line should be well grounded (e.g. working table, measuring equipment, assembly jigs)
- 3) Observe the correct polarity of output terminal
- 4) Avoid input voltage exceeds the maximum rating, which will cause damage to the circuit and result in malfunction

Legal and additional information.

About Samsung Electronics Co., Ltd.

Samsung Electronics Co., Ltd. inspires the world and shapes the future with transformative ideas and technologies, redefining the worlds of TVs, smartphones, wearable devices, tablets, cameras, digital appliances, printers, medical equipment, network systems and semiconductors. We are also leading in the Internet of Things space through, among others, our Digital Health and Smart Home initiatives. We employ 307,000 people across 84 countries. To discover more, please visit our official website at www.samsung.com and our official blog at global.samsungtomorrow.com.

Copyright © 2015 Samsung Electronics Co., Ltd. All rights reserved. Samsung is a registered trademark of Samsung Electronics Co., Ltd. Specifications and designs are subject to change without notice. Non-metric weights and measurements are approximate. All data were deemed correct at time of creation. Samsung is not liable for errors or omissions. All brand, product, service names and logos are trademarks and/or registered trademarks of their respective owners and are hereby recognized and acknowledged.

Samsung Electronics Co., Ltd. 95, Samsung 2-ro Giheung-gu Yongin-si, Gyeonggi-do, 446-711 KOREA

www.samsungled.com

