imall

Chipsmall Limited consists of a professional team with an average of over 10 year of expertise in the distribution of electronic components. Based in Hongkong, we have already established firm and mutual-benefit business relationships with customers from, Europe, America and south Asia, supplying obsolete and hard-to-find components to meet their specific needs.

With the principle of "Quality Parts, Customers Priority, Honest Operation, and Considerate Service", our business mainly focus on the distribution of electronic components. Line cards we deal with include Microchip, ALPS, ROHM, Xilinx, Pulse, ON, Everlight and Freescale. Main products comprise IC, Modules, Potentiometer, IC Socket, Relay, Connector. Our parts cover such applications as commercial, industrial, and automotives areas.

We are looking forward to setting up business relationship with you and hope to provide you with the best service and solution. Let us make a better world for our industry!



Contact us


Tel: +86-755-8981 8866 Fax: +86-755-8427 6832 Email & Skype: info@chipsmall.com Web: www.chipsmall.com Address: A1208, Overseas Decoration Building, #122 Zhenhua RD., Futian, Shenzhen, China



Honeywell

Bipolar, Latching, or Unipolar Digital Hall-effect Sensor ICs: SS400 Series, SS500 Series

32320997 Issue A



DESCRIPTION

The SS400 Series and SS500 Series are small, versatile, digital Hall-effect devices that are operated by the magnetic field from a permanent magnet or an electromagnet. They are designed to respond to alternating North and South poles, or to a South pole only. They are available in bipolar, latching or unipolar magnetics. On-board regulation provides stable operation over a 3.8 Vdc to 30 Vdc supply voltage range. These sensors are capable of continuous 20 mA sinking output and may be cycled as high as 50 mA max. The 3.8 V capability allows for use in many potential low voltage applications. The digital, open collector sinking-type output is easily interfaced with a wide variety of electronic circuits. To provide reliable products and consistent quality, the SS400 Series products are tested at both 25 °C [75 °F] and 125 °C [257 °F]. All catalog listings in the SS400 Series are qualified for operation up to 150 °C [302 °F].

For design flexibility, these product are available in the following package styles:

- SS400 Series:
 - **SS4XX:** 14,5 mm [0.57 in] straight standard leads, bulk pack, 1000 units/bag
 - **SS4XX-L:** 18,7 mm [0.74 in] straight long leads, bulk pack, 1000 units/bag
 - **SS4XX-T3:** 14,5 mm [0.57 in] straight standard leads, ammopack tape-in-box, 5000 units/box
 - **SS4XX-R:** 3,30 [0.130 in] straight reduced leads, bulk pack, 1000 units/bag
 - **SS4XX-SP:** 3,18 [0.125 in] surface mount, pocket tape and reel, 1000 units/reel
- **SS500 Series:** SOT-89B, pocket tape and reel, 1000 units/ reel

FEATURES

- Quad Hall IC design minimizes mechanical stress effects
- Temperature-compensated magnetics help provide stable operation over a wide temperature range of -40 °C to 150 °C [-40 °F to 302 °F] (SS400 Series) and -50 °C to 150 °C [-58 °F to 320 °F] (SS500 Series)
- Broad inclusive supply voltage capability from 3.8 Vdc to 30 Vdc for application flexibility
- Digital, open collector sinking output for easy interfacing with a variety of common electronic circuits
- High sensitivity versions available for potential applications requiring high accuracy or wide gaps
- Bipolar, latching or unipolar magnetics

POTENTIAL APPLICATIONS

- Industrial: Speed and RPM (revolutions per minute) sensing, tachometer, counter pickup, flow-rate sensing, brushless dc (direct current) motor commutation, motor and fan control, robotics control
- Transportation: Speed and RPM (revolutions per minute) sensing, tachometer, counter pickup, motor and fan control, electric window lift, convertible roof position
- Medical: Motor assemblies, medication dispensing control

PORTFOLIO

Other bipolar, latching and unipolar digital Hall-effect sensor ICs include:

- SS360NT, SS360ST, SS360ST-10K, SS460S, SS460S-T2
- VF360NT, VF360ST, VF460S
- SS361RT, SS461R
- SS361CT, SS461C
- SS340RT, SS440R Series
- SS360PT, SS460P, SS460P-T2
- SS311PT, SS411P

SS400 Series, SS500 Series

Characteristic	Symbol	Condition	Min.	Тур.	Max.	Unit
Supply voltage ¹	Vs	_	3.8	_	30	Vdc
Rated sinking current (Isink)	I _{sink}	_	_	20	_	mA
Current consumption:						
On:						
SS400 Series		V_s = 30 Vdc, I_{sink} = 20 mA, -40 °C < T < 150 °C, B > operate max.	-	_	10.0	
SS500 Series	_	V _s = 30 Vdc, -40 °C < T < 150 °C, B > operate max.	_	_	10.0	mA
Off:						
SS400 Series		$V_s = 30$ Vdc, $I_{sink} = 20$ mA, -40 °C < T < 150 °C, B > operate max.	_	_	9.0	
SS500 Series		V _s = 30 Vdc, I _{sink} = 20 mA, -40 °C < T < 150 °C, B > release min.	_	_	10.0	
Vsat:						
SS400 Series	_	$V_s = 3.8$ Vdc, $I_{sink} = 20$ mA, B > operate max.	-	_	0.4	V
SS500 Series		$V_s = 3.8$ Vdc, B > operate max.	_	_	0.4	
Output leakage current:						
SS400 Series	-	Vs = 24 V, Vout = 30 V, B < release min.	-	—	0.4	uA
SS500 Series		_	_	—	10.0	
Output switching time:						
rise	-	V_{s} = 12 V, R_{L} = 1.6 kOhm, C_{L} = 20 pF, T = 25 °C [77 °F]	-	—	1.5	μs
fall		V_s = 12 V, R _L = 1.6 kOhm, C _L = 20 pF, T = 25 °C [77 °F]	_	—	1.5	
Operating temperature:						
SS400 Series	Т	-	-40 [-40]	—	150 [302]	℃[°F]
SS500 Series		-	-50 [-58]	_	150 [302	
Storage temperature:						
SS400 Series	Ts	-	-50 [-58]	—	150 [302]	°C [°F]
SS500 Series		-	-65 [-85]	—	150 [302]	
Soldering temp. and time:						
SS400 Series	-	wave soldering process: 250 °C to 260 °C [482 °F to 500 °F] for 3	3 s max.			

Table 1. Electrical and Environmental Specifications (Applies to both SS400 series and 500 Series, unless otherwise noted.

¹For supply voltages above 24 Vdc, a capacitor may be needed between the output and supply pins to ensure proper operation.

NOTICE

SS500 Series

These Hall-effect sensor ICs may have an initial output in either the ON or OFF state if powered up with an applied magnetic field in the differential zone (applied magnetic field >Brp and <Bop). Honeywell recommends allowing 10 µs after supply voltage has reached 5 V for the output voltage to stabilize.

NOTICE

The magnetic field strength (Gauss) required to cause the switch to change state (operate and release) will be as specified in the magnetic characteristics. To test the switch against the specified limits, the switch must be placed in a uniform magnetic field.

infrared reflow process: peak temperature 245 °C [473 °F] for 10 s max.



SS400 Series, SS500 Series

Table 2. Absolute Maximum Specifications

Characteristic	Symbol	Min.	Тур.	Max.	Unit	
Supply voltage	Vs	-1	_	30	V	
Applied output voltage:						
SS400 Series	V _{out}	-0.5	_	30	V	
SS500 Series (off)		_	_	30		
Output current:						
$V_s = -1$ Vdc to 24 Vdc		_	_	50		
V _s = 24 Vdcto 25 Vdc		_	_	37		
$V_s = 25$ Vdc to 26 Vdc		_	_	33		
$V_s = 26$ Vdc to 27 Vdc	Isink	_	_	28	mA	
$V_s = 27$ Vdc to 28 Vdc		_	_	24		
$V_s = 28$ Vdc to 29 Vdc		_	_	19		
$V_{\rm s}$ = 29 Vdc to 30 Vdc		_	_	15		
Magnetic flux	_	_	_	no limit	Gauss	

NOTICE

Absolute maximum ratings are the extreme limits the device will momentarily withstand without damage to the device. Electrical and mechanical characteristics are not guaranteed if the rated voltage and/or currents are exceeded, nor will the device necessarily operate at absolute maximum ratings.

Figure 1. Circuit Diagram





Figure 2. Magnetic Activation




SS400 Series, SS500 Series

Table 3. Magnetic Specifications

		Magnetic Characteristic (Guass)													
ture	Operating Characteristic	Bipolar				Unipolar					Latching				
Temperature		SS411	SS511AT	SS413	SS513AT	SS441	SS541AT	SS443	SS543AT	SS449	SS549AT	SS461	SS561AT	SS466	SS566AT
-40 °C [-40 °F]	operate: minimum maximum release: minimum maximum differential (min.)	NS 70 -70 NS 15		NS 140 -140 NS 20		50 135 20 120 15		110 215 80 190 25		285 435 210 360 30		5 110 -110 -5 50	 100 -100 -5 50	20 -2 -10	00 00 00 00 00
0 °C [0 °F]	operate: minimum maximum release: minimum maximum differential (min.)	NS 65 -65 NS 15		N 14 -1 ² N 21	40 5	53 117 20 99 15		110 190 80 165 25		305 400 230 325 30		5 90 -90 -5 50		100 185 -185 -100 200	
25 °C [77 °F]	operate: minimum maximum release: minimum maximum differential (min.)	NS 60 -60 NS 15		NS 140 -140 NS 20		55 115 20 95 20		110 180 75 155 25		310 390 235 315 30		10 85 -85 -10 50		18 -11 -11	00 30 80 00 00
85 °C [185 °F]	operate: minimum maximum release: minimum maximum differential (min.)	NS 60 -60 NS 12		N 14 -14 N 20	40 40 S	12 1: 10	45 120 15 105 15		90 180 70 165 15		290 – 400 400 215 315 325 – 30 30		10 85 -85 -10 50		5 30 80 95 90
125 °C [257 °F]	operate: minimum maximum release: minimum maximum differential (min.)	NS 65 -65 NS 12		14 -14 N	NS 140 -140 NS 20		40 123 15 115 8		80 190 60 180 10		270 410290 400200 340215 325 30		5 100 -100 -5 50		0 30 80 30 50
150 °C [302 °F]	operate: minimum maximum release: minimum maximum differential (min.)	NS 70 -70 NS 10		N 14 -14 N 21	40 40 S	35 125 10 120 5		65 200 55 195 5		260 420 185 345 30		5 110 -110 -5 50		18 -11 -7	0 35 85 70 40

SS400 Series, SS500 Series





SS400 Series, SS500 Series

Figure 4. Circuit Diagrams







Figure 5. SS400 Series Flat TO-92-Style Mounting and Dimensional Drawings (For reference only: mm/[in].)






SS400 Series, SS500 Series

Figure 5. SS400 Series Flat TO-92-Style Mounting and Dimensional Drawings (continued)




F. 3,18 [0.125 in] Surface Mount Sensor IC, Pocket Tape and Reel



SS400 Series, SS500 Series

Figure 6. SS500 Series Mounting and Dimensional Drawings (For reference only: mm/[in].)

SOT-89B Sensor IC, Pocket Tape and Reel



SS400 Series, SS500 Series

Catalog Listin	g Description	SS4XX	SS4XX-L	SS4XX-T3
SS4XX: 14,5 m	nm [0.57 in] straight standard leads, bulk pack, 1000 units/bag		Constant of	
SS411A	Bipolar		T-T-T	-
SS413A	Bipolar			
SS441A	Unipolar			
SS443A	Unipolar			
SS449A	Unipolar			
SS461A	Latching			111
SS466A	Latching			
SS4XX-L: 18,7	7 mm [0.74 in] straight long leads, bulk pack, 1000 units/bag			
SS461A-L	Latching			
SS4XX-T3: 14 5000 units/bc	,5 mm [0.57 in] straight standard leads, ammopack tape-in-box, x			
SS443A-T3	Unipolar			
SS449A-T3	Unipolar			
SS4XX-R: 3,3	0 [0.130 in] straight reduced leads, bulk pack, 1000 units/bag			
SS411A-R	Bipolar			
SS4XX-S: 3,18	3 [0.125 in] surface mount, bulk pack	SS4XX-R	SS4XX-S	SS4XX-SP
SS411A-S	Bipolar	- All and a		• •
SS443A-S	Unipolar	TTT	111	1.00016
SS449A-S	Unipolar		111	
SS4XX-SP: 3,	18 [0.125 in] surface mount, pocket tape and reel, 1000 units/reel			
SS443A-SP	Unipolar			
SS449A-SP	Unipolar			

Table 4. Order Guide for the SS400 Series (Flat TO-92-Style)

Table 5. Order Guide for the SS500 Series (SOT-89B, Pocket Tape and Reel, 1000 Units/Reel)

Catalog Listing	Description
SS511AT	Bipolar
SS513AT	Bipolar
SS541AT	Unipolar
SS543AT	Unipolar
SS549AT	Unipolar
SS561AT	Latching
SS566AT	Latching



ADDITIONAL INFORMATION

The following associated literature is available on the Honeywell web site at sensing.honeywell.com:

- Product Line Guide
- Product Range Guide
- Selection Guides
- Application-specific Information

WARNING PERSONAL INJURY

DO NOT USE these products as safety or emergency stop devices or in any other application where failure of the product could result in personal injury.

Failure to comply with these instructions could result in death or serious injury.

WARNING MISUSE OF DOCUMENTATION

- The information presented in this datasheet is for reference only. Do not use this document as a product installation guide.
- Complete installation, operation, and maintenance information is provided in the instructions supplied with each product.

Failure to comply with these instructions could result in death or serious injury.

Warranty/Remedy

Honeywell warrants goods of its manufacture as being free of defective materials and faulty workmanship. Honeywell's standard product warranty applies unless agreed to otherwise by Honeywell in writing; please refer to your order acknowledgement or consult your local sales office for specific warranty details. If warranted goods are returned to Honeywell during the period of coverage, Honeywell will repair or replace, at its option, without charge those items it finds defective. **The foregoing is buyer's sole remedy and is in lieu of all other warranties, expressed or implied, including those of merchantability and fitness for a particular purpose. In no event shall Honeywell be liable for consequential, special, or indirect damages.**

While Honeywell may provide application assistance personally, through our literature and the Honeywell web site, it is up to the customer to determine the suitability of the product in the application.

Specifications may change without notice. The information we supply is believed to be accurate and reliable as of this printing. However, we assume no responsibility for its use.

Find out more

Honeywell serves its customers through a worldwide network of sales offices, representatives and distributors. For application assistance, current specifications, pricing or name of the nearest Authorized Distributor, contact your local sales office.

To learn more about Honeywell Sensing and Productivity Solutions' products, call +1-815-235-6847 or 1-800-537-6945, visit sensing.honeywell.com, or e-mail inquiries to info.sc@honeywell.com

Honeywell Sensing and Productivity Solutions

9680 Old Bailes Road Fort Mill, SC 29707 honeywell.com

32320997-A-EN IL50 GLO June 2016 © 2016 Honeywell International Inc. All rights reserved.