



Chipsmall Limited consists of a professional team with an average of over 10 year of expertise in the distribution of electronic components. Based in Hongkong, we have already established firm and mutual-benefit business relationships with customers from,Europe,America and south Asia,supplying obsolete and hard-to-find components to meet their specific needs.

With the principle of "Quality Parts,Customers Priority,Honest Operation,and Considerate Service",our business mainly focus on the distribution of electronic components. Line cards we deal with include Microchip,ALPS,ROHM,Xilinx,Pulse,ON,Everlight and Freescale. Main products comprise IC,Modules,Potentiometer,IC Socket,Relay,Connector.Our parts cover such applications as commercial,industrial, and automotives areas.

We are looking forward to setting up business relationship with you and hope to provide you with the best service and solution. Let us make a better world for our industry!



Contact us

Tel: +86-755-8981 8866 Fax: +86-755-8427 6832

Email & Skype: info@chipsmall.com Web: www.chipsmall.com

Address: A1208, Overseas Decoration Building, #122 Zhenhua RD., Futian, Shenzhen, China



18kVA 18kW 4U Step-Down Isolation Transformer - Converts 208/240V 60Hz (Source) to 120/240V split phase (Load)

MODEL NUMBER: **SU20KXFMRT4U**



Description

Tripp Lite's SU20KXFMRT4U step-down, isolation transformer converts 208 or 240V input from any 60Hz generator, utility or UPS high voltage source to 240/120V output. 208 or 240V hardwire input connection and hardwire 240/120V output. Supports 4U rackmount installation in 4 post racks with included brackets. Supports upright tower installation with 2-9USTAND.

Features

- Step-down/isolation transformer converts 60Hz high voltage 208 or 240V input from generator, utility or UPS to 120/240V split phase output
- 18kW watt power handling capacity with 240V input (output de-rates to 16kW with 208V input)
- Hardwire input and output connections
- Included mounting accessories support 4U installation in 4 post rack enclosures

Specifications

OVERVIEW	
UPC Code	037332176608
Accessories Type	Isolation Transformer
OUTPUT	
Output Capacity Details	Output capacity with 240V input is 18kVA / 18kW / 18,000 watts; Output capacity de-rates to 16kVA / 16kW / 16,000 watts with 208V input

Highlights

- 18kVA / 18kW / 18,000 watt step-down isolation transformer converts 208 or 240V 60Hz to 120/240V split phase output
- Supports hardwire input and output
- Ideal means of converting UPS, utility, generator or other 208/240V input to 120/240V split phase
- Supports 4U rackmount installation

Package Includes

- SU20KXFMRT4U step-down, isolation transformer
- 4 post rackmount accessories
- Owner's manual with warranty information



Tripp Lite
1111 W. 35th Street
Chicago, IL 60609 USA
Telephone: 773.869.1234
www.tripplite.com

Frequency Compatibility	60 Hz
Output (VA)	18000
Output (Watts)	18000
Output Nominal Voltage	120, 240V AC
INPUT	
Nominal Input Voltage(s) Supported	208V AC; 240V AC
Maximum Input Amps	77
Input Connection Type	Hardwire
Voltage Compatibility (VAC)	208; 240
PHYSICAL	
Shipping Dimensions (hwd / in.)	12.50 x 23.00 x 34.50
Shipping Dimensions (hwd / cm)	31.75 x 58.42 x 87.63
Shipping Weight (lbs.)	319.70
Shipping Weight (kg)	145.01
Unit Dimensions (hwd / in.)	7 x 17.5 x 29.32
Unit Dimensions (hwd / cm)	17.78 x 44.45 x 74.47
Unit Weight (lbs.)	281.09
Unit Weight (kg)	127.50
Material of Construction	Steel
Form Factors Supported	Rack/Tower (2U)
ENVIRONMENTAL	
Relative Humidity	0-95% (non-condensing)
CERTIFICATIONS	
Certifications	Tested to UL1778, CSA, RoHS
WARRANTY	
Product Warranty Period (Worldwide)	2-year limited warranty

© 2018 Tripp Lite. All rights reserved. All product and company names are trademarks or registered trademarks of their respective holders. Use of them does not imply any affiliation with or endorsement by them. Tripp Lite has a policy of continuous improvement. Specifications are subject to change without notice. Tripp Lite uses primary and third-party agencies to test its products for compliance with standards. See a list of Tripp Lite's testing agencies: <https://www.tripplite.com/products/product-certification-agencies>