mail

Chipsmall Limited consists of a professional team with an average of over 10 year of expertise in the distribution of electronic components. Based in Hongkong, we have already established firm and mutual-benefit business relationships with customers from, Europe, America and south Asia, supplying obsolete and hard-to-find components to meet their specific needs.

With the principle of "Quality Parts, Customers Priority, Honest Operation, and Considerate Service", our business mainly focus on the distribution of electronic components. Line cards we deal with include Microchip, ALPS, ROHM, Xilinx, Pulse, ON, Everlight and Freescale. Main products comprise IC, Modules, Potentiometer, IC Socket, Relay, Connector. Our parts cover such applications as commercial, industrial, and automotives areas.

We are looking forward to setting up business relationship with you and hope to provide you with the best service and solution. Let us make a better world for our industry!



Contact us

Tel: +86-755-8981 8866 Fax: +86-755-8427 6832 Email & Skype: info@chipsmall.com Web: www.chipsmall.com Address: A1208, Overseas Decoration Building, #122 Zhenhua RD., Futian, Shenzhen, China





Specification

LC/UPC Receptacle XFP

Optical Transceiver Module

10 Gigabit Ethernet 10GBASE-ER



Ordering Information

$TAS - X \times US5 - KA6$

Operating Case Temperature

| Model Name | Voltage | Category | Device type | Interface | Temperature | Distance |
|---------------|---------|-----------|-------------|-------------|---------------|----------|
| TAS-X5US5-KA6 | | | | | -5°C ~ +70°C | |
| TAS-X1US5-KA6 | 3.3V | With DDMI | 1550 nm EML | AC-AC / TTL | -0°C ~ +70°C | 40 km |
| TAS-X2US5-KA6 | | | | | -40°C ~ +85°C | |

Formerica OptoElectronics Inc.



Features

- > STM64 or 10GBase ER/EW application
- > Supports Data rate 9.95 ~ 11.3 Gbps
- > Up to 40km transmission distance over SMF
- > 1550nm DFB Laser transmitter
- > 1550nm receiver with PIN-TIA
- > 2-wire interface for integrated digital diagnostic Monitoring
- > Operation case temperature -40~85°C for industrial and -5~70°C for commercial
- Single +3.3V power supply
- > XFP MAS package with LC/UPC receptacle optical interface
- RoHS-10 compliance



Pin Assignment and Pin Description



Pin Definitions

| PIN | Logic | Symbol | Name/Description | | |
|-----|-----------|-----------|--|---|--|
| 1 | | GND | Ground | | |
| 2 | | VEE5 | Optional -5.2V power supply, not in use | | |
| 3 | LVTLL-I | Mod DeSel | Module Deselect; when held low allows module to | | |
| | | Mod_Boool | respond 2-wire serial interface | | |
| 1 | | Intorrunt | Indicates presence of an important condition which | 2 | |
| 4 | | interrupt | can be read over the 2-wire serial interface | ۷ | |
| 5 | LVTLL-I | TX_DIS | Transmitter Disable; turn off transmitter laser output | | |
| 6 | | VCC5 | +5V power supply, not in use | 3 | |
| 7 | | GND | Ground | | |
| 8 | | VCC3 | +3.3V power supply | | |
| 9 | | VCC3 | +3.3V power supply | | |
| 10 | LVTTL-I/O | SCL | 2-wire serial interface clock | 2 | |
| 11 | LVTTL-I/O | SDA | 2-wire serial interface data | 2 | |
| 10 | | Mad Aba | Indicates module is not present. ground in the | | |
| 12 | | | module | ۷ | |

Formerica OptoElectronics Inc.

5F-11, No.38, Taiyuan St.,Zhubei City, Hsinchu County 30265, Taiwan Ph: +886-3-5600286 Fax: +886-3-5600239 www.formericaoe.com



| 13 | LVTTL-O | Mod_NR | Module not ready, indicating module operational fault | 2 | | |
|----|---------|---|---|---|--|--|
| 14 | LVTTL-O | RX_LOS | Receiver loss of signal indicator | | | |
| 15 | | GND | Ground | 1 | | |
| 16 | | GND | Ground | | | |
| 17 | CML-O | RD- | Receiver Inverted Data Output | | | |
| 18 | CML-O | RD+ | Receiver Non-Inverted Data Output | | | |
| 19 | | GND | Ground | | | |
| 20 | | VCC2 | +1.8V power supply, not in use | | | |
| | | | Power down; when high, requires the module to | | | |
| | | | limit power consumption to 1.5w or below ,2-wire | | | |
| | | | serial interface must be functional in the low power | | | |
| 21 | LVTTL-I | P_Down/RST | mode | | | |
| | | Reset; the falling edge initiates a complete reset of | | | | |
| | | | the module including the 2-wire Serial interface, | | | |
| | | | equivalent to a power cycle | | | |
| 22 | | VCC2 | +1.8V power supply, not in use | | | |
| 23 | | GND | Ground | 1 | | |
| | | | Reference clock non-inverted input, ac coupled on | | | |
| 24 | PECL-I | RefCLK+ | the host board, not in use | 3 | | |
| | | | Reference clock inverted input, ac coupled on the | 3 | | |
| 25 | PECL-I | RefCLK- | host board, not in use | | | |
| 26 | | GND | Ground | 1 | | |
| 27 | | GND | Ground | 1 | | |
| 28 | CML-I | TD- | Transmitter inverted data input | | | |
| 29 | CML-I | TD+ | Transmitter non-inverted data input | | | |
| 30 | | GND | Ground | 1 | | |

Notes:

- 1. Module ground pins GND are isolated from the module case and chassis ground within the module.
- 2. Shall be pulled up with 4.7K-10Kohms to a voltage between 3.15V and 3.45V on the host board.
- 3. Not connected internally.

Formerica OptoElectronics Inc.



Absolute Maximum Ratings

It has to be noted that the operation in excess of any individual absolute maximum ratings might cause permanent damage to this module.

| Parameters | Symbol | Min. | Max. | Unit | |
|----------------------------|--------|------|------|------|--|
| Power Supply Voltage | Vcc | 3.15 | 3.45 | V | |
| Power Dissipation | | | 2.5 | W | |
| Storage Temperature | Тс | -40 | 85 | О° | |
| Operating Case Temperature | То | -5 | 70 | • | |
| | TC | -40 | 85 | | |



Optical Characteristics

The following optical characteristics are defined over the Recommended Operating Environment unless otherwise specified.

| Parameter | Symbol | Min. | Тур. | Max | Unit | Notes |
|--|------------|----------------------|------|------|------|-------|
| Operating Reach, SMF | | | | 40 | Km | |
| | Transmitte | er | | | | |
| Center Wavelength | λt | 1530 | 1550 | 1570 | nm | |
| Spectral Width (-20dB) | | | | 1 | nm | |
| Side Mode Suppression Ratio (SMSR) | | 30 | | | dB | |
| Average Optical Power | Pavg | 0 | | 4 | dBm | |
| Transmitter and dispersion penalty (max) | TDP | | | 2 | dB | 3 |
| Optical Return Loss Tolerance | | -12 | | | dB | |
| Average launch power of Off transmitter | Poff | | | -45 | dBm | |
| Extinction Ratio | ER | 8.2 | | | dB | |
| Transmitter Mask (PRBS2 ³¹ -1@9.95G) | | Compliant With ITU-T | | | | |
| | Receiver | | | | | |
| Center Wavelength | λr | 1270 | 1550 | 1610 | nm | |
| Sensitivity (PRBS2 ³¹ -1@9.95G, BER<10 ⁻ ¹²) | | | | -16 | dBm | |
| Overload (PRBS2 ³¹ -1@9.95G, BER<10 ⁻¹²) | | 0.5 | | | dBm | |
| Los Assert | LosA | -30 | | | dBm | |
| Los Dessert | LosD | | | -18 | dBm | |
| Los Hysteresis | LosH | 0.5 | | | dB | |

Note:

- 1. Average optical power shall be measured using the methods specified in TIA/EIA-455-95.
- 2. Receiver sensitivity is informative. Stressed receiver sensitivity shall be measured with conformance test signal for BER =1x 10^{-12} .
- **3.** Path penalty is intended as the power penalty of the interface between back-to-back and the maximum applied dispersion.



Electrical Characteristics

The following electrical characteristics are defined over the Recommended Operating Environment unless otherwise specified.

| Parameter | Symbol | Min. | Typical | Max | Unit | Notes |
|--------------------------------------|--------|-------|---------|---------|------|-------|
| Data Rate | | 9.953 | 9.953 | 11.3 | Gbps | |
| Data Input Swing Differential/TX | | 120 | | 820 | mV | |
| Data Output Swing Differential/RX | | 340 | | 850 | mV | |
| Date Differential Impedance | | 90 | 100 | 110 | Ω | |
| Output High | | 2.4 | | Vcc | V | |
| Output Low | | 0 | | 0.4 | V | |
| Input High | | 2 | | Vcc+0.3 | V | |
| Input Low | | 0 | | 0.8 | V | |
| LOS Assert Time | TLOSA | | | 100 | us | |
| LOS De-assert Time | TLOSD | | | 100 | us | |

Formerica OptoElectronics Inc.



10Gb/s XFP Transceiver PRODUCT NUMBER: TAS-XxUS5-KA6

Typical Interface Circuit



EEPROM Memory Map



Formerica OptoElectronics Inc.

5F-11, No.38, Taiyuan St.,Zhubei City, Hsinchu County 30265, Taiwan Ph: +886-3-5600286 Fax: +886-3-5600239 www.formericaoe.com



Mechanical Dimensions



ESD

This transceiver is specified as ESD threshold 2kV for all electrical input pins, tested per MIL-STD-883, Method 3015.4 /JESD22-A114-A (HBM). However, normal ESD precautions are still required during the handling of this module. This transceiver is shipped in ESD protective packaging. It should be removed from the packaging and handled only in an ESD protected environment.

LASER Safety

This is a Class 1 Laser Product according to IEC/EN60825-1:2014 (Third Edition).. This product complies with 21 CFR 1040.10 and 1040.11 except for deviations pursuant to Laser Notice No. 50, dated (June 24, 2007)



Revision History

| Date | Version | Description |
|------------|---------|-----------------|
| 03/12/2018 | 1.0 | Initial release |