

Chipsmall Limited consists of a professional team with an average of over 10 year of expertise in the distribution of electronic components. Based in Hongkong, we have already established firm and mutual-benefit business relationships with customers from, Europe, America and south Asia, supplying obsolete and hard-to-find components to meet their specific needs.

With the principle of "Quality Parts, Customers Priority, Honest Operation, and Considerate Service", our business mainly focus on the distribution of electronic components. Line cards we deal with include Microchip, ALPS, ROHM, Xilinx, Pulse, ON, Everlight and Freescale. Main products comprise IC, Modules, Potentiometer, IC Socket, Relay, Connector. Our parts cover such applications as commercial, industrial, and automotives areas.

We are looking forward to setting up business relationship with you and hope to provide you with the best service and solution. Let us make a better world for our industry!



# Contact us

Tel: +86-755-8981 8866 Fax: +86-755-8427 6832

Email & Skype: info@chipsmall.com Web: www.chipsmall.com

Address: A1208, Overseas Decoration Building, #122 Zhenhua RD., Futian, Shenzhen, China









## Is Now Part of



# ON Semiconductor®

To learn more about ON Semiconductor, please visit our website at <a href="https://www.onsemi.com">www.onsemi.com</a>

ON Semiconductor and the ON Semiconductor logo are trademarks of Semiconductor Components Industries, LLC dba ON Semiconductor or its subsidiaries in the United States and/or other countries. ON Semiconductor owns the rights to a number of patents, trademarks, copyrights, trade secrets, and other intellectual property. A listing of ON Semiconductor's product/patent coverage may be accessed at www.onsemi.com/site/pdf/Patent-Marking.pdf. ON Semiconductor reserves the right to make changes without further notice to any products herein. ON Semiconductor makes no warranty, representation or guarantee regarding the suitability of its products for any particular purpose, nor does ON Semiconductor assume any liability arising out of the application or use of any product or circuit, and specifically disclaims any and all liability, including without limitation special, consequential or incidental damages. Buyer is responsible for its products and applications using ON Semiconductor products, including compliance with all laws, regulations and safety requirements or standards, regardless of any support or applications information provided by ON Semiconductor. "Typical" parameters which may be provided in ON Semiconductor data sheets and/or specifications can and do vary in different applications and actual performance may vary over time. All operating parameters, including "Typicals" must be validated for each customer application by customer's technical experts. ON Semiconductor does not convey any license under its patent rights nor the rights of others. ON Semiconductor products are not designed, intended, or authorized for use as a critical component in life support systems or any EDA Class 3 medical devices with a same or similar classification in a foreign jurisdiction or any devices intended for implantation in the human body. Should Buyer purchase or use ON Semiconductor products for any such unintended or unauthorized application, Buyer shall indemnify and hold ON Semiconductor and its officers, employees, emplo




November 2014

# TIP110 / TIP111 / TIP112 NPN Epitaxial Silicon Darlington Transistor

## **Features**

- Monolithic Construction with Built-in Base-Emitter Shunt Resistors
- · Complementary to TIP115 / TIP116 / TIP117
- High DC Current Gain:  $h_{FE} = 1000 @ V_{CE} = 4 \text{ V}, I_{C} = 1 \text{ A (Minimum)}$
- · Low Collector-Emitter Saturation Voltage
- Industrial Use



## **Ordering Information**

Part Number	Top Mark	Package	Packing Method
TIP110	TIP110	TO-220 3L (Single Gauge)	Bulk
TIP110TU	TIP110	TO-220 3L (Single Gauge)	Rail
TIP111TU	TIP111	TO-220 3L (Single Gauge)	Rail
TIP112	TIP112	TO-220 3L (Single Gauge)	Bulk
TIP112TU	TIP112	TO-220 3L (Single Gauge)	Rail

## **Absolute Maximum Ratings**

Stresses exceeding the absolute maximum ratings may damage the device. The device may not function or be operable above the recommended operating conditions and stressing the parts to these levels is not recommended. In addition, extended exposure to stresses above the recommended operating conditions may affect device reliability. The absolute maximum ratings are stress ratings only. Values are at  $T_C = 25^{\circ}$ C unless otherwise noted.

Symbol	Parameter		Value	Unit
		TIP110	60	
V <sub>CBO</sub>	Collector-Base Voltage	TIP111	80	V
		TIP112	100	
V <sub>CEO</sub>		TIP110	60	V
	Collector-Emitter Voltage	TIP111	80	
		TIP112	100	
V <sub>EBO</sub>	Emitter-Base Voltage		5	V
I <sub>C</sub>	Collector Current (DC)		2	Α
I <sub>CP</sub>	Collector Current (Pulse)		4	Α
I <sub>B</sub>	Base Current (DC)		50	mA
TJ	Junction Temperature		150	°C
T <sub>STG</sub>	Storage Temperature Range		-65 to 150	°C

## **Thermal Characteristics**

Values are at  $T_C = 25^{\circ}C$  unless otherwise noted.

Symbol	Parameter	Value	Unit	
Pc	Collector Dissipation (T <sub>A</sub> = 25°C)	2	W	
r <sub>C</sub>	Collector Dissipation (T <sub>C</sub> = 25°C)	50		

## **Electrical Characteristics**(1)

Values are at  $T_C = 25$ °C unless otherwise noted.

Symbol	Parameter		Conditions	Min.	Max.	Unit
V <sub>CEO</sub> (sus)	Collector-Emitter Sustaining Voltage	TIP110	I <sub>C</sub> = 30 mA, I <sub>B</sub> = 0	60		V
		TIP111		80		
		TIP112		100		
I <sub>CEO</sub>	Collector Cut-Off Current	TIP110	V <sub>CE</sub> = 30 V, I <sub>B</sub> = 0		2	mA
		TIP111	V <sub>CE</sub> = 40 V, I <sub>B</sub> = 0		2	
		TIP112	V <sub>CE</sub> = 50 V, I <sub>B</sub> = 0		2	
I <sub>CBO</sub>	Collector Cut-Off Current	TIP110	V <sub>CB</sub> = 60 V, I <sub>E</sub> = 0		1	mA
		TIP111	V <sub>CB</sub> = 80 V, I <sub>E</sub> = 0		1	
		TIP112	V <sub>CB</sub> = 100 V, I <sub>E</sub> = 0		1	
I <sub>EBO</sub>	Emitter Cut-Off Current		V <sub>EB</sub> = 5 V, I <sub>C</sub> = 0	\	2	mA
h	DC Current Gain		V <sub>CE</sub> = 4 V, I <sub>C</sub> = 1 A	1000		
h <sub>FE</sub>			$V_{CE} = 4 \text{ V}, I_{C} = 2 \text{ A}$	500		
V <sub>CE</sub> (sat) Collector-Emitter Saturation Voltage		$I_C = 2 \text{ A}, I_B = 8 \text{ mA}$		2.5	V	
V <sub>BE</sub> (on)	Base-Emitter On Voltage		V <sub>CE</sub> = 4 V, I <sub>C</sub> = 2 A		2.8	V
C <sub>ob</sub>	Output Capacitance		V <sub>CB</sub> = 10 V, I <sub>E</sub> = 0, f = 0.1 MHz		100	pF

## Note:

1. Pulse test: pw  $\leq$  300  $\mu$ s, duty cycle  $\leq$  2%.

## **Typical Performance Characteristics**




Figure 1. Static Characteristic




Figure 3. Base-Emitter Saturation Voltage and Collector-Emitter Saturation Voltage




Figure 5. Safe Operating Area





Figure 2. DC Current Gain



**Figure 4. Collector Output Capacitance** 





Figure 6. Power Derating





#### TRADEMARKS

The following includes registered and unregistered trademarks and service marks, owned by Fairchild Semiconductor and/or its global subsidiaries, and is not intended to be an exhaustive list of all such trademarks.

 AccuPower™
 F-PFS™

 Awinda®
 FRFET®

 AX-CAP®+
 Global Power Resource

 BISSION
 Case Bridge IV

 BitSiC™
 GreenBridge™

 Build it Now™
 Green FPS™

 CorePLUS™
 Green FPS™ e-Series™

CorePOWER<sup>TM</sup>  $CROSSVOLT^{TM}$   $CTL^{TM}$   $CTL^{TM}$   $CUrrent Transfer Logic^{TM}$   $CSCPI ANAR^{TM}$   $CSCPI ANAR^{TM}$ 

DEUXPEED<sup>®</sup> Making Small Speakers Sound Louder
Dual Cool™ and Retter™

Dual Cool™ and Better™
EcoSPARK® MegaBuck™
EfficientMax™ MICROCOUPLER™
ESBC™ MicroFET™
MicroPak™

MicroPak2™ Fairchild® MillerDrive™ Fairchild Semiconductor® MotionMax™ FACT Quiet Series™ MotionGrid® FACT FAST® MTi<sup>®</sup> MTx® FastvCore™ MVN® FFTBench™ mWSaver® **FPS™** 

OptoHiT™ OPTOLOGIC® OPTOPLANAR®

® PowerTrench® PowerXS™

Programmable Active Droop™

QFĒT<sup>®</sup>
QS™
Quiet Series™
RapidConfigure™

Saving our world, 1mW/W/kW at a time™

SignalWise™
SmartMax™
SMART START™

Solutions for Your Success™

SPM®
STEALTH™
SuperFET®
SuperSOT™-3
SuperSOT™-6
SuperSOT™-6
SuperSOT™-8
SuperSOT™-8
SuperSOT™-8
SuperSOT™-8
SuperSOT™-8
SuperSOT™-8
SuperSOT™-8
SuperSOT™-8

SYSTEM GENERAL®\*

TinyBoost®
TinyBuck®
TinyCalc™
TinyLogic®
TINYOPTO™
TinyPower™
TinyPWM™
TrinyWire™
TranSiC™
TriFault Detect™

TRUECURRENT®\*

µSerDes™

SerDes™

SerDes\*
UHC®
Ultra FRFET™
UniFET™
VCX™
VisualMax™
VoltagePlus™
XS™
Xsens™
仙童™

#### DISCLAIMER

FAIRCHILD SEMICONDUCTOR RESERVES THE RIGHT TO MAKE CHANGES WITHOUT FURTHER NOTICE TO ANY PRODUCTS HEREIN TO IMPROVE RELIABILITY, FUNCTION, OR DESIGN. TO OBTAIN THE LATEST, MOST UP-TO-DATE DATASHEET AND PRODUCT INFORMATION, VISIT OUR WEBSITE AT <a href="http://www.fairchildsemi.com">http://www.fairchildsemi.com</a>, FAIRCHILD DOES NOT ASSUME ANY LIABILITY ARISING OUT OF THE APPLICATION OR USE OF ANY PRODUCT OF CIRCUIT DESCRIBED HEREIN, NEITHER DOES IT CONVEY ANY LICENSE UNDER ITS PATENT RIGHTS, NOR THE RIGHTS OF OTHERS. THESE SPECIFICATIONS DO NOT EXPAND THE TERMS OF FAIRCHILD'S WORLDWIDE TERMS AND CONDITIONS, SPECIFICALLY THE WARRANTY THEREIN, WHICH COVERS THESE PRODUCTS.

#### LIFE SUPPORT POLICY

FAIRCHILD'S PRODUCTS ARE NOT AUTHORIZED FOR USE AS CRITICAL COMPONENTS IN LIFE SUPPORT DEVICES OR SYSTEMS WITHOUT THE EXPRESS WRITTEN APPROVAL OF FAIRCHILD SEMICONDUCTOR CORPORATION.

#### As used herein:

- Life support devices or systems are devices or systems which, (a) are intended for surgical implant into the body or (b) support or sustain life, and (c) whose failure to perform when properly used in accordance with instructions for use provided in the labeling, can be reasonably expected to result in a significant injury of the user.
- A critical component in any component of a life support, device, or system whose failure to perform can be reasonably expected to cause the failure of the life support device or system, or to affect its safety or effectiveness.

## ANTI-COUNTERFEITING POLICY

Fairchild Semiconductor Corporation's Anti-Counterfeiting Policy. Fairchild's Anti-Counterfeiting Policy is also stated on our external website, www.fairchildsemi.com, under Sales Support

Counterfeiting of semiconductor parts is a growing problem in the industry. All manufacturers of semiconductor products are experiencing counterfeiting of their parts. Customers who inadvertently purchase counterfeit parts experience many problems such as loss of brand reputation, substandard performance, failed applications, and increased cost of production and manufacturing delays. Fairchild is taking strong measures to protect ourselves and our customers from the proliferation of counterfeit parts. Fairchild strongly encourages customers to purchase Fairchild parts either directly from Fairchild or from Authorized Fairchild Distributors who are listed by country on our web page cited above. Products customers buy either from Fairchild directly or from Authorized Fairchild Distributors are genuine parts, have full traceability, meet Fairchild's quality standards for handling and storage and provide access to Fairchild's full range of up-to-date technical and product information. Fairchild and our Authorized Distributors will stand behind all warranties and will appropriately address any warranty issues that may arise. Fairchild will not provide any warranty coverage or other assistance for parts bought from Unauthorized Sources. Fairchild is committed to combat this global problem and encourage our customers to do their part in stopping this practice by buying direct or from authorized distributors.

## PRODUCT STATUS DEFINITIONS

## **Definition of Terms**

Datasheet Identification	Product Status	Definition	
Advance Information	Formative / In Design	Datasheet contains the design specifications for product development. Specifications may change in any manner without notice.	
Preliminary	First Production	Datasheet contains preliminary data; supplementary data will be published at a later date. Fairchild Semiconductor reserves the right to make changes at any time without notice to improve design.	
No Identification Needed Full Production		Datasheet contains final specifications. Fairchild Semiconductor reserves the right to make changes at any time without notice to improve the design.	
Obsolete	Not In Production	Datasheet contains specifications on a product that is discontinued by Fairchild Semiconductor. The datasheet is for reference information only.	

Rev. 172

<sup>\*</sup> Trademarks of System General Corporation, used under license by Fairchild Semiconductor.

ON Semiconductor and in are trademarks of Semiconductor Components Industries, LLC dba ON Semiconductor or its subsidiaries in the United States and/or other countries. ON Semiconductor owns the rights to a number of patents, trademarks, copyrights, trade secrets, and other intellectual property. A listing of ON Semiconductor's product/patent coverage may be accessed at <a href="www.onsemi.com/site/pdf/Patent-Marking.pdf">www.onsemi.com/site/pdf/Patent-Marking.pdf</a>. ON Semiconductor reserves the right to make changes without further notice to any products herein. ON Semiconductor assume any liability arising out of the application or use of any product or circuit, and specifically disclaims any and all liability, including without limitation special, consequential or incidental damages. Buyer is responsible for its products and applications using ON Semiconductor products, including compliance with all laws, regulations and safety requirements or standards, regardless of any support or applications information provided by ON Semiconductor. "Typical" parameters which may be provided in ON Semiconductor data sheets and/or specifications can and do vary in different applications and actual performance may vary over time. All operating parameters, including "Typicals" must be validated for each customer application by customer's technical experts. ON Semiconductor does not convey any license under its patent rights nor the rights of others. ON Semiconductor products are not designed, intended, or authorized for use as a critical component in life support systems or any FDA Class 3 medical devices or medical devices with a same or similar classification in a foreign jurisdiction or any devices intended for implantation in the human body. Should Buyer purchase or use ON Semiconductor products for any such unintended or unauthorized application, Buyer shall indemnify and hold ON Semiconductor and its officers, employees, subsidiaries, affiliates, and distributors harmless against all claims, costs, damages, and exp

## **PUBLICATION ORDERING INFORMATION**

#### LITERATURE FULFILLMENT:

Literature Distribution Center for ON Semiconductor 19521 E. 32nd Pkwy, Aurora, Colorado 80011 USA Phone: 303-675-2175 or 800-344-3860 Toll Free USA/Canada Fax: 303-675-2176 or 800-344-3867 Toll Free USA/Canada Email: orderlit@onsemi.com N. American Technical Support: 800–282–9855 Toll Free USA/Canada
Europe, Middle East and Africa Technical Support:
Phone: 421 33 790 2910

Phone: 421 33 790 2910

Japan Customer Focus Center

Phone: 81–3–5817–1050

ON Semiconductor Website: www.onsemi.com

Order Literature: http://www.onsemi.com/orderlit

For additional information, please contact your local Sales Representative