



Chipsmall Limited consists of a professional team with an average of over 10 year of expertise in the distribution of electronic components. Based in Hongkong, we have already established firm and mutual-benefit business relationships with customers from,Europe,America and south Asia,supplying obsolete and hard-to-find components to meet their specific needs.

With the principle of “Quality Parts,Customers Priority,Honest Operation,and Considerate Service”,our business mainly focus on the distribution of electronic components. Line cards we deal with include Microchip,ALPS,ROHM,Xilinx,Pulse,ON,Everlight and Freescale. Main products comprise IC,Modules,Potentiometer,IC Socket,Relay,Connector.Our parts cover such applications as commercial,industrial, and automotives areas.

We are looking forward to setting up business relationship with you and hope to provide you with the best service and solution. Let us make a better world for our industry!



Contact us

Tel: +86-755-8981 8866 Fax: +86-755-8427 6832


Email & Skype: info@chipsmall.com Web: www.chipsmall.com

Address: A1208, Overseas Decoration Building, #122 Zhenhua RD., Futian, Shenzhen, China




Power Transistors

TO-220 Case (Continued)



Standard



Optional

TYPE NO.		I_C	P_D	BV_{CBO}	BV_{CEO}	h_{FE}		@ I_C	$V_{CE(SAT)}$	@ I_C	f_T
NPN	PNP	(A) MAX	(W)	(V) MIN	(V) MIN	MIN	MAX	(A)	(V) MAX	(A)	(MHz) MIN
SE9300	SE9400	10	70	60	60	1,000	--	4.0	2.0	4.0	1.0
SE9301	SE9401	10	70	80	80	1,000	--	4.0	2.0	4.0	1.0
SE9302	SE9402	10	70	100	100	1,000	--	4.0	2.0	4.0	1.0
TIP29	TIP30	1.0	30	40	40	15	75	1.0	0.7	1.0	3.0
TIP29A	TIP30A	1.0	30	60	60	15	75	1.0	0.7	1.0	3.0
TIP29B	TIP30B	1.0	30	80	80	15	75	1.0	0.7	1.0	3.0
TIP29C	TIP30C	1.0	30	100	100	15	75	1.0	0.7	1.0	3.0
TIP31	TIP32	3.0	40	40	40	10	50	3.0	1.2	3.0	3.0
TIP31A	TIP32A	3.0	40	60	60	10	50	3.0	1.2	3.0	3.0
TIP31B	TIP32B	3.0	40	80	80	10	50	3.0	1.2	3.0	3.0
TIP31C	TIP32C	3.0	40	100	100	10	50	3.0	1.2	3.0	3.0
TIP41	TIP42	6.0	65	40	40	15	75	3.0	1.5	6.0	3.0
TIP41A	TIP42A	6.0	65	60	60	15	75	3.0	1.5	6.0	3.0
TIP41B	TIP42B	6.0	65	80	80	15	75	3.0	1.5	6.0	3.0
TIP41C	TIP42C	6.0	65	100	100	15	75	3.0	1.5	6.0	3.0
TIP47		1.0	40	350	250	30	150	0.3	1.0	1.0	10
TIP48		1.0	40	400	300	30	150	0.3	1.0	1.0	10
TIP49		1.0	40	450	350	30	150	0.3	1.0	1.0	10
TIP50		1.0	40	500	400	30	150	0.3	1.0	1.0	10
TIP100	TIP105	8.0	80	60	60	1,000	20,000	3.0	2.0	3.0	4.0
TIP101	TIP106	8.0	80	80	80	1,000	20,000	3.0	2.0	3.0	4.0
TIP102	TIP107	8.0	80	100	100	1,000	20,000	3.0	2.0	3.0	4.0
TIP110	TIP115	2.0	50	60	60	500	--	2.0	2.5	2.0	25
TIP111	TIP116	2.0	50	80	80	500	--	2.0	2.5	2.0	25
TIP112	TIP117	2.0	50	100	100	500	--	2.0	2.5	2.0	25
TIP120	TIP125	5.0	65	60	60	1,000	--	3.0	2.0	3.0	4.0
TIP121	TIP126	5.0	65	80	80	1,000	--	3.0	2.0	3.0	4.0
TIP122	TIP127	5.0	65	100	100	1,000	--	3.0	2.0	3.0	4.0
TIP130	TIP135	8.0	70	60	60	1,000	15,000	4.0	2.0	4.0	--
TIP131	TIP136	8.0	70	80	80	1,000	15,000	4.0	2.0	4.0	--
TIP132	TIP137	8.0	70	100	100	1,000	15,000	4.0	2.0	4.0	--

Shaded areas indicate Darlington.

OUTSTANDING SUPPORT AND SUPERIOR SERVICES



PRODUCT SUPPORT

Central's operations team provides the highest level of support to insure product is delivered on-time.

- Supply management (Customer portals)
- Inventory bonding
- Consolidated shipping options
- Custom bar coding for shipments
- Custom product packing

DESIGNER SUPPORT/SERVICES

Central's applications engineering team is ready to discuss your design challenges. Just ask.

- Free quick ship samples (2nd day air)
- Online technical data and parametric search
- SPICE models
- Custom electrical curves
- Environmental regulation compliance
- Customer specific screening
- Up-screening capabilities
- Special wafer diffusions
- PbSn plating options
- Package details
- Application notes
- Application and design sample kits
- Custom product and package development

REQUESTING PRODUCT PLATING

1. If requesting Tin/Lead plated devices, add the suffix " TIN/LEAD" to the part number when ordering (example: 2N2222A TIN/LEAD).
2. If requesting Lead (Pb) Free plated devices, add the suffix " PBFREE" to the part number when ordering (example: 2N2222A PBFREE).

CONTACT US

Corporate Headquarters & Customer Support Team

Central Semiconductor Corp.
145 Adams Avenue
Hauppauge, NY 11788 USA
Main Tel: (631) 435-1110
Main Fax: (631) 435-1824
Support Team Fax: (631) 435-3388
www.centrasemi.com

Worldwide Field Representatives:
www.centrasemi.com/wwreps

Worldwide Distributors:
www.centrasemi.com/wwdistributors

For the latest version of Central Semiconductor's **LIMITATIONS AND DAMAGES DISCLAIMER**, which is part of Central's Standard Terms and Conditions of sale, visit: www.centrasemi.com/terms



<http://www.centrasemi.com>

Product End of Life Notification

PDN ID:	PDN01044
Notification Date:	8/15/16
Last Buy Date:	2/15/17
Last Shipment Date	8/15/17

Summary: The TIP130 series of NPN and PNP Darlington power transistors, with the exception of part TIP132 and TIP137, is discontinued and now classified as End of Life (EOL).

Although Central Semiconductor Corp. makes every effort to continue to produce devices that have been proclaimed EOL (End of Life) by various manufacturers, it is an accepted industry practice to discontinue certain devices when customer demand falls below a minimum level of sustainability. Accordingly, the following product(s) have been transitioned to End of Life status as part of Central's Product Management Process. Any replacement product will be noted below. The effective date for placing the last purchase order will be six(6) months from the date of this notice and twelve(12) months from the notice date for final shipments; this may be extended if inventory is available.

Central Part Number	Replacement
TIP130	TIP132
TIP131	TIP132
TIP135	TIP137
TIP136	TIP137

Central would be happy to assist you by providing additional information or technical data to help locate an alternate source if we have no replacement available. Please email your requests to engineering@centrasemi.com.

DISCLAIMER: This End of Life (EOL) notification is in accordance with JEDEC standard JESD48 - Product Discontinuance. Central Semiconductor Corp. will make every effort to offer life-time buy (LTB) opportunities and/or offer replacement devices to existing customers for discontinued devices, however, one or both may not be possible for all devices. Please contact your local Central Semiconductor sales representative for LTB opportunities/additional information.