

Chipsmall Limited consists of a professional team with an average of over 10 year of expertise in the distribution of electronic components. Based in Hongkong, we have already established firm and mutual-benefit business relationships with customers from, Europe, America and south Asia, supplying obsolete and hard-to-find components to meet their specific needs.

With the principle of "Quality Parts, Customers Priority, Honest Operation, and Considerate Service", our business mainly focus on the distribution of electronic components. Line cards we deal with include Microchip, ALPS, ROHM, Xilinx, Pulse, ON, Everlight and Freescale. Main products comprise IC, Modules, Potentiometer, IC Socket, Relay, Connector. Our parts cover such applications as commercial, industrial, and automotives areas.

We are looking forward to setting up business relationship with you and hope to provide you with the best service and solution. Let us make a better world for our industry!



# Contact us

Tel: +86-755-8981 8866 Fax: +86-755-8427 6832

Email & Skype: info@chipsmall.com Web: www.chipsmall.com

Address: A1208, Overseas Decoration Building, #122 Zhenhua RD., Futian, Shenzhen, China








# TMC429-LI BOB Description

Document Revision V1.00 • 2017-Oct-19

## **Module Top View**



### Features and additional Resources

- TMC429-LI triple-axis dedicated motion controller
- Supply voltage 3.3V or 5V
- · Configuration and control via SPI
- 3x dedicated Step and Direction output
- Up to 32MHz input frequecy
- Up to 1MHz step output frequency
- Board width 1.0", board height 1.0"
- 2x10 pin 0.1" header rows for pins/connectors
- Link to additional information and IC Datasheet
- Link to Evaluation Kit


#### Pin List

Left	Signal	Right	Signal	
1	5V	11	REF1 (Left reference)	
2	GND	12	REF2	
3	3V3	13	REF3	
4	CSN_C	14	REFR1 (right reference)	
5	SCK_C	15	D2 (Direction 2)	
6	SDI_C	16	S2 (Step 2)	
7	SDO_C	17	D3 (Direction 2)	
8	CLK (up to 32MHz)	18	S3 (Step 3)	
9	PSCMP	19	D1 (Direction 2)	
10	nINT_SDO_C	20	S1 (Step 1)	

#### Bill of Materials

Pcs.	MPN	Value	Footprint	Description
1	MC0603X474K160CT	470nF,16V,10%	0603	Cap, Multicomp
2	MC0603B104K160CT	100nF,16V,10%	0603	Cap, Multicomp
6	MC0603B103K160CT	10nF/16V/10%	0603	Cap, Multicomp
2	LTST-C191TBKT-5A	20mA,2.8V,465nm	0603	LED, Lite-On
1	TMC429-LI	TMC429-LI	QFN32,5x5,0.5	PreDriver, TRINAMIC
1	MC0063W0603110K	10k	0603	Res, Multicomp
2	MC0063W060311K	1k	0603	Res, Multicomp
6	MC0063W060314K7	4k7	0603	Res, Multicomp

#### **BOB Schematics**



©2017 TRINAMIC Motion Control GmbH & Co. KG, Hamburg, Germany Download newest version at: www.trinamic.com



