

Chipsmall Limited consists of a professional team with an average of over 10 year of expertise in the distribution of electronic components. Based in Hongkong, we have already established firm and mutual-benefit business relationships with customers from, Europe, America and south Asia, supplying obsolete and hard-to-find components to meet their specific needs.

With the principle of "Quality Parts, Customers Priority, Honest Operation, and Considerate Service", our business mainly focus on the distribution of electronic components. Line cards we deal with include Microchip, ALPS, ROHM, Xilinx, Pulse, ON, Everlight and Freescale. Main products comprise IC, Modules, Potentiometer, IC Socket, Relay, Connector. Our parts cover such applications as commercial, industrial, and automotives areas.

We are looking forward to setting up business relationship with you and hope to provide you with the best service and solution. Let us make a better world for our industry!



# Contact us

Tel: +86-755-8981 8866 Fax: +86-755-8427 6832

Email & Skype: info@chipsmall.com Web: www.chipsmall.com

Address: A1208, Overseas Decoration Building, #122 Zhenhua RD., Futian, Shenzhen, China











### ULN2002A/ ULN2003A/ ULN2004A

# HIGH VOLTAGE, HIGH CURRENT DARLINGTON TRANSISTOR ARRAYS

### Description

The ULN2002A, ULN2003A and ULN2004A are high voltage, high current Darlington arrays each containing seven open collector common emitter pairs. Each pair is rated at 500mA. Suppression diodes are included for inductive load driving, the inputs and outputs are pinned in opposition to simplify board layout.

Device options are designed to be compatible with common logic families:

ULN2002A (14-25V PMOS) ULN2003A (5V TTL, CMOS) ULN2004A (6-15V CMOS, PMOS)


These devices are capable of driving a wide range of loads including solenoids, relays, DC motors, LED displays, filament lamps, thermal print-heads and high-power buffers.


The ULN2002A, ULN2003A and ULN2004A are available in both a small outline 16-pin package (SO-16) and PDIP-16 package.

#### **Features**

- 500mA Rated Collector Current (Single Output)
- High Voltage Outputs: 50V
- Output Clamp Diodes
- Inputs Compatible with Popular Logic Types
- Relay Driver Applications
- "Green" Molding Compound (No Br, Sb)
- Totally Lead-Free & Fully RoHS Compliant (Notes 1 & 2)
- Halogen and Antimony Free. "Green" Device (Note 3)

### **Pin Assignments**






PDIP-16

Notes:

- 1. No purposely added lead. Fully EU Directive 2002/95/EC (RoHS) & 2011/65/EU (RoHS 2) compliant.
- 2. See http://www.diodes.com/quality/lead\_free.html for more information about Diodes Incorporated's definitions of Halogen- and Antimony-free, "Green" and Lead-free.
- 3. Halogen- and Antimony-free "Green" products are defined as those which contain <900ppm bromine, <900ppm chlorine (<1500ppm total Br + Cl) and <1000ppm antimony compounds.

# **Connection Diagram**







# **Pin Descriptions**

Pin Number	Pin Name	Function
SO-16/PDIP-16	Pin Name	Function
1	1B	Input Pair 1
2	2B	Input Pair 2
3	3B	Input Pair 3
4	4B	Input Pair 4
5	5B	Input Pair 5
6	6B	Input Pair 6
7	7B	Input Pair 7
8	E	Common Emitter (Ground)
9	COM	Common Clamp Diodes
10	7C	Output Pair 7
11	6C	Output Pair 6
12	5C	Output Pair 5
13	4C	Output Pair 4
14	3C	Output Pair 3
15	2C	Output Pair 2
16	1C	Output Pair 1

# **Functional Block Diagram**



ULN2002A



 $\begin{array}{ll} ULN2003A: & R_B=2.7k \\ ULN2004A: & R_B=10.5k \end{array}$ 

ULN2003A, ULN2004A



# Absolute Maximum Ratings (Note 4) (@T<sub>A</sub> = +25°C, unless otherwise specified.)

Symbol	Parameter		Rating	Unit
V <sub>CC</sub>	Collector to Emitter Voltage		50	V
$V_{R}$	Clamp Diode Reverse Voltage (Note 5)		50	V
Vı	Input Voltage (Note 5)		30	V
I <sub>CP</sub>	Peak Collector Current		500	mA
I <sub>OK</sub>	Output Clamp Current		500	mA
I <sub>TE</sub>	Total Emitter Current		-2.5	Α
0	Thermal Decistance Junction to Ambient (Note 6)	SO-16	63.0	°C/W
θја	Thermal Resistance Junction-to-Ambient (Note 6)	PDIP-16	50.0	- C/VV
0	Thermal Resistance Junction-to-Case (Note 7)	SO-16	12.0	°C/W
$\theta_{ m JC}$	Thermal Resistance Junction-to-Case (Note 7)	PDIP-16	15.0	C/ <b>VV</b>
TJ	Junction Temperature	+150	°C	
T <sub>STG</sub>	Storage Temperature	-65 to +150	°C	

Notes:

- 4. Stresses beyond those listed under "absolute maximum ratings" may cause permanent damage to the device. These are stress ratings only. Functional operation of the device at these or any other conditions beyond those indicated under "recommended operating conditions" is not implied. Exposure to absolute-maximum-rated conditions for extended periods may affect device reliability.
- 5. All voltage values are with respect to the emitter/substrate terminal E, unless otherwise noted.
- 6. Maximum power dissipation is a function of  $T_J(max)$ ,  $\theta_{JA}$  and  $T_A$ . The maximum allowable power dissipation at any allowable ambient temperature is  $P_D = (T_J(max) T_A)/\theta_{JA}$ . Operating at the absolute maximum  $T_J$  of +150°C can affect reliability.
- 7. Maximum power dissipation is a function of  $T_J(max)$ ,  $\theta_{JC}$  and  $T_A$ . The maximum allowable power dissipation at any allowable ambient temperature is  $P_D = (T_J(max) T_C)/\theta_{JC}$ . Operating at the absolute maximum  $T_J$  of +150°C can affect reliability.

### **Recommended Operating Conditions**

Symbol Parameter		Min	Max	Unit
V <sub>CC</sub> Collector to Emitter Voltage			50	V
T <sub>A</sub> Operating Ambient Temperature		-40	+105	°C

### Electrical Characteristics (@T<sub>A</sub> = +25°C, unless otherwise specified.)

ULN2002A								
Symbol	Parameter	Test Figure	Test C	onditions	Min	Тур	Max	Unit
V <sub>I(ON)</sub>	On State Input Voltage	6	$V_{CE} = 2V, I_{C} = 3$	00mA	_	_	13	٧
			$I_1 = 250 \mu A, I_C =$	100mA	_	0.9	1.1	
V <sub>CE(SAT)</sub>	Collector Emitter Saturation Voltage	5	$I_I = 350 \mu A, I_C = 3$	200mA	_	1	1.3	V
	Vollage		$I_I = 500 \mu A, I_C = 3$	350mA	_	1.2	1.6	
$V_{F}$	Clamp Forward Voltage	8	I <sub>F</sub> = 350mA		_	1.7	2	V
	1		$V_{CE} = 50V, I_{I} = 0$	)	_	_	50	
I <sub>CEX</sub>	Collector Cut-off Current	2	$V_{CE} = 50V$ ,	$I_I = 0$	_	_	100	μΑ
		2	$T_A = +105^{\circ}C$	$V_I = 6V$	_	_	500	
I <sub>I(OFF)</sub>	Off State Input Current	3	$V_{CE} = 50V$ , $I_{C} =$	500μΑ	50	65	_	μΑ
II	Input Current	4	$V_I = 17V$		_	0.82	1.25	mA
l <sub>a</sub>	Clama Povorco Curront	7	V- F0V	T <sub>A</sub> = +105°C	_	_	100	
I <sub>R</sub>	Clamp Reverse Current		$V_R = 50V$	_	_	_	50	μΑ
Cı	Input Capacitance	_	$V_I = 0$ , $f = 1MHz$	·	_	_	25	pF



# **Electrical Characteristics** (Cont.) (@T<sub>A</sub> = +25°C, unless otherwise specified.)

JLN2003 <i>A</i>	Α							
	Parameter	Test Figure	Test	Conditions	Min	Тур	Max	Unit
				$I_C = 200 \text{mA}$	_		2.4	
$V_{I\left(ON\right)}$	On State Input Voltage	6	$V_{CE} = 2V$	$I_C = 250 \text{mA}$	_		2.7	V
				$I_C = 300 \text{mA}$			3	
			$I_1 = 250 \mu A, I_C$	= 100mA	_	0.9	1.1	
$V_{CE(SAT)}$	Collector Emitter Saturation Voltage	5	$I_1 = 350 \mu A, I_C =$	= 200mA	_	1	1.3	V
	Voltage		$I_1 = 500 \mu A, I_C =$	= 350mA	_	1.2	1.6	
VF	Clamp Forward Voltage	8	I <sub>F</sub> = 350mA		_	1.7	2	V
		1	V <sub>CE</sub> = 50V, I <sub>I</sub> =	: 0	_		50	
I <sub>CEX</sub>	Collector Cut-off Current	2	$V_{CE} = 50V,$ $T_{A} = +105^{\circ}C$	$I_1 = 0$	_	_	100	μΑ
I <sub>I(OFF)</sub>	Off State Input Current	3	V <sub>CE</sub> = 50V, I <sub>C</sub>	= 500µA	50	65		μΑ
II	Input Current	4	V <sub>I</sub> = 3.85V		_	0.93	1.35	mA
		nt 7		$T_A = +105^{\circ}C$	_	_	100	
I <sub>R</sub>	Clamp Reverse Current		$V_R = 50V$	_	_	_	50	μΑ
Cı	Input Capacitance	_	$V_1 = 0, f = 1MH$	lz	_	15	25	рF
JLN2004 <i>A</i>	Ā							
	Parameter	Test Figure	Test	Conditions	Min	Тур	Max	Unit
				I <sub>C</sub> = 125mA	_	_	5	
$V_{I(ON)}$	On State Input Voltage	6	V <sub>CE</sub> = 2V	$I_C = 200 \text{mA}$	_	_	6	V
VI(ON)	On State input Voltage	6	VCE = ZV	$I_C = 275 \text{mA}$	_	_	7	
				$I_C = 350 \text{mA}$		_	8	
	0 11 .		$I_I=250\mu A,\ I_C=$	100mA		0.9	1.1	
$V_{CE(SAT)}$	Collector Emitter Saturation Voltage	5	$I_I=350\mu A,\ I_C=$	200mA	_	1	1.3	V
	Tonago		$I_{I} = 500 \mu A, I_{C} =$	350mA	_	1.2	1.6	
V <sub>F</sub>	Clamp Forward Voltage	8	I <sub>F</sub> = 350mA		_	1.7	2	V
		1	$V_{CE} = 50V, I_{I} = 0$	)	_	_	50	
I <sub>CEX</sub>	Collector Cut-off Current	0		lı – 0	_	_	100	μΑ
		2	$V_{CE} = 50V, T_A =$	V <sub>I</sub> = 6V	_	_	500	1
I <sub>I(OFF)</sub>	Off State Input Current	3	V <sub>CE</sub> = 50V, I <sub>C</sub> =	500μΑ	50	65	_	μΑ
lı	Input Current	4	$V_I = 5V$		_	0.35	0.5	mA
- 11	·			T <sub>A</sub> = +105°C	_	_	100	<u> </u>
	Claure Devenue Command	7	\/ =0\/					
I <sub>R</sub>	Clamp Reverse Current	7	$V_R = 50V$	_	_	_	50	μA



# **Electrical Characteristics** (Cont.) (@ $T_A = -40$ °C to +105°C, unless otherwise specified.)

ULN2003	JLN2003A								
	Parameter	Test Figure	Test Conditions		Min	Тур	Max	Unit	
				$I_C = 200 \text{mA}$	_	_	2.7		
$V_{I(ON)}$	On State Input Voltage	6	$V_{CE} = 2V$	$I_C = 250 \text{mA}$	_	_	2.9	V	
				$I_C = 300 \text{mA}$	_	_	3		
			$I_{I} = 250 \mu A, I_{C}$	= 100mA	_	0.9	1.2		
V <sub>CE(SAT)</sub>	V <sub>CE(SAT)</sub> Collector Emitter Saturation Voltage	5	$I_1 = 350\mu A$ , $I_C = 200mA$		_	1	1.4	V	
			$I_I = 500\mu A, I_C = 350mA$		_	1.2	1.7		
V <sub>F</sub>	Clamp Forward Voltage	8	I <sub>F</sub> = 350mA		_	1.7	2.2	V	
I <sub>CEX</sub>	Collector Cut-off Current	1	V <sub>CE</sub> = 50V, I <sub>I</sub> =	= 0	_	_	100	μΑ	
I <sub>I(OFF)</sub>	Off State Input Current	3	V <sub>CE</sub> = 50V, I <sub>C</sub>	$V_{CE} = 50V, I_{C} = 500\mu A$		65	_	μΑ	
Iį	Input Current	4	V <sub>I</sub> = 3.85V		_	0.93	1.35	mA	
I <sub>R</sub>	Clamp Reverse Current	7	V <sub>R</sub> = 50V		_	_	100	μΑ	
Cı	Input Capacitance	_	$V_{I} = 0, f = 1MI$	Нz	_	15	25	pF	

# Switching Characteristics (@T<sub>A</sub> = +25°C, unless otherwise specified.)

ULN2002A, ULN2003A, ULN2004A								
	Parameter	Test figure	Min	Тур	Max	Unit		
t <sub>PLH</sub>	Propagation Delay Time, Low to High Level Output	9	_	0.25	1	μs		
t <sub>PHL</sub>	Propagation Delay Time, High to Low Level Output	9	_	0.25	1	μs		
V <sub>OH</sub>	High Level Output Voltage after Switching	9 ( $V_S = 50V$ , $I_O = 300mA$ )	V <sub>S</sub> -20		1	mV		

# **Switching Characteristics** (@ $T_A = -40 \text{ to } +105^{\circ}\text{C}$ , unless otherwise specified.)

ULN2003A							
Parameter		Test figure	Min	Тур	Max	Unit	
t <sub>PLH</sub>	Propagation Delay Time, Low to High Level Output	9	_	1	10	μs	
t <sub>PHL</sub>	Propagation Delay Time, High to Low Level Output	9	_	1	10	μs	
$V_{OH}$	High Level Output Voltage after Switching	9 ( $V_S = 50V$ , $I_O = 300mA$ )	V <sub>S</sub> -50	_	_	mV	



# **Parameter Measurement Circuits**




Fig.1 ICEX Test Circuit




Fig.3 II(off) Test Circuit




Fig. 5 hfe, VCE(sat) Test Circuit




Fig. 7 In Test Circuit




Fig.2 ICEX Test Circuit




Fig.4 In Test Circuit




Fig. 6 V<sub>I(on)</sub> Test Circuit




Fig. 8 VF Test Circuit



### **Parameter Measurement Circuits (Cont.)**




Fig. 9 Latch-Up Test Circuit and Voltage Waveform

Notes: 8. The pulse generator has the following characteristics: Pulse Width = 12.5Hz, output impedance  $50\Omega$ , tr  $\leq 5$ ns, tr  $\leq 10$ ns.


9. C<sub>L</sub> includes prove and jig capacitance.

10. For testing the ULN2002A,  $V_{IH}$  = 13V; for the ULN2003A,  $V_{IH}$  = 3V; for the ULN2004A,  $V_{IH}$  = 8V.




### **Typical Performance Characteristics**


# Collector-Emitter Saturation Voltage vs. Collector Current (One Darlington)




#### **Collector Current vs. Input Current**




Input Current vs. Input Voltage




# Collector-Emitter Saturation Voltage vs. Collector Current (Two Darlington in Parallel)



#### **Maximum Collector Current vs. Duty Cycle**




Collector-Emitter Saturation Voltage vs.
Output Current






# **Typical Performance Characteristics (Cont.)**

### **Output Current vs. Input Current**





### **Ordering Information**




ULN2002A: 14~25V ULN2003A: 5V TTL S16: SO-16 D16: PDIP-16 13: Tape & Reel U : Tube

ULN2004A: 6~15V

	Dookono		13" Tape an	d Reel	Т	ube
Part Number	Package Code	Package	Quantity	Part Number Suffix	Quantity	Part Number Suffix
ULN2002AS16-13	S16	SO-16	2,500/Tape & Reel	-13	NA	NA
ULN2003AS16-13	S16	SO-16	2,500/Tape & Reel	-13	NA	NA
ULN2004AS16-13	S16	SO-16	2,500/Tape & Reel	-13	NA	NA
ULN2002AD16-U	D16	PDIP-16	NA	NA	25/Tube	-U
ULN2003AD16-U	D16	PDIP-16	NA	NA	25/Tube	-U
ULN2004AD16-U	D16	PDIP-16	NA	NA	25/Tube	-U

# **Marking Information**


#### (1) SO-16



YY: Year: 08, 09,10~ WW: Week: 01~52; 52 represents 52 and 53 week

XX: Internal Code

#### (2) PDIP-16



YY: Year: 08, 09,10~ WW: Week: 01~52; 52 represents 52 and 53 week


XX : Internal Code



# **Package Outline Dimensions**


Please see http://www.diodes.com/package-outlines.html for the latest version.


### (1) Package Type: SO-16




SO-16							
Dim	Min Max Typ						
Α		1.260					
A1	0.10	0.23					
A2	1.02	-	-				
b	0.31	0.51	-				
c D	0.10	0.25	-				
	9.80	10.00	-				
E	5.90	6.10					
E1	3.80	4.00					
е	1	.27 BS	0				
h	0.15	0.25	0.20				
L	0.40	1.27	-				
L1	1	.04 RE	F				
L2	C	).25 BS(	)				
R	0.07	-					
R1	0.07						
X	3.	945 RE	F				
Υ		.661 RE	F				
θ	0°	8°					
θ1	5°	15°					
θ2	0°						
All	Dimens	ions in	mm				

#### (2) Package Type: PDIP-16








	PDIP-16								
Dim	Min Max Nom								
Α	3.60	4.00	3.80						
A1	0.51	-	-						
A2	3.20	3.40	3.30						
A3	1.47	1.57	1.52						
b	0.44	0.53	-						
b2		1.52BSC							
С	0.25	0.31	-						
D	18.90	19.30	19.10						
E1	6.15	6.55	6.35						
E2a	7	7.62 BS0							
E2b	7.62	9.30	-						
E2c	0.00	0.84	-						
е	- 2	2.54BSC							
L	3.00	-	-						
All	Dimens	ions in	mm						



# **Suggested Pad Layout**

Please see http://www.diodes.com/package-outlines.html for the latest version.

### (1) Package Type: SO-16



Dimensions	Value (in mm)
С	1.270
X	0.670
X1	9.560
Υ	1.450
Y1	6.400

#### ULN2002A/ ULN2003A/ ULN2004A



#### **IMPORTANT NOTICE**

DIODES INCORPORATED MAKES NO WARRANTY OF ANY KIND, EXPRESS OR IMPLIED, WITH REGARDS TO THIS DOCUMENT, INCLUDING, BUT NOT LIMITED TO, THE IMPLIED WARRANTIES OF MERCHANTABILITY AND FITNESS FOR A PARTICULAR PURPOSE (AND THEIR EQUIVALENTS UNDER THE LAWS OF ANY JURISDICTION).

Diodes Incorporated and its subsidiaries reserve the right to make modifications, enhancements, improvements, corrections or other changes without further notice to this document and any product described herein. Diodes Incorporated does not assume any liability arising out of the application or use of this document or any product described herein; neither does Diodes Incorporated convey any license under its patent or trademark rights, nor the rights of others. Any Customer or user of this document or products described herein in such applications shall assume all risks of such use and will agree to hold Diodes Incorporated and all the companies whose products are represented on Diodes Incorporated website, harmless against all damages.

Diodes Incorporated does not warrant or accept any liability whatsoever in respect of any products purchased through unauthorized sales channel. Should Customers purchase or use Diodes Incorporated products for any unintended or unauthorized application, Customers shall indemnify and hold Diodes Incorporated and its representatives harmless against all claims, damages, expenses, and attorney fees arising out of, directly or indirectly, any claim of personal injury or death associated with such unintended or unauthorized application.

Products described herein may be covered by one or more United States, international or foreign patents pending. Product names and markings noted herein may also be covered by one or more United States, international or foreign trademarks.

This document is written in English but may be translated into multiple languages for reference. Only the English version of this document is the final and determinative format released by Diodes Incorporated.

#### LIFE SUPPORT

Diodes Incorporated products are specifically not authorized for use as critical components in life support devices or systems without the express written approval of the Chief Executive Officer of Diodes Incorporated. As used herein:

- A. Life support devices or systems are devices or systems which:
  - 1. are intended to implant into the body, or
  - 2. support or sustain life and whose failure to perform when properly used in accordance with instructions for use provided in the labeling can be reasonably expected to result in significant injury to the user.
- B. A critical component is any component in a life support device or system whose failure to perform can be reasonably expected to cause the failure of the life support device or to affect its safety or effectiveness.

Customers represent that they have all necessary expertise in the safety and regulatory ramifications of their life support devices or systems, and acknowledge and agree that they are solely responsible for all legal, regulatory and safety-related requirements concerning their products and any use of Diodes Incorporated products in such safety-critical, life support devices or systems, notwithstanding any devices- or systems-related information or support that may be provided by Diodes Incorporated. Further, Customers must fully indemnify Diodes Incorporated and its representatives against any damages arising out of the use of Diodes Incorporated products in such safety-critical, life support devices or systems.

Copyright © 2017, Diodes Incorporated

www.diodes.com