imall

Chipsmall Limited consists of a professional team with an average of over 10 year of expertise in the distribution of electronic components. Based in Hongkong, we have already established firm and mutual-benefit business relationships with customers from, Europe, America and south Asia, supplying obsolete and hard-to-find components to meet their specific needs.

With the principle of "Quality Parts, Customers Priority, Honest Operation, and Considerate Service", our business mainly focus on the distribution of electronic components. Line cards we deal with include Microchip, ALPS, ROHM, Xilinx, Pulse, ON, Everlight and Freescale. Main products comprise IC, Modules, Potentiometer, IC Socket, Relay, Connector. Our parts cover such applications as commercial, industrial, and automotives areas.

We are looking forward to setting up business relationship with you and hope to provide you with the best service and solution. Let us make a better world for our industry!



Contact us

Tel: +86-755-8981 8866 Fax: +86-755-8427 6832 Email & Skype: info@chipsmall.com Web: www.chipsmall.com Address: A1208, Overseas Decoration Building, #122 Zhenhua RD., Futian, Shenzhen, China







Powermite Package Commercial Two-Way Radio Antenna Switch Diode

DESCRIPTION

This Microsemi Powermite PIN diode is perfect for two-way radio antenna switch applications where size and power handling capability are critical with its high isolation, low loss and low distortion characteristics. Its advantages also include the low forward-bias resistance and high zero-bias impedance that are essential for low loss, high isolation and wide bandwidth antenna switch performance. It is an ideal selection for applications requiring low profile and high-density mounting and is also RoHS compliant. The Powermite package provides a full-metallic bottom that eliminates the possibility of solder flux entrapment during assembly, which in combination with its unique locking tab acts as an efficient heat path to the mounting surface. Its innovative design makes this device ideal for use with automatic insertion equipment. Microsemi also offers numerous other products to meet higher and lower power voltage regulation applications.

Important: For the latest information, visit our website http://www.microsemi.com.

FEATURES

- High power surface mount package with very low thermal resistance.
- Specified low distortion.
- Low bias current requirements.
- High zero bias impedance.
- Full metallic bottom eliminates flux entrapment.
- Integral heat sink/locking tabs.
- RoHS compliant.

APPLICATIONS / BENEFITS

- Two-way radio antenna switch.
- Low forward bias resistance.
- Low loss high isolation for wide bandwidth performance.
- Small size DO-216 package.
- Compatible with automatic insertion equipment.
- Very low inductance and capacitance.

MAXIMUM RATINGS

Parameters/Test Conditions	Symbol	Value	Unit
Junction and Storage Temperature	$T_{\rm J}$ and $T_{\rm STG}$	-55 to +150	°C
Thermal Resistance Junction-to-Case	R _{eJC}	10	ºC/W
Steady-State Power Dissipation @ T _{TAB1} = 75 °C (1)	PD	2.5	W
Reverse Voltage	V _R	50	V
Solder Temperature @ 10 s	T _{SP}	260	°C

Notes: 1. When mounted on a PC board with 2 oz copper.





DO-216 Package

MSC – Lawrence

6 Lake Street, Lawrence, MA 01841 1-800-446-1158 (978) 620-2600 Fax: (978) 689-0803

MSC – Ireland

Gort Road Business Park, Ennis, Co. Clare, Ireland Tel: +353 (0) 65 6840044 Fax: +353 (0) 65 6822298

Website:

www.microsemi.com






MECHANICAL and PACKAGING

- CASE: Void-free transfer molded thermosetting epoxy compound meeting UL94V-0.
- TERMINALS: Tin/lead or RoHS compliant annealed matte-tin over copper. Readily solderable per MIL-STD-750, method 2026.
- MARKING: P01• (dot indicates "e3" designation).
- POLARITY: Cathode connected to TAB 2.
- TAPE & REEL option: 16 mm tape per standard EIA-481-B. Consult factory for quantities.
- WEIGHT: Approximately 0.016 gram.
- See <u>Package Dimensions</u> on last page.

PART NOMENCLATURE




SYMBOLS & DEFINITIONS							
Symbol	Definition						
f	Frequency						
I _R	Reverse current						
١ _F	Forward current						

ELECTRICAL CHARACTERISTICS @ T_A = +25^oC unless otherwise noted

$\begin{array}{c} \text{SERIES} \\ \text{RESISTANCE} \\ \text{R}_{\text{S}} \\ @ \text{ f} = 100 \\ \text{ MHz} \\ \text{I}_{\text{F}} = 50 \text{ mA} \end{array}$		CAPACITANCE C _T @ f = 100 MHz V _R = 0 V		PARALLEL RESISTANCE R _P @ f = 100 MHz V = 0 V		CARRIER LIFETIME τ @ I _F = 10 mA		TRANSMIT HARMONIC DISTORTION @ Pin = 50 W f = 50 MHz I _F = 50 mA	RECEIVE 3^{rd} ORDER HARMONIC DISTORTION @ f = 100 MHz V = 0 V f ₁ = 50 MHz f ₂ = 51 MHz	VOLTAGE RATING V _R @ I _R = 10 μA	FORWARD VOLTAGE V _F @ I _F = 50 mA
Ohr	Ohms			Ohms		μS		-dB	-dB	Volts	Volts
TYP	MAX	TYP	МАХ	MIN	TYP	MIN	TYP	MIN	MIN	MIN	МАХ
0.75	1.0	0.75	1.0	5K	10K	1.0	2.0	80	60	50	1.0



PACKAGE and MOUNTING PAD DIMENSIONS



DIMENSIONS in inches