# imall

Chipsmall Limited consists of a professional team with an average of over 10 year of expertise in the distribution of electronic components. Based in Hongkong, we have already established firm and mutual-benefit business relationships with customers from, Europe, America and south Asia, supplying obsolete and hard-to-find components to meet their specific needs.

With the principle of "Quality Parts, Customers Priority, Honest Operation, and Considerate Service", our business mainly focus on the distribution of electronic components. Line cards we deal with include Microchip, ALPS, ROHM, Xilinx, Pulse, ON, Everlight and Freescale. Main products comprise IC, Modules, Potentiometer, IC Socket, Relay, Connector. Our parts cover such applications as commercial, industrial, and automotives areas.

We are looking forward to setting up business relationship with you and hope to provide you with the best service and solution. Let us make a better world for our industry!



## Contact us

Tel: +86-755-8981 8866 Fax: +86-755-8427 6832 Email & Skype: info@chipsmall.com Web: www.chipsmall.com Address: A1208, Overseas Decoration Building, #122 Zhenhua RD., Futian, Shenzhen, China



Preliminary data

Symbol

l<sub>dAV</sub>

davm

I<sub>FSM</sub>

V <sub>RSM</sub>	V <sub>RRM</sub>	Туре
$V_{\text{DSM}}$	$V_{\text{DRM}}$	
V	V	
1200	1200	VUO 18-12DT8
1400	1600	VUO 18-14DT8
1600	1800	VUO 18-16DT8

Conditions


 $V_R = 0$ 

 $T_c = 85^{\circ}C$ , module

 $T_c = 63^{\circ}C$ , module

 $T_{VJ} = 45^{\circ}C;$  t = 10 ms

t = 8.3 ms



**Maximum Ratings** 

14

18

300

330

A

A


А

А



**VUO 18** 

*BI* 



Features

- Package with 1/4" fast-on terminals
- Isolation voltage 3000 V~
- Planar passivated chips
- Blocking voltage up to 1600 V
- Low forward voltage drop
- UL registered E 72873


#### Applications

- Supplies for DC power equipment
- Input rectifiers for PWM inverter
- Battery DC power supplies
- Field supply for DC motors

#### Advantages

- Easy to mount with one screw
- · Space and weight savings
- Improved temperature & power cycling
- Up to 10 dB lower EMI/RFI compared to standard rectifier

#### Dimensions in mm (1 mm = 0.0394")



	$T_{V,I} = T_{V,IM};$	t = 10 ms	(50 Hz)	270	А		
	$V_{R} = 0$	t = 8.3 ms	(60 Hz)	300	Α		
l²t	T <sub>vJ</sub> = 45°C;	t = 10 ms	(50 Hz)	450	A <sup>2</sup> s		
	$V_R = 0$	t = 8.3 ms	(60 Hz)	460	A <sup>2</sup> s		
	$T_{VJ} = T_{VJM};$	t = 10 ms	(50 Hz)	365	A <sup>2</sup> s		
	$V_R = 0$	t = 8.3 ms	(60 Hz)	380	A <sup>2</sup> s		
T <sub>vj</sub>				-40+150	°C		
T <sub>VJM</sub>				150	°C		
T <sub>stg</sub>				-40+150	°C		
VISOL	50/60 Hz, RI	MS t=1 mi	in	2500	V~		
	$I_{\rm ISOL} \le 1 \ {\rm mA}$	t = 1 s		3000	V~		
M <sub>d</sub>	Mounting tor	que (M5)		2 ±10%	Nm		
		(10-32	UNF)	18 ±10%	lb.in.		
Weight	Тур.			22	g		
Symbol	Conditions			Characteristic Va	Characteristic Values		
I <sub>R</sub>	$V_{R} = V_{RRM}$	$T_{VJ} = 25^{\circ}C$		0.3	mA		
		$T_{VJ} = T_{VJM}$		5.0	mA		
V <sub>F</sub>	I <sub>F</sub> = 55 A	$T_{VJ} = 25^{\circ}C$		1.85	V		
V <sub>T0</sub>	For power-lo	ss calculation	ns only	1.2	V		

(50 Hz)

(60 Hz)

V <sub>T0</sub>	For power-loss calculations only	1.2	V
r <sub>t</sub>		16	mΩ
t <sub>rr</sub>	$I_{c} = 10 \text{ A}$ $T_{vJ} = 25^{\circ}\text{C}$ -di/dt = 10 A/µs, $V_{R} = \frac{1}{2} V_{RRM}$	1.5	μs
R <sub>thJC</sub>	per diode; 120° el.	9.30	K/W
	per module	1.55	K/W
$\mathbf{R}_{thCH}$	per diode; 120° el.	10.20	K/W
	per module	1.70	K/W
ds	Creeping distance on surface	12.7	mm
dĂ	Creepage distance in air	9.4	mm
a	Max. allowable acceleration	50	m/s²

Data according to IEC 60747 and refer to a single diode unless otherwise stated.

IXYS reserves the right to change limits, test conditions and dimensions.

© IXYS All rights reserved

### 1 - 1