



Chipsmall Limited consists of a professional team with an average of over 10 year of expertise in the distribution of electronic components. Based in Hongkong, we have already established firm and mutual-benefit business relationships with customers from,Europe,America and south Asia,supplying obsolete and hard-to-find components to meet their specific needs.

With the principle of "Quality Parts,Customers Priority,Honest Operation,and Considerate Service",our business mainly focus on the distribution of electronic components. Line cards we deal with include Microchip,ALPS,ROHM,Xilinx,Pulse,ON,Everlight and Freescale. Main products comprise IC,Modules,Potentiometer,IC Socket,Relay,Connector.Our parts cover such applications as commercial,industrial, and automotives areas.

We are looking forward to setting up business relationship with you and hope to provide you with the best service and solution. Let us make a better world for our industry!



Contact us


Tel: +86-755-8981 8866 Fax: +86-755-8427 6832

Email & Skype: info@chipsmall.com Web: www.chipsmall.com

Address: A1208, Overseas Decoration Building, #122 Zhenhua RD., Futian, Shenzhen, China



Engineered for Efficient Design and Debug 200 MHz – 1 GHz



Key Specifications

Bandwidth	200 MHz, 400 MHz, 600 MHz, 1 GHz
Channels	2, 4, or 4 + 18
Memory	16 Mpts/Ch, 32 Mpts interleaved
Sample Rate	up to 10 GS/s
Connectivity	USB, LAN, GPIB


- **Speed and Performance** — 10 GS/s and 32 Mpts with a responsive user interface and fast updating math and measurement tools
- **WaveScan** — quickly search analog or digital waveforms for runts, glitches or other anomalies
- **Touch Screen** — easily configure Channels, time base, trigger and all functions with the intuitive, efficient touch screen interface
- **Embedded System Test Tools** — powerful MSO capabilities plus a wide range of serial data trigger and decode capabilities
- **LabNotebook™** — quickly save all results plus flashback to previous tests and create custom reports

For more information, please contact:






Use WaveScan to search for and identify anomalies on analog or digital signals.



View and measure analog, digital and serial data signals in one place.



Easily control all aspects of the WaveSurfer with the intuitive touch screen interface.



Ordering Information

Model	Bandwidth	Channels	Memory (Per Ch/Interleaved)	Sample Rate (Per Ch / Interleaved)
WaveSurfer 24MXs-B	200 MHz	4	16 Mpts / 32 Mpts	2.5 GS/s
WaveSurfer 42MXs-B	400 MHz	2	16 Mpts / 32 Mpts	5 GS/s
WaveSurfer 44MXs-B	400 MHz	4	16 Mpts / 32 Mpts	5 GS/s
MSO 44MXs-B	400 MHz	4 + 18	16 Mpts / 32 Mpts	5 GS/s
WaveSurfer 62MXs-B	600 MHz	2	16 Mpts / 32 Mpts	5 GS/s / 10 GS/s
WaveSurfer 64MXs-B	600 MHz	4	16 Mpts / 32 Mpts	5 GS/s / 10 GS/s
MSO 64MXs-B	600 MHz	4 + 18	16 Mpts / 32 Mpts	5 GS/s / 10 GS/s
WaveSurfer 104MXs-B	1 GHz	4	16 Mpts / 32 Mpts	5 GS/s / 10 GS/s
MSO 104MXs-B	1 GHz	4 + 18	16 Mpts / 32 Mpts	5 GS/s / 10 GS/s

Available Probes

Single-Ended

ZS1500	1.5 GHz, 0.9 pF, 1 M Ω High Impedance Active Probe
ZS1000	1 GHz, 0.9 pF, 1 M Ω High Impedance Active Probe

Differential

ADP300	1,400 V, 20 MHz High-Voltage Differential Probe
ADP305	1,400 V, 100 MHz High-Voltage Differential Probe
ZD200	200 MHz Active Differential Probe
ZD500	500 MHz Active Differential Probe
ZD1000	1 GHz Active Differential Probe
ZD1500	1.5 GHz Active Differential Probe

Differential Amplifiers

DA185A	1 Ch, 100 MHz Differential Amplifier
---------------	--------------------------------------

High-Voltage

PPE1.2KV	10:1/100:1 200/300 MHz 50 M Ω High-Voltage Probe 600V/1.2kV Max. Volt. DC
PPE2KV	100:1 400 MHz 50 M Ω 2 kV High-Voltage Probe
PPE4KV	100:1 400 MHz 50 M Ω 4kV High-Voltage Probe
PPE5KV	1000:1 400 MHz 50 M Ω 5 kV High-Voltage Probe
PPE6KV	1000:1 400 MHz 50 M Ω 6 kV High-Voltage Probe
PPE20KV	1000:1 100 MHz 50 M Ω High-Voltage Probe 20kV Max. Volt. DC + 40kV Peak AC

Current

AP015	30 A; 50 MHz Current Probe – AC/DC; 30 A _{rms} ; 50 A _{peak} Pulse
CP030	30 A; 50 MHz Current Probe – AC/DC; 30 A _{rms} ; 50 A _{peak} Pulse
CP031	30 A; 100 MHz Current Probe – AC/DC; 30 A _{rms} ; 50 A _{peak} Pulse
CP150	150 A; 10 MHz Current Probe – AC/DC; 150 A _{rms} ; 50 A _{peak} Pulse
CP500	500 A; 2 MHz Current Probe – AC/DC; 500 A _{rms} ; 700 A _{peak} Pulse

Excellent Performance

- 200 MHz, 400 MHz, 600 MHz and 1 GHz bandwidths
- 10 GS/s maximum sample rate
- 16 Mpts/Ch, 32 Mpts interleaved

Rich Feature Set

- WaveStream™ fast update mode
- WaveScan™ search and find
- LabNotebook™ documentation and report generator

Wide Range of Serial Data Tools

- I²C, SPI, UART
- CAN, LIN, FlexRay™
- USB 1.0/1.1/2.0, USB 2.0 HSIC
- Audio (I²S, LJ, RJ, TDM)
- MIL-STD-1553, ARINC 429
- MIPI D-PHY, DigRF 3G, DigRF v4