



Chipsmall Limited consists of a professional team with an average of over 10 year of expertise in the distribution of electronic components. Based in Hongkong, we have already established firm and mutual-benefit business relationships with customers from,Europe,America and south Asia,supplying obsolete and hard-to-find components to meet their specific needs.

With the principle of “Quality Parts,Customers Priority,Honest Operation,and Considerate Service”,our business mainly focus on the distribution of electronic components. Line cards we deal with include Microchip,ALPS,ROHM,Xilinx,Pulse,ON,Everlight and Freescale. Main products comprise IC,Modules,Potentiometer,IC Socket,Relay,Connector.Our parts cover such applications as commercial,industrial, and automotives areas.

We are looking forward to setting up business relationship with you and hope to provide you with the best service and solution. Let us make a better world for our industry!



Contact us

Tel: +86-755-8981 8866 Fax: +86-755-8427 6832

Email & Skype: info@chipsmall.com Web: www.chipsmall.com

Address: A1208, Overseas Decoration Building, #122 Zhenhua RD., Futian, Shenzhen, China





Basic Whisker.BlockXD™

General Description

Whisker.BlocksXD™ are battery powered, long range wireless devices that can monitor the world around them from as much as 1 mile away or more. They are designed to be extremely flexible and can easily be configured to meet exacting requirements.

The Basic **Whisker.BlockXD™** is configured with an internal temperature sensor and two external digital inputs. The sample period for these inputs can be set by the user from 5 minutes to every 24 hours.

Power

The Basic **Whisker.BlockXD™** is powered from a field replaceable internal battery pack which will last 5+ years with a 5-minute sample period. This block can optionally be configured with a long-life battery pack capable of extending operate to 15+ years.

Antenna

The **Whisker.BlockXD™** can be configured for an internal or external antenna. External antennas are connected via an RPSMA connector, allowing the customer to select the antenna that is appropriate for the application.

It is important to select the proper antenna for the application. Generally, smaller or less expensive antennas will exhibit lower performance and therefore less transmission range.

Digital Six Labs offers a variety of antennas that are compatible with **Whisker.BlockXD™**:

Part Number	Size	Cost	Range
INTERNAL	Smallest	Lowest	Good
TQX-900-A (AI)	Small	Good	Better
TQX-900-E	Larger	Higher	Best

Internal Channels

As stated earlier, the Basic **Whisker.BlockXD™** is configured to monitor three channels: internal temperature and two external digital inputs.

The internal temperature sensor is accurate to within +/- 3°C.

Up to two dry contacts can be monitored using the two digital inputs. These can be connected to the **Whisker.BlockXD™** using a 4-conductor cable.

External Connections

External connection is made via a 4-conductor cable.

Color	Description
Black	GND
Yellow	DIN1
Brown	DIN2
Red	NA



Mechanical



Electrical Specification

Parameter	Minimum	Typical	Maximum	Units
Battery life – Standard Pack		5		Year
Battery life – Extended Pack		15		
Operating Temp. Range (standard pack)	-20	25	40	°C
Operating Temp. Range (extended pack)	-40	25	60	°C
Transmission range		1	20	Miles ¹
Temperature measurement range	-40		80	°C
Temperature measurement accuracy	-3		+3	°C
Maximum periodic sample rate	-	-	24	Hours/sample
Minimum periodic sample rate	5	-	-	Minutes/sample

Order Information

Part Number	Description
XB-900-0000-IS	902-928MHz Basic Whisker.BlockXD with internal antenna and standard battery pack
XB-900-0000-IE	902-928MHz Basic Whisker.BlockXD with internal antenna and extended battery pack
XB-900-0000-ES	902-928MHz Basic Whisker.BlockXD with external antenna and standard battery pack
XB-900-0000-EE	902-928MHz Basic Whisker.BlockXD with external antenna and extended battery pack
XB-868-0000-IS	868MHz Basic Whisker.BlockXD with internal antenna and standard battery pack
XB-868-0000-IE	868MHz Basic Whisker.BlockXD with internal antenna and extended battery pack
XB-868-0000-ES	868MHz Basic Whisker.BlockXD with external antenna and standard battery pack
XB-868-0000-EE	868MHz Basic Whisker.BlockXD with external antenna and extended battery pack

