imall

Chipsmall Limited consists of a professional team with an average of over 10 year of expertise in the distribution of electronic components. Based in Hongkong, we have already established firm and mutual-benefit business relationships with customers from, Europe, America and south Asia, supplying obsolete and hard-to-find components to meet their specific needs.

With the principle of "Quality Parts, Customers Priority, Honest Operation, and Considerate Service", our business mainly focus on the distribution of electronic components. Line cards we deal with include Microchip, ALPS, ROHM, Xilinx, Pulse, ON, Everlight and Freescale. Main products comprise IC, Modules, Potentiometer, IC Socket, Relay, Connector. Our parts cover such applications as commercial, industrial, and automotives areas.

We are looking forward to setting up business relationship with you and hope to provide you with the best service and solution. Let us make a better world for our industry!




Contact us

Tel: +86-755-8981 8866 Fax: +86-755-8427 6832 Email & Skype: info@chipsmall.com Web: www.chipsmall.com Address: A1208, Overseas Decoration Building, #122 Zhenhua RD., Futian, Shenzhen, China



Multilayer Ferrite Chip Beads Standard Type (Z-SMS Series) KPN: Z0201C601ASMST






Exterr	nal Dimensions
L	0.6 ±0.03 mm
W	0.3 ±0.03 mm
Т	0.3 ±0.03 mm
е	0.15 ±0.05 mm

Products Characteristics Table	
Case Size (EIA/JIS)	0201/0603
Impedance	600Ω
Impedance Measuring Frequency	100MHz
Rated Current	150mA
DC Resistance (max)	1.2Ω
Temperature Range	-55 to +125 °C
RoHS Compliance	Yes
Halogen Free	Yes
Soldering Method	Reflow

Features	
-Item Summary	
600Ω, 150mA, 0201	
-Lifecycle Stage	
Mass Production	
-Standard packaging quantity (minimum)	
Taping 15,000pcs	





Statements of suitability for certain applications are based on our knowledge of typical operating conditions for such applications, but are not intended to constitute and we specifically disclaim - any warranty concerning suitability for a specific customer application or use. This Information is intended for use only by customers who have the requisite experience and capability to determine the correct products for their application. Any technical advice inferred from this Information or otherwise provided by us with reference to the use of our products is given gratis, and we assume no obligation or liability for the advice given or results obtained.